
1. Antenna Description:

Antenna type	PIFA antenna					
Model	M24D-M616A-S-M					
Manufacturer	Signalinks Communication Technology Co.,Ltd					

2. Antenna Photo:



3. Test data

	Efficienc y / dB	MaxGain /dBi	Efficienc y / %	Frequency/Mhz	Efficiency / dB	MaxGain/ dBi	Efficiency / %	Frequency/Mhz	Efficiency /	MaxGain/d Bi	Efficiency
700	-9.13	-1.95	12.22	170	0 -5.19	0.99	30.27	2220	-5.39	-0.9	28.9
710	-8.66	-1.7	13.61	172	-5.08	0.72	31.05	2240			29.0
720	-9.47	-2.69		174	0 -4.82	0.87	32.96	2260			28.
730				176	0 -4.62	0.75	34.51	2280			27.9
740	-8.33			178	0 -4.62	0.43	34.51	2300			27.3
750				180	0 -4.7	0.38	33.88				
760				182	0 -4.8	0.52	33.04	2320			27.4
770	-5.88	-0.46	25.82	184	0 -4.66	0.8	34.2	2340			26.9
780				186	0 -4.7	0.69	33.81	2360	-5.36	0.37	29.
790	-5.26			188	0 -4.88	-0.01	32.51	2380	-5.38	0.08	28.9
800				190	0 -4.98	-0.82	31.77	2400	-5.67	-0.17	27
810	-5.75	-0.93	26.61	192	0 -4.90	-0.65	31.7	2420	-5.83	-0.9	26.
820	-5.37	-0.42	29.04	194	0 -5.12	-1.18	30.76	2440	-5.84	-0.93	26.
830	-5.7	-0.76	26.92	196	0 -4.94	-1	32.06	2460	-5.89	-0.93	25.
840	-5.4			198	0 -4.96	-0.86	31.92	2480	-5.61	-0.28	27.4
850				200	0 -5.14	-1.1	30.62	2500			27
860	-5.1	-0.54		202	0 -5.1	-0.98	30.83	2520			27.
870	-5.37	-0.97		204	0 -5.04	-0.62	31.33				27.0
880				206	-5.0	-0.68	31.55	2540			
890	-5.75			208	0 -4.79	-0.35	33.19	2560			26.0
900	-5.85			210	0 -4.96	-0.35	31.92	2580			
910				212	0 -4.84	-0.25	32.81	2600	-5.87	0.59	
920				214	0 -4.86	-0.58	32.66	2620	-6.15	0.2	24.
930	-6		_	216	0 -4.9	-0.78	31.84	2640	-6.21	0.57	23.9
940	-6.31	-1.45		218	-5.14	-0.7	30.62	2660	-6.49	0.59	22.4
950	-6.58			220	0 -5.28	-0.81	29.65	2680	-6.81	0.49	20.
960	-7.32	-2.91	18.54					2700	-7.16	0.28	19.:

We statement that All measurements were performed radiated and therefore additional antenna gain documentation is not required.