

Dog Training Collar





Please Read The Manual Before Use



Key Definition

1. Antenna: transmit the signal strongly
2. LED light : Press (10) to light it, press (10) again to be off.
3. LCD screen :Show the modes ,levels and channels
4. Shock button :Shock button: the screen being on, press to choose Shock mode, press or-button to adjust the levels from 0--99, press Shock button again to Make the Receiver shock
5. Vibration button :the screen being on, press to choose Vibration mode, press+or-button to adjust the levels from 0--99,press Shock button again to make the Receiver vibrate.
6. Sound button : press to choose Sound mode, don't need to adjust the levels,just press to make the receiver sound Bee~
7. button: press - to reduce the levels.
8. button: press + to increase the levels.
9. Channel button :choose your training channelamong Ch1/CH2 /Ch3 by press this button.
10. Light button : Pressing to light the LED of the Remote,press again the LED will be off; Ifyou press this button for 2 seconds, the white LED on the Receiver will be on, pressing2 seconds again,the White LED will be off, if you don't press it again ,the White LED will be off automatically after 10 seconds.
11. charging :hole of the Remote.
12. Power button: press to turn on the Receiver , press again to turn it off
13. Charging: hole of the Receiver.
14. Contact points: to install the rubber cap, reach to pet's skin . Conduct the safe statics.
15. Indicator light : the light will flash when we press the shock/vibration /sound button; when charging, it's on.



Pair the Remote With Receiver


1. Press the shock button or vibration button to turn on the Remote
2. Choose a channel CH1 or CH2 or CH3 by pressing the CH button
3. Adjust the level by pressing + or - button , make sure the level above 01
4. Press the Power button ofthe Receiver for 3 seconds , you will hear a sound like Bee~,and the indicator light is flashing; Then quickly, Press the vibration button or Shock button within 10 seconds after the sound Bee~,you can hear a sound Bee~again ,which means the pairingsuccessfully.
5. If you have 2 or 3 Receivers just choose the different channers ,and pair as the above steps.

Note:

please rememberthe channel you have chose to pair , if you use another channel without pair , you can't control the Receiver.

Test the training collar set (After paired successfully)

1. Test the Shock function
Take out the test bulb and put it on the Receiver's contact point Press the Shock button (make sure the level above 01)
The test bulb will be on
2. Test the Vibration function
Press the Vibration button
(make sure the level above 01)The Receiver will vibrate
3. Test the Sound function
Press the Sound button
(don't need to adjust the level)The Receiver will sound bi~bi~



- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.