

HY-254101 PCB IFA antenna module:

(1).藍牙核心版本 (Bluetooth Core Version : V4.0)

(2).核心配置 (Core Configuration) : LE

(3).RF輸出功率(RF Output Power) Low energy Bluetooth : 0 dBm

(4).天線增益(Antenna Gain) : 2.813dBi at 2440MHz

Synthesizer : Set Frequency	Gain dBi	Efficiency (%)	Efficiency (dB)
2400	2.469	45.44%	-3.425
2402	2.591	46.44%	-3.331
2404	2.556	45.97%	-3.375
2406	2.905	46.85%	-3.293
2408	2.818	45.69%	-3.401
2410	2.686	44.24%	-3.542
2412	2.768	44.83%	-3.484
2414	2.772	45.06%	-3.462
2416	2.968	46.52%	-3.324
2418	2.997	46.61%	-3.315
2420	2.902	45.53%	-3.417
2422	2.869	45.35%	-3.434
2424	2.983	46.24%	-3.349
2426	3.137	47.18%	-3.262
2428	3.038	46.52%	-3.324
2430	3.062	46.46%	-3.330
2432	2.981	45.77%	-3.394
2434	3.007	46.46%	-3.329
2436	3.073	47.50%	-3.233
2438	2.944	46.23%	-3.351
2440	2.813	45.11%	-3.457
2442	2.885	45.81%	-3.391
2444	2.864	45.19%	-3.449
2446	2.605	43.92%	-3.574
2448	2.735	45.24%	-3.445
2450	2.782	45.27%	-3.442
2452	2.767	45.06%	-3.462
2454	2.804	44.98%	-3.470
2456	2.984	44.43%	-3.523
2458	3.079	45.54%	-3.416
2460	3.160	46.87%	-3.291
2462	3.142	46.03%	-3.370
2464	3.161	46.01%	-3.371
2466	3.426	47.81%	-3.204
2468	3.316	46.07%	-3.366
2470	3.347	46.56%	-3.320
2472	3.250	46.15%	-3.358
2474	3.053	43.30%	-3.635
2476	2.719	42.85%	-3.681
2478	2.928	44.98%	-3.470
2480	2.986	45.84%	-3.387
2482	3.012	46.89%	-3.289
2483.5	3.086	47.15%	-3.265



