








## LABEL AND LOCATION

<p>Model: Singo 3000 Capacity: 2048Wh, 51.2V, 40Ah Max Total Output Power: 3580W USB-A Output (x1): 5V=2.4A, 12W USB-A QC Output (x2): 5V/3A, 9V/2A, 12V/1.5A, 18W each port, Total: 36W USB-C PD Output (x2): (5V/9V/12V)=3A, 20V=5A, 100W each port, Total: 200W AC Output (x4): 120Vac/60Hz, Total: 3200W DC Output: 13.2V=10A, DC Power socket/5525 (x2) Total: 132W AC Charge Input: 90~140Vac, 60Hz, 1800Wmax PV Charge Input: 12~80Vdc, 16Amax, 1000Wmax DC Charge Input: 12Vdc/8A, 24Vdc/10A, 240Wmax Discharge Temperature: -15 ~ 40°C (5 ~ 104°F) Charge Temperature: 0 ~ 40°C (32 ~ 104°F) FCC ID: 2BK4Q-SINGO3000</p> <div></div>	<p><b>WARNING</b></p> <ol style="list-style-type: none"><li>1. Please refer to local laws and regulations for disposal.</li><li>2. Do not disassemble, puncture, shock or burn the subject.</li><li>3. Do not overcharge the internal battery. See instruction manual.</li><li>4. Do not smoke, strike a match, or cause a spark in the vicinity of the power pack.</li><li>5. Only charge the internal battery in a well ventilated area.</li></ol> <p><b>CAUTION</b></p> <ol style="list-style-type: none"><li>1. Risk of Electric Shock. Do not remove cover. No user serviceable parts inside. Refer servicing to qualified service personnel.</li><li>2. Risk of injury to people. Do not use this product if the power cord or the battery cables are damaged in any way.</li><li>3. This device is not intended for use in a commercial repair facility.</li><li>4. This device is intended to be used indoors only. Do not use outdoors.</li></ol>
--	--

Material: tagboard

Gule: adhesive sticker

Font color: white

Label color: silver polyester

(Size: L: 13.6cm x W: 7.0cm)



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Building A and 301 Building C, Juji Industrial Park, Yabianxueziwei Shajing Street, Baoan District, Shenzhen, 518000, P.R.C.

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity