



Appendix A

RF Test Data for BLE 2M (Conducted Measurement)

Product Name: LED string lights

Test Model: HB-1000COI

Environmental Conditions

Temperature:	23.9° C
Relative Humidity:	52.2%
ATM Pressure:	100.0 kPa
Test Engineer:	Jay Luo
Supervised by:	Nick Peng



Shenzhen LCS Compliance Testing Laboratory Ltd.
Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China
Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com
Scan code to check authenticity



A.1 -6dB Bandwidth


Condition	Mode	Frequency (MHz)	Antenna	-6 dB Bandwidth (MHz)	Limit -6 dB Bandwidth (MHz)	Verdict
NVNT	BLE 2M	2402	Ant1	0.653	≥ 0.5	Pass
NVNT	BLE 2M	2440	Ant1	0.66	≥ 0.5	Pass
NVNT	BLE 2M	2480	Ant1	0.664	≥ 0.5	Pass






Test Graphs

-6dB Bandwidth NVNT BLE 2M 2402MHz Ant1



-6dB Bandwidth NVNT BLE 2M 2440MHz Ant1




Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity





A.2 Maximum Peak Conducted Output Power

Condition	Mode	Frequency (MHz)	Antenna	Conducted Power (dBm)	Limit (dBm)	Verdict
NVNT	BLE 2M	2402	Ant1	-0.13	30	Pass
NVNT	BLE 2M	2440	Ant1	-0.42	30	Pass
NVNT	BLE 2M	2480	Ant1	0.45	30	Pass




Shenzhen LCS Compliance Testing Laboratory Ltd.
Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China
Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com
Scan code to check authenticity





Test Graphs

Power NVNT BLE 2M 2402MHz Ant1



Power NVNT BLE 2M 2440MHz Ant1







A.3 Maximum Power Spectral Density Level

Condition	Mode	Frequency (MHz)	Antenna	Conducted PSD (dBm/3kHz)	Limit (dBm/3kHz)	Verdict
NVNT	BLE 2M	2402	Ant1	-16.48	8	Pass
NVNT	BLE 2M	2440	Ant1	-17.19	8	Pass
NVNT	BLE 2M	2480	Ant1	-16.07	8	Pass




Shenzhen LCS Compliance Testing Laboratory Ltd.
Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China
Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com
Scan code to check authenticity





Test Graphs

PSD NVNT BLE 2M 2402MHz Ant1



PSD NVNT BLE 2M 2440MHz Ant1







A.4 Band Edge

Condition	Mode	Frequency (MHz)	Antenna	Max Value (dBc)	Limit (dBc)	Verdict
NVNT	BLE 2M	2402	Ant1	-55.7	-20	Pass
NVNT	BLE 2M	2480	Ant1	-54.92	-20	Pass




Shenzhen LCS Compliance Testing Laboratory Ltd.
Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China
Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com
Scan code to check authenticity




Test Graphs

Band Edge NVNT BLE 2M 2402MHz Ant1 Ref



Band Edge NVNT BLE 2M 2402MHz Ant1 Emission





Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity





A.5 Conducted RF Spurious Emission

Condition	Mode	Frequency (MHz)	Antenna	Max Value (dBc)	Limit (dBc)	Verdict
NVNT	BLE 2M	2402	Ant1	-53.59	-20	Pass
NVNT	BLE 2M	2440	Ant1	-52.69	-20	Pass
NVNT	BLE 2M	2480	Ant1	-53.77	-20	Pass




Shenzhen LCS Compliance Testing Laboratory Ltd.
Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China
Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com
Scan code to check authenticity




Test Graphs

Tx. Spurious NVNT BLE 2M 2402MHz Ant1 Ref




Tx. Spurious NVNT BLE 2M 2402MHz Ant1 Emission






Tx. Spurious NVNT BLE 2M 2440MHz Ant1 Ref



Tx. Spurious NVNT BLE 2M 2440MHz Ant1 Emission



Shenzhen LCS Compliance Testing Laboratory Ltd.


Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com


Scan code to check authenticity



Tx. Spurious NVNT BLE 2M 2480MHz Ant1 Ref



Tx. Spurious NVNT BLE 2M 2480MHz Ant1 Emission





A.6 Duty Cycle


Condition	Mode	Frequency (MHz)	Antenna	Duty Cycle (%)	Correction Factor (dB)	1/T (kHz)
NVNT	BLE 2M	2402	Ant1	87.39	0.59	0.61
NVNT	BLE 2M	2440	Ant1	87.36	0.59	0.61
NVNT	BLE 2M	2480	Ant1	87.36	0.59	0.61







Test Graphs

Duty Cycle NVNT BLE 2M 2402MHz Ant1



Duty Cycle NVNT BLE 2M 2440MHz Ant1







A.7 Restrict Band


Condition	Mode	Frequency (MHz)	Antenna	Spur Freq (MHz)	Power (dBm)	Gain (dBi)	Duty Factor (dB)	E (dBuV/m)	Detector	Limit (dBuV/m)	Verdict
NVNT	BLE 2M	2402	Ant1	2310	-49.01	2	-	48.25	Peak	74	Pass
NVNT	BLE 2M	2402	Ant1	2310	-57.88	2	0.59	39.97	Average	54	Pass
NVNT	BLE 2M	2402	Ant1	2355.792	-46.23	2	-	51.03	Peak	74	Pass
NVNT	BLE 2M	2402	Ant1	2381.52	-56.55	2	0.59	41.3	Average	54	Pass
NVNT	BLE 2M	2402	Ant1	2390	-49.78	2	-	47.48	Peak	74	Pass
NVNT	BLE 2M	2402	Ant1	2390	-57.77	2	0.59	40.08	Average	54	Pass
NVNT	BLE 2M	2480	Ant1	2483.5	-49.08	2	-	48.18	Peak	74	Pass
NVNT	BLE 2M	2480	Ant1	2483.5	-56.76	2	0.59	41.09	Average	54	Pass
NVNT	BLE 2M	2480	Ant1	2487.952	-44.57	2	-	52.69	Peak	74	Pass
NVNT	BLE 2M	2480	Ant1	2490.04	-56.09	2	0.59	41.76	Average	54	Pass
NVNT	BLE 2M	2480	Ant1	2500	-48.62	2	-	48.64	Peak	74	Pass
NVNT	BLE 2M	2480	Ant1	2500	-57.08	2	0.59	40.77	Average	54	Pass






Test Graphs

Restrict Band NVNT BLE 2M 2402MHz Ant1 Peak



Restrict Band NVNT BLE 2M 2402MHz Ant1 Average



Shenzhen LCS Compliance Testing Laboratory Ltd.


Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com


Scan code to check authenticity



Restrict Band NVNT BLE 2M 2480MHz Ant1 Peak



Restrict Band NVNT BLE 2M 2480MHz Ant1 Average



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity