

LABEL AND LOCATION

LiFePO4

Lithium Iron Phosphate Battery

Bluetooth

DYNES

LFP 12.8V 100Ah 1280Wh

Product Parameters Information

- Model: ARL12-BT
- Nominal Volt: 12.8V
- Nominal Capacity: 100Ah
- Nominal Energy: 1280Wh
- Max.Cont. Discharge/Charge Current:100A(IC)
- Max. Charge Volt: 14.6V
- Recommended Charge Current: 20A(0.2C)
- FCC ID: 2BPRZ-12V100

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions:
(1) This device may not cause harmful interference
(2) This device must accept any interference received, including interference that may cause undesired operation.

WARNING: RISK OF FIRE, EXPLOSION, or BURN

Do not short circuit the(+) and (-) terminals with any metals
Do not immerse, throw and wet battery in water
Do not heat above 60°C or throw battery into fire
Do not disassemble, crush, or modify the battery
Do not reverse the (+) and (-) terminals
Stopping using the battery under the conditions: abnormal heat, odor, deformation
Elevation: no more than 4000m

Web: www.dynesspower.com

Tel: +86 400 666 0655

Email: dynesscare@dyness-tech.com

Dyness Digital Energy Technology Co., LTD.

