

Thank you for purchasing Jabees BTwins Bluetooth True Wireless Stereo Headphones. This manual will help you to accurately operate BTwins, but you should familiarize yourself with the Bluetooth function of your mobile phone or other devices before using the Bluetooth headphones BTwins.

CHARGING THE CAT FEW

STWins come with the charging contact points on the headphones body and the Power Pouch for storage and charging.

2. Pet the filt was not be charging slots of the Power Pouch individually.


2. Pet the filt was not be charging slots of the Power Pouch individually.

3. The red indicator light will be on when charging.

4. When the battery is fully charged, the red LED light turns off.

(i.i. ... i.i)





The Power Pouch is with built-in 450mAh battery capacity, it provides almost 4 additional charges for 2 earbuds. The LED Indicators of Battery Capacity on the Power Pack shows the remaining battery capacity. Please charge the Power Pouch when it is running out of

power.

J. Pilig one end of the USB charging cable into the charging port of the Power Pouch, and put the other end into your computer or AC charger with USB port.

Z. When the Power Pouch is fully charged, 4 LED Indicators of Battery Capacity will be turned on in solid blue.

D Indicators of I	Settery Cape	city (During 0	tharging the f	larbods & Being (
Sattery Especity	LED 1	LED 2	LED 3	LED 4
0.25%	Rashing	OF	Off.	Off
25%-50%	Ωs	Flashing	Off	011
50% 75%	01	On	Flashing	Off
75%-99%	On	On	On	Rashing
99%-100%	0+	On	On	Os.

You will hear the voice prompt "Battery Low". At this time, please charge up BTwins.




For the first use, please make sure to fully charge the BTwins beforehand.
 You must recharge BTwins if it has been not used for more than 12 months.
 You must use the authorized charger to charge up BTwins.

Answering/Ending/Rejecting/Redialing/Transferring calls; Playing/Pausing the Music: Language Selection; Factory Reset; Pairing.

TURNING THE HEADPHONES ON/OFF
To turn on BTwins:
Press and hold the MF Button for about 3.5 seconds to turn on BTwins.

## To turn off BTwins: Press and hold the MF Button for about 4 seconds to turn off BTwins.

NOTE:
When the 2 headphones are in in-sync mode, if you turn off one headphone, the another connected headphone will be turned off automatically along with the Voice Prompt 'Power



1) Press and note the MP dutton for about 3.5 sections or two earbuss, the LED lights flash in red, then, 2 earbuds are turned on and connected automatically.
2) The LED lights of main earbuds (left channel) flash in red &blue, then, it turns into pairing mode with mobile phone.



connection.

2) If your phone asks for passkey or PIN-code, confirm with '0000' (4-zero).

3) When the mobile phone and the Left Channel of BTwins are connected, the Right Channel of BTwins will be connected with them automatically.

# NOTE: 1) When BTwins are in in-sync mode, they doesn't support Multipoint for 2 phones connection. That means you can only pair and connect BTwins with 1 mobile phone if

connection. That means you can only pair and connect \$\tilde{\text{Wint}}\$ with \$1\$ mabile phone if the they are useful in plant. He are the pair of the pair of the pair of the plant of the plant of the 2 Ulwer of the Lotted Charles when it is till have the battery life remaining, if the Right Channel earthur has been paired and connected with your mobile phone before, you can turn on the light Channel earthur days not in it will be commerced with your mobile phone before pair of the light Channel or the plant of the light Channel or the light Channel or the light Channel or the light Channel or the light of the light Channel or the light Channel or the light Channel or the light of the ligh

automatically.

3) When the Right Channel earbud is out of power, the Left Channel earbud will be turned off even if it still has the battery life remaining. When you turn on the Left Channel earbud again, it will be connected with the mobile phone automatically.

You may need to pair and connect BTwins with your mobile phone or other Bluetooth devices again if you want to use the headphone individually.

How To Pair And Connect With The 1st Mobile Phone.
 If Press and hold the MF button for about 3.5 secands to turn on the earbout, the LED lights flash in recip Press MF button for 2 seconds more, the LED lights turn on in solid base, then go into pairing model Or press and hold the MF button for about 5 seconds, when the LED lights turn on in solid bus, then go into pairing model, and the LED lights flash in the LED lights turn on in solid bus, then go into pairing model, and the LED lights flash in

the LED lights turn on in solid blau, then go into pairing model, and the LED lights flash in the best efter pairing.

2) Turn on the Blautcondent hardine of your melbals place or colder Efficient Section 5.11

2) Turn on the Blautcondent hardine of your melbals place or soler Efficient in all following the contraction of your melbals places (select Efficient in all following the contraction of your amone asks for pasks or PIRI does continue with 10000 (44 extent).

3) When Blavins and your mobile phone are paired and connected, you will hear the voice prompt.

NOTE: If no pairing is possible for a period of time (approximately 10 minutes), the earbud will be turned off automatically.

How To Pair And Connect With The 2nd Mobile Phone.
 RTwins supports Multipoint Technology for 2 phones connection when it is used individually.

1) Par and connect Elvine with the 1st mobile phone. (Please refer to the "1 How To Park And Connect With The 1st Mobile Phone,")
3 Farm of the Subscribe huston of the 1st mobile phone.
4 Tarm on Elvine, pair and connect the enthud with the 2nd mobile phone.
5 Tarm of the Binscribe het connection complete, and turn on again.
6 Tarm on the Binscribe has decreased the 1st mobile phone, the earbod will be connected with both mobile phone subscribe the subscribe t

Once BTwins are successfully connected to your mobile phone, you can use them to make and receive calls. Please consult your mobile phone's manual for more information.

Dial By The Phone Keys
 Enter and dial the number or your mobile phone as you normally do. Once the call has
 been set up, the round will be transmitted to your BT-wins automatically.
 Redial
 Double click MF Button to redial the last number you called.

-Press MF Button to answer the call.
-Press MF Button to end the call.
-Long press MF Button for 2 seconds to reject the call.

During both incoming call and outgoing call state, you can double click MF Button to transfer the call to the mobile phone. If you want to transfer the call back to BTwins, double click MF Button again. More procedures may be involved for some mobile

ADJUSTING THE VOLUME

To make sure BTwins can be so mini and lightweight, we removed the volume buttons from the headphones. You will need to increase/decrease the volume through your mobile phone or other Bulectoot hevices.

As there is no room to contain the tracking buttons on the headphones, please track the songs through your mobile phone or other Bluetooth devices.

BTwins are with 2-language voice prompt: English & Chinese. You can switch between these 2 languages by double click the MF Button after the headphones are turned on but not connected with any device.

You can connect BTwins with the Bluetooth enabled PC. Please refer to the user manual of your Bluetooth enabled PC for setup information.

To restore the headphones to factory setting, you will have to turn off the headphones, then press and hold the MiF Button of 2 earbuids separately for about 12 seconds. When the LED light flashes in red and blue twice, the factory reset is successful.

GUARANTE

Abbes is a registreed trademark of FreeTek International Co, Ltd. Other brands and product names are trademarks of their respective owners, beloes warrants this product against all defects in material and workmanhip for a period of velowe (12) members from the date of original purchase of the product. The conditions of this guarantee and the extent of responsibility of abbes under this guarantee and read in the Warranty Card.

Permanent hearing loss may result from long-term exposure to sound at high volumes. Use as low volume as possible and avoid prolonged use of the earphone at excessive sound pressure levels. Please read the below safety guidelines prior to using the product

(Prior to using this product)

1. Before putting on the earphones, turn the volume to its lowest level.

2.Put the earphones on, and then slowly adjust the volume to a comfortable level

(During the use of this product)

1.Keep the volume at the lowest level as possible.

1.Keep the volume at the lowest level as possible.

2.If it is necessary hor increase the volume, adjust the volume control slowly.

3.If you appearance discomfort or reging in your ears, immediately discontinue using the earliphones. With continued use at they forwing, your ear says become accustomed to the sound level, which may result in permanent damage to your hearing without any noticeable discomforts.

Lift you have a cardiac parentser or other electronic medical equipment, you should consult your physician before using this product.

2.This product contains small parts that may be hazardous to children. Keep out of the reach of children. The bags themselves or the many small parts they contain may cause their products of the contains small parts.

reach of children. The blage thermiteviers of the many small parts they contain may cause classed in figuration. As the containment of the contain

Be sure to ensure safe driving, avoid distractions and follow local laws.

BTHS160620 V1.0

Note: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- —Reorient or relocate the receiving antenna.
- —Increase the separation between the equipment and receiver.
- —Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- —Consult the dealer or an experienced radio/TV technician for help.

This device complies with part 15 of the FCC rules. Operation is subject to the following two conditions:

- (1) this device may not cause harmful interference, and
- (2) this device must accept any interference received, including interference that may cause undesired operation.

Changes or modifications to this unit not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.