

EXHIBIT D

[FCC Ref. 2.983(d)(9)]

"Tune-Up Procedures"

Exhibit D(1)-1

Tune-up procedure of the power level of JC215R

Connect a power meter to the antenna terminal.

- 1.Set the channel to 20.**
- 2.Adjust VR101 to the point where the maximum power level is obtained.**
- 3.Adjust L105 to the point where the maximum power level is obtained.**
- 4.Adjust IFT106,L111 and L109 in the order so that the maximum power level is obtained.**
- 5.Adjust L103, L104 and L105 so that the maximum power level is obtained.**
- 6.Adjust VR101 again to the point where the power level should be 3.8 watts.**
- 7.Confirm that the power level on both channel 1 and channel 40 is between 3.6 and 4.0 watts.**