

Antenna Datasheet

Product OC: Y0REB0CB9AA

Version: 1.0

Date: 2025-04-17

Product Name: Wi-Fi FPC Antenna

Key Features:

Frequency Band: 2400-2500 MHz, 5150-5850 MHz

Dimensions: 31 mm × 22.42 mm

Efficiency: Up to 52%

RoHS, REACH and HF Compliant



Contents

Со	ntents			1			
1	Spec	ification	on	2			
	1.1.		trical				
	1.2.	hanical & Environmental	2				
	1.3.	nna Assembly	3				
	1.4.		ching Circuit				
2	Draw	ing		4			
3	Detailed Performance						
	3.1.	S-Pa	arameter Test	5			
	3	3.1.1.	VSWR	5			
	3	3.1.2.	Return Loss	6			
	3.2.	Radia	ation Performance Test	7			
			Efficiency & Peak Gain				
	3	3.2.2.	3D & 2D Radiation Pattern	8			
Re	vision	Histor	ry	13			



1 Specification

Test Condition: Assembled in test device

1.1. Electrical

Electrical				
Frequency Range	2400–2500 MHz, 5150–5850 MHz			
Impedance	50 Ω			
Polarization	Linear			
Radiation Pattern	Omni-directional			
VSWR	≤ 3.7			
Peak Gain	2.98 dBi			

1.2. Mechanical & Environmental

Mechanical				
Antenna Dimensions	31 mm × 22.42 mm			
Material & Color & Cable	FPC & Black&			
Cable Type & Color & Length	Ф 1.13 & Black & 110 mm			
Connector Type	RF 4			
Weight	Typ. 0.5 g			
Mounting Type	Adhesive			
Environmental				
Operation Temperature	-40 °C to +85 °C			
Storage Temperature	-40 °C to +85 °C			


Antenna_Datasheet 2 / 13



RoHS & REACH	Yes

1.3. Antenna Assembly

1.4. Matching Circuit



		E1	E2	E3
\A/IEI	Default Matching	NA	0 ohm	NA
WIFI	Tolerance	NA	NA	NA

Antenna_Datasheet 3 / 13



2 Drawing

Antenna_Datasheet 4 / 13




3 Detailed Performance

- Network Analyzer: Keysight E5071C (Device number: QTB6331E; Calibration date: 2024-08-27; Due date: 2025-04-26)
- Chamber: OTA RayZone 2800 GTS (Device number: QTA0709; Calibration date: 2024-07-14; Due date: 2025-07-13)
- Testing Software: LibraAntenna Tpye: PIFA
- Product name: Wi-Fi FPC Antenna

Test Engineer:

3.1. S-Parameter Test

3.1.1. VSWR




VSWR

Frequency (MHz)	2400	2450	2500	5150	5300	5400	5500	5700	5850
VSWR	1.9	1.4	1.6	2.8	3.4	3.7	3.1	2.3	2.6

Antenna_Datasheet 5 / 13



3.1.2. Return Loss



Return Loss (dB)

Frequency (MHz)	2400	2450	2500	5150	5300	5400	5500	5700	5850
Return Loss (dB)	-10.3	-15.2	-12.4	-6.6	-5.3	-4.9	-5.8	-8.2	-7.2

Antenna_Datasheet 6 / 13



3.2. Radiation Performance Test

3.2.1. Efficiency & Peak Gain

Frequency (MHz)	Peak Gain (dBi)	Efficiency (%)	Frequency (MHz)	Peak Gain (dBi)	Efficiency (%)
2400	1.59	48.36	5150	-1.57	30.72
2410	0.99	47.79	5200	-0.73	32.54
2420	0.59	48.09	5250	-0.02	34.73
2430	0.27	47.29	5300	0.42	36.65
2440	0.04	46.26	5350	1.16	38.81
2450	-0.04	45.98	5400	1.8	43.93
2460	-0.1	45.56	5450	1.68	44.82
2470	-0.21	45.55	5500	2.35	49.58
2480	-0.37	43.69	5550	2.43	50.76
2490	-0.5	42.45	5600	2.98	52.24
2500	-0.5	41.81	5650	2.34	50.02
MAX	1.59		5700	2.28	50.08
			5750	2.57	49.57
			5800	2.09	42.8
			5850	1.64	38.39
_			MAX	2.98	

Antenna_Datasheet 7 / 13



3.2.2. 3D & 2D Radiation Pattern


Test Condition: Assembled in test device

Test Chamber: GL-G-1

Antenna_Datasheet 8 / 13



WIFI



Antenna_Datasheet 9 / 13



Contact Us

At Quectel, our aim is to provide timely and comprehensive services to our customers. If you require any assistance, please contact our headquarters:

Quectel Wireless Solutions Co., Ltd.

Building 5, Shanghai Business Park Phase III (Area B), No.1016 Tianlin Road, Minhang District, Shanghai 200233, China

Tel: +86 21 5108 6236 Email: <u>info@quectel.com</u>

Or our local offices. For more information, please visit:

http://www.quectel.com/support/sales.htm.

For technical support, or to report documentation errors, please visit:

http://www.quectel.com/support/technical.htm.

Or email us at: support@quectel.com.

Antenna_Datasheet 10 / 13



Legal Notices

We offer information as a service to you. The provided information is based on your requirements and we make every effort to ensure its quality. You agree that you are responsible for using independent analysis and evaluation in designing intended products, and we provide reference designs for illustrative purposes only. Before using any hardware, software or service guided by this document, please read this notice carefully. Even though we employ commercially reasonable efforts to provide the best possible experience, you hereby acknowledge and agree that this document and related services hereunder are provided to you on an "as available" basis. We may revise or restate this document from time to time at our sole discretion without any prior notice to you.

Use and Disclosure Restrictions

License Agreements

Documents and information provided by us shall be kept confidential, unless specific permission is granted. They shall not be accessed or used for any purpose except as expressly provided herein.

Copyright

Our and third-party products hereunder may contain copyrighted material. Such copyrighted material shall not be copied, reproduced, distributed, merged, published, translated, or modified without prior written consent. We and the third party have exclusive rights over copyrighted material. No license shall be granted or conveyed under any patents, copyrights, trademarks, or service mark rights. To avoid ambiguities, purchasing in any form cannot be deemed as granting a license other than the normal non-exclusive, royalty-free license to use the material. We reserve the right to take legal action for noncompliance with abovementioned requirements, unauthorized use, or other illegal or malicious use of the material.

Trademarks

Except as otherwise set forth herein, nothing in this document shall be construed as conferring any rights to use any trademark, trade name or name, abbreviation, or counterfeit product thereof owned by Quectel or any third party in advertising, publicity, or other aspects.

Third-Party Rights

This document may refer to hardware, software and/or documentation owned by one or more third parties ("third-party materials"). Use of such third-party materials shall be governed by all restrictions and obligations applicable thereto.

Antenna_Datasheet 11 / 13



We make no warranty or representation, either express or implied, regarding the third-party materials, including but not limited to any implied or statutory, warranties of merchantability or fitness for a particular purpose, quiet enjoyment, system integration, information accuracy, and non-infringement of any third-party intellectual property rights with regard to the licensed technology or use thereof. Nothing herein constitutes a representation or warranty by us to either develop, enhance, modify, distribute, market, sell, offer for sale, or otherwise maintain production of any our products or any other hardware, software, device, tool, information, or product. We moreover disclaim any and all warranties arising from the course of dealing or usage of trade.

Privacy Policy

To implement module functionality, certain device data are uploaded to Quectel's or third-party's servers, including carriers, chipset suppliers or customer-designated servers. Quectel, strictly abiding by the relevant laws and regulations, shall retain, use, disclose or otherwise process relevant data for the purpose of performing the service only or as permitted by applicable laws. Before data interaction with third parties, please be informed of their privacy and data security policy.

Disclaimer

- a) We acknowledge no liability for any injury or damage arising from the reliance upon the information.
- b) We shall bear no liability resulting from any inaccuracies or omissions, or from the use of the information contained herein.
- c) While we have made every effort to ensure that the functions and features under
- d) development are free from errors, it is possible that they could contain errors, inaccuracies, and omissions. Unless otherwise provided by valid agreement, we make no warranties of any kind, either implied or express, and exclude all liability for any loss or damage suffered in connection with the use of features and functions under development, to the maximum extent permitted by law, regardless of whether such loss or damage may have been foreseeable.
- e) We are not responsible for the accessibility, safety, accuracy, availability, legality, or completeness of information, advertising, commercial offers, products, services, and materials on third-party websites and third-party resources.

Copyright © Quectel Wireless Solutions Co., Ltd. 2025. All rights reserved.

Antenna_Datasheet 12 / 13



Revision History

Version	Date	Author	Note
-	2025-04-17	Damon ZHANG/ Steven MO/ Rainey LIAO	Creation of the document
1.0	2025-04-17	Damon ZHANG/ Steven MO/ Rainey LIAO	First official release

Antenna_Datasheet 13 / 13



www.quectel.com

1.2 NFC Antenna

NFC Frequency Band: 13.553 - 13.567 MHz

Modulation Type : ASK

Supported Card Type: A / B

NFC Antenna Type: Loop Antenna

NFC Antenna size: 73.08 * 59 * 4.85mm

NFC Antenna location: at the back of device screen