3 Using the baby monitor (Con't)

NOTE
The sound alert feature is only available in **Split** mode.

Monitor the temperature

Your baby unit monitors the temperature of your baby's room with its built-in temperature sensor. If the detected temperature is out of the preset temperature range, the parent unit will display an alert message.

Set temperature range

You can set the desired room temperature alert range. The minimum temperature can be set between **52 °F (11 °C)** and **69 °F (20 °C)**. The maximum temperature can be set between **70 °F (21 °C)** and **86 °F (30 °C)**.

1. Press **MENU** when the parent unit is idle.
2. Press ∨ or ∧ to choose **Temperature**, then press **SELECT**.
3. Press ∨ or ∧ to choose **Minimum** or **Maximum**, then press **SELECT**.
   - If you have two baby units, the system prompts you to choose the desired baby unit or both baby units, press ∨ or ∧ to choose **ALL CAM** or **CAM #**, then press **SELECT**.
4. Press ∨ or ∧ to choose the desired minimum or maximum temperature, then press **SELECT** to confirm your selection.

Temperature alert tone

You can turn on the temperature alert tone so that the parent unit will emit an alert tone if the detected temperature is out of range.

1. Press **MENU** when the parent unit is idle.
2. Press ∨ or ∧ to choose **Temperature**, then press **SELECT**.
3. Press ∨ or ∧ to choose **Alert tone**, then press **SELECT**.
   - If you have two baby units, the system prompts you to choose the desired baby unit or both baby units, press ∨ or ∧ to choose **ALL CAM** or **CAM #**, then press **SELECT**.
4. Press ∨ or ∧ to choose **On** or **Off**, then press **SELECT** to confirm your selection.

Temperature format

You can choose to display the temperature in Fahrenheit (°F) or Celsius (°C).

1. Press **MENU** when the parent unit is idle.
2. Press ∨ or ∧ to choose **Temperature**, then press **SELECT**.
3. Press ∨ or ∧ to choose **Format**, then press **SELECT**.
4. Press ∨ or ∧ to choose °F or °C, then press **SELECT** to confirm your selection.

Rename the baby unit

You can rename the baby unit. Once the baby unit is renamed, its new name together with the baby unit number will appear in the sub-menu of below options:

- VOX Sensitivity
- Rename
- Temperature

1. Press **MENU** when the parent unit is idle.
2. Press ∨ or ∧ to choose **Rename**, then press **SELECT**.
3. Press ∨ or ∧ to choose the desired baby unit, then press **SELECT**.
4. Press ∨ or ∧ to choose the desired name for the baby unit, then press **SELECT** to confirm your selection.

Baby unit overview



1 **Microphone**
2 **Camera**
3 **Light sensor**
4 **ON/OFF LED light**
- On when the baby unit is turned on and is paired to the parent unit.
- Flashes when the baby unit is not being viewed; or when the link to the parent unit is lost.

5 **Infrared LEDs**
6 **Pair hole**
- Your baby units and parent unit provided are already paired.

7 **Speaker**
8 **Temperature sensor**
9 **ON/OFF switch**
- Slide to turn on or off the baby unit.

10 **Power jack**
11 **Wall mount holes for upright mounting**
12 **Wall mount holes for lateral mounting**

Parent unit overview



1 **LED lights**
Indicate the different statuses of the parent unit. For details, refer to **Parent unit lights**.
2 **LCD display**
3 **VOL**
4 **VOL**

Parent unit overview (Con't)

5 **Zoom**
- Press to zoom in or out.

6 **VIEW / LCD ON/OFF**
7 **Microphone**
8 **POWER**
9 **TALK**
- Press and hold to talk to the selected baby unit.

10 **<**
- While in a menu, press to return to the main menu or idle screen.
- While viewing zoomed image, press and hold to move the zoomed image leftward.
- While in **Split** mode, press to move the selection box leftward.

11 **∧**
- While in a menu, press to scroll up.
- While viewing zoomed image, press and hold to move the zoomed image upward.

12 **>**
- While in a menu, press to choose an item.
- While viewing zoomed image, press and hold to move the zoomed image rightward.
- While in **Split** mode, press to move the selection box rightward.

13 **MENU/SELECT**
- Press to enter the menu.
- While in a menu, press to choose an item, or save a setting.

14 **∨**
- While in a menu, press to scroll down.
- While viewing zoomed image, press and hold to move the zoomed image downward.

15 **Antenna**
16 **Stand**
17 **Speaker**
18 **Power jack**

Parent unit lights

LINK
- On when the parent unit is linked to the baby unit.
- Flashes when the link to the baby unit being viewed in **Single CAM** or **Patrol** mode is lost; or when the link to at least one baby unit being viewed in **Split** mode is lost.

- On when the parent unit is connected to AC power, or the battery is charging.
- Flashes when the parent unit battery is low and needs charging.
- Off when the parent unit is disconnected from AC power.

It turns on:
- When the parent unit speaker volume is set to off; or
- When the parent unit is talking to the baby unit; or
- When the parent unit is in **Split** mode.

TALK
- On when the parent unit is talking to the baby unit.

Parent unit icons

Status icons

Connection status
- displays when strong signal strength is detected between the baby unit and the parent unit.
- / displays when moderate or low signal strength is detected between the baby unit and the parent unit.
- displays when the link between the baby unit and the parent unit is lost.

Lullaby
- Displays when the baby unit being viewed is playing lullaby.

Current view status
- Displays the number of the baby unit that is being viewed when in **Single CAM** and **Patrol** mode.
- Displays the baby unit number of the selected baby unit when in **Split** mode.

Patrol mode
- Displays when the parent unit is in **Patrol** mode.
- For VM5251-2 only.

Split mode
- Displays when the parent unit is in **Split** mode.
- For VM5251-2 only

Night vision
- Displays when the baby unit being viewed has activated the night vision feature.

Zoom
- Displays when the current image on the parent unit has zoomed in.

Temperature alert tone
- Displays when the temperature alert tone is set on.

°F or °C

Real-time temperature
- Displays the real-time temperature detected by the baby unit in Fahrenheit (°F) or Celsius (°C) (e.g. **57 °F** or **14 °C**).

Mute alert
- Displays when the parent unit speaker volume is set to off.
- Displays when the parent unit is talking to the baby unit.
- Displays when **Split** mode is turned on.

9-level sound indicator
- (1 to 3 bars) indicates low sound level detected by the baby unit.
- (4 to 6 bars) indicates moderate sound level detected by the baby unit.
- (7 to 9 bars) indicates high sound level detected by the baby unit.

Speaker volume
- Displays the parent unit speaker volume level while adjusting.

Battery status
- animates when the battery is charging.
- displays solid when the battery is fully charged.
- displays when the battery is low and needs charging.

AC power without battery
- Displays when the parent unit is connected to AC power without the battery.

Main menu icons

Monitoring Mode
- If you have two baby units, you can select a monitoring mode (**Single CAM**, **Patrol** or **Split**).
- For VM5251-2 only.

Alert Tone
You can set the parent unit to beep when
- the parent unit operates in low battery condition;
- the link between the parent unit and the baby unit is lost; or
- the baby unit detects sounds while in **Split** mode.

Language
- You can select a language (**English**, **French** or **Spanish**) to be used in all screen displays.

LCD
- You can change the brightness of the parent unit screen, or turn on the Dim Mode to save power.

Rename
- You can choose a specific name for the baby unit from a pre-defined name list.

VOX Sensitivity
- With this feature, you can choose to hear sounds from the baby unit all the time, or only sounds that exceed a certain level. You can use the parent unit to adjust the microphone sensitivity of your baby unit. The higher the sensitivity level, the more sensitive the baby unit is in detecting sounds for transmitting to the parent unit.

Sound-activated Screen
- When the baby unit detects no sound, the parent unit screen stays off to save power. Once a sound is detected, the parent unit screen turns on automatically. It will then turn off again after 30 seconds of no sound detection.

Temperature
- You can choose to set the maximum/ minimum temperature and turn on the **Temperature alert tone**, so that the parent unit beeps whenever the room temperature detected by the baby unit falls outside of the desired temperature range.
- You can choose to display the temperature in Fahrenheit (°F) or Celsius (°C) on your parent unit.

Lullaby on CAM
- You can choose a lullaby or soothing sound to comfort your baby.

Volume on CAM
- You can adjust the volume of baby units which determines the lullaby volume and talkback volume transmitted from parent unit.

Warning icons and messages

No link to CAM # *	The selected baby unit is out of range or is turned off.
Battery low at Parent Unit	The battery level of the parent unit is very low and needs to be recharged.
Battery empty. Powering off ...	The battery is empty and needs to be recharged.
Sound detected at CAM #	The sound level exceeds the threshold at CAM # in **Split** mode.

Parent unit icons (Con't)

Temperature too high at CAM # or **Temperature too low at CAM #**	The temperature detected by the baby unit is higher/lower than the desired temperature alert range.
Powering on...	The parent unit is turning on.
	The parent unit is searching for baby units.
Auto Timer of lullaby is reset	The timer that determines the remaining play time for the lullabies is restarted.
	The parent unit has just been connected to AC power.

* # represents the baby unit number.

Night vision

The baby unit has infrared LEDs that allow you to see your baby clearly at night or in a dark room. When the baby unit being viewed detects low light levels, the infrared LEDs are switched on automatically. The images from the baby unit are in black and white, and appears on the screen.

NOTES
- It is normal if you see a short white glare on your parent unit screen as the baby unit is adapting to the dark environment.
- When the infrared LEDs are on, the images are in black and white. This is normal.

TIP
- Depending on the surroundings and other interfering factors, like lightings, objects, colors and backgrounds, the video quality may vary. Adjust the baby unit's angle or place the baby unit at a higher level to prevent glare and blurry display.

Mount the baby unit (optional)

Your baby monitor comes ready for tabletop use. You can also choose to mount your baby monitor on the wall. See Mount the baby unit on dry wall (optional) in the **Quick Start Guide** for the wall mounting instructions.

General product care

To keep this product working well and looking good, follow these guidelines:

- Avoid putting it near heating appliances and devices that generate electrical noise (for example, motors or fluorescent lamps).
- DO NOT expose it to direct sunlight or moisture.
- Avoid dropping the product or treating it roughly.
- Clean with a soft cloth.
- DO NOT immerse the parent unit and the baby unit in water and do not clean them under the tap.
- DO NOT use cleaning spray or liquid cleaners.
- Make sure the baby unit and parent unit are dry before you connect them to the mains again.

Storage

When you are not going to use the baby monitor for some time, remove the rechargeable battery from the parent unit. Store the parent unit, the baby unit and the adapters in a cool and dry place.

Frequently asked questions

Before are the questions most frequently asked about the baby monitor. If you cannot find the answer to your question, visit our website at **www.vtechphones.com**, or contact **1 (800) 595-9511** for customer service.

Why does the baby monitor not respond normally?	Try the following (in the order listed) for common cure: 1. Disconnect the power to the baby units and the parent unit. 2. Remove the batteries in the parent unit. Then, install the batteries again. 3. Wait a few seconds before connecting power back to the baby units and the parent unit. 4. Turn on the baby units and the parent unit. 5. Wait for the parent unit to synchronize with the baby units. Allow up to one minute for this to take place.
Why don't the power-on light of the baby unit and parent unit light up when I switch on the units?	Perhaps the parent unit is not connected to the power. Insert the appliance plug into the parent unit and put the adapter in a wall socket. Then, press and hold **POWER** to switch on the parent unit and to establish connection with the baby unit. Perhaps the baby unit is not connected to the power. Insert the appliance plug into the baby unit and put the adapter in a wall socket. Then, slide the **ON/OFF** switch to **ON** to switch on the baby unit and to establish connection with the parent unit.
Why doesn't my parent unit charge while connected to AC power?	Make sure the power is not controlled by a wall switch. Make sure the battery is correctly installed in your parent unit. You may have used the battery for a long time. Replace a new battery.
Why is my screen in black and white?	The screen is in black and white during night-time or in a dark room when the night vision feature is activated. This is normal.
Why do I get glare or blurry display on my screen when viewing my baby at night?	During night-time or in a dark room, the surroundings and other interfering factors, like lightings, objects, colors and backgrounds may affect the image quality on the parent unit' screen. Adjust the baby unit's angle or place the baby unit at a higher level to prevent glare and blurry display.
Why does the baby monitor produce a high-pitched noise?	The parent unit and baby units may be too close to each other. - Move the parent unit away from the baby units until the noise stops; OR - Turn down the volume of your parent unit.
Why does the parent unit beep?	The baby units may be out of range. Move the parent unit closer to the baby units (but not less than 3 feet). The parent unit may not have enough charge for the parent unit to perform normally. Charge the battery in the parent unit for up to 3 hours. If your parent unit is in **Split** mode, some of your baby units may detect sounds. The temperature of your baby's room may be too high or too low.
Why does the parent unit react too quickly to other sounds?	You may have set the VOX sensitivity level to **Highest** when the sound alert feature is turned on. The baby unit picks up other sounds than those of your baby. Adjust the VOX sensitivity level to a lower level.
Why does the parent unit react too quickly to other sounds?	The baby unit also picks up other sounds than those of your baby. Adjust the VOX sensitivity level to a lower level or lower the parent unit speaker volume.
Why don't I hear any sound/ only can't I hear my baby cry?	The parent unit speaker volume may be too low. Press VOL ❶ to increase the volume. You may have set a low VOX sensitivity level. See **Adjust the sound sensitivity of the baby unit** to set to a higher level.
Why can't I establish a connection? Why is the connection lost every now and then? Why are there sound interruptions?	The baby units may be out of range. Move the parent unit closer to the baby units (but not less than 3 feet). Other electronic and wireless products may cause interference with your baby monitor. Try installing your baby monitor as far away from these devices as possible.
	If you power on only one baby unit, your parent unit may display ⁂ and **No link to CAM #**, and the **LINK** LED light flashes. Press **VIEW** to switch to the baby unit you have powered on.

The RBRC® seal

The RBRC® seal on the lithium-ion battery indicates that VTech Communications, Inc. is voluntarily participating in a program to provide a convenient method for recycling such batteries at the end of their useful lives, when taken out of service within the United States and Canada.

The RBRC® program provides a convenient alternative to placing used lithium-ion batteries into the trash or municipal waste, which may be illegal in your area.

VTech's participation in RBRC® makes it easy for you to drop off the spent battery at local retailers participating in the RBRC® program or at authorized VTech product service centers. Please call **1 (800) 8 BATTERY** for information on Li-ion battery recycling and disposal bans/restrictions in your area. VTech's involvement in this program is part of its commitment to protecting our environment and conserving natural resources.

RBRC® and 1 (800) 8 BATTERY® are registered trademarks of the Rechargeable Battery Recycling Corporation.

FCC and IC regulations

FCC Part 15

This equipment has been tested and found to comply with the requirements for a Class B digital device under Part 15 of the Federal Communications Commission (FCC) rules. These requirements are intended to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

WARNING: Changes or modifications to this equipment not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

This device complies with Part 15 of the FCC rules. Operation is subject to the following two conditions: (1) this device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

To ensure safety of users, the FCC has established criteria for the amount of radio frequency energy that can be safely absorbed by a user or bystander according to the intended usage of the product. This product has been tested and found to comply with the FCC criteria. The baby unit shall be installed and used such that parts of all persons' body are maintained at a distance of approximately 8 in (20 cm) or more. The transmitter and antenna of the parent unit shall be held at least 1 in (2.5 cm) from your face.

This Class B digital apparatus complies with Canadian requirement:
CAN ICES-3 (B)/ NMB-3(B)

Industry Canada

This device contains licence-exempt transmitter(s)/receiver(s) that comply with Innovation, Science and Economic Development Canada's licence-exempt RSS(s). Operation is subject to the following two conditions: (1) This device may not cause interference. (2) This device must accept any interference, including interference that may cause undesired operation of the device.

The term "IC:" before the certification/registration number only signifies that the Industry Canada technical specifications were met.

This product meets the applicable Innovation, Science and Economic Development Canada technical specifications.

RF radiation exposure statement

The baby unit complies with FCC RF radiation exposure limits set forth for an uncontrolled environment. The baby unit should be installed and operated with a minimum distance of 8 in (20 cm) between the baby unit and all persons' body. Use of other accessories may not ensure compliance with FCC RF exposure guidelines. This transmitter must not be co-located or operating in conjunction with any other antenna or transmitter. This equipment complies also with Industry Canada RSS-102 with respect to Canada's Health Code 6 for Exposure of Humans to RF fields.

California Energy Commission battery charging testing mode

This baby monitor meets the California Energy Commission (CEC) regulations for energy consumption. Your baby monitor is set up to comply with the energy-conserving standards right out of the box. Follow the instructions to install and charge the battery. The CEC battery charging testing mode is activated while charging. Even if the parent unit is paired to baby units, the CEC battery charging testing mode is activated while it is powered off and charging.

For cETL compliance only

Mesures de sécurité importantes

Lorsque vous utilisez votre appareil, vous devriez toujours suivre certaines mesures de précaution de base afin de réduire les risques d'incendie, d'électrocution et de blessures corporelles, dont ceux que suivent:

1. Observez toutes les instructions et mises en garde inscrites sur l'appareil.
2. L'installation par un adulte est requise.
3. Ce produit ne remplace pas la surveillance adulte du nourrisson. La supervision du nourrisson est la responsabilité du parent ou de la personne qui prend soin du nourrisson. Ce produit ne convient pas à une personne qui ne peut pas assumer la responsabilité de surveiller le nourrisson de façon consciencieuse pendant une période de temps donnée. De plus, il ne s'agit pas d'un instrument médical et ne devrait pas être utilisé comme tel. Ce produit ne devrait vous aider à superviser votre bébé.
4. Ne placez pas l'appareil dans un endroit où il pourrait faire quelque source d'humidité, par exemple, près d'une baignoire, cuve à lessive, évier de cuisine, dans un sous-sol humide ou près d'une piscine, dans un sauna/ humide ou une douche.
5. **MISE EN GARDE:** Utilisez uniquement les piles fournies. Il existe un risque d'explosion si vous avez mal installé la pile. Ne démontez pas la pile, ne la jetez pas au feu et ne la court-circuitez pas. Ne rechargez pas les piles non rechargeables. Ne brûlez pas les piles. Celles-ci risquent de s'exploser. Jetez les piles usées selon les renseignements ci-avant **le sens du RBRC®**.
6. N'utilisez que les adaptateurs inclus avec ce produit. L'utilisation d'un adaptateur dont la polarité ou la tension serait inadéquate risque d'endommager l'appareil. Le bloc d'alimentation est utilisé comme un appareil de sectionnement.
   Adaptateur de l'unité du bébé : Entrée: 5V CC 400mA
   Adaptateur de l'unité du parent : Sortie : 5V CC 1A
7. Ne placez pas l'appareil sur une table, un présentoir, un adaptateur sectoriel ou un lit rugueux pour être orientés correctement, sauf s'il le verrouille ou qu'il le fixe. Les appareils tombent rarement sur des surfaces douces pour suggérer le poids du bébé. d'alimentation et le maintenir en place à contact ou branché dans une prise au plafond, sous une table ou dans un meuble.
8. Ne placez pas les cordons d'alimentation DU BÉBÉ OU DU COUSIN( ), la prise de courant doit être installée près du produit, afin d'assurer une accessibilité ininterrompue à la prise de courant.
9. Débranchez ce produit de la prise de courant avant de procéder au nettoyage. N'utilisez pas de nettoyants en aérosols. Utilisez un chiffon humide pour le nettoyer.
10. Débranchez les cordons d'alimentation avant de remplacer le bloc-piles.
11. Ne placez pas d'objets sur le produit ou ne couvrez pas le produit, de sorte que ceci peut présenter un danger potentiel.
12. Ne bloquez aucun objet risquant ni appuyer sur le cordon d'alimentation. N'installez pas cet appareil dans un endroit où l'on risque d'écraser le cordon d'alimentation ou de le pétiner.
13. Ne surchargez pas les prises de courant. Pour un rendement optimal, le type d'alimentation indiqué sur l'étiquette. Si vous ne connaissez pas le type d'alimentation que vous possédez à votre domicile, consulter votre marchand ou votre compagnie locale d'électricité.
14. Ne surchargez pas les prises de courant murales ni les rallonges électriques.
15. Ne placez pas cet appareil sur un chariot, meuble, trépied, support de montage ni table chancelants.
16. Les trous et ouvertures du boîtier, situés à l'arrière de l'appareil ou sous celui-ci, servent à aérer l'appareil. Pour l'empêcher de surchauffer, ne couvrez pas ou ne bouchez pas les ouvertures. Ne placez pas l'appareil près ou au-dessus d'un radiateur ou d'une source de chaleur ou sur une surface de hauts-parleurs surface complète. De même, ne le positionnez pas à proximité d'une source de chaleur ou d'un calorifère. De plus, ne placez pas l'appareil dans un endroit avant de vous assurer qu'il y ait une bonne circulation d'air.
17. Ne placez pas d'objets sur le produit ou ne couvrez pas le produit, de sorte que ceci peut avec des points de tension dangereuse ou causer des courts-circuits qui peuvent déclencher un incendie ou un risque d'électrocution. Ne renversez jamais de liquide dans ce produit.
18. Afin de réduire les risques d'électrocution, ne démontez pas cet appareil, mais apportez-le dans un centre de service autorisé. L'ouverture du boîtier ou le fait de retirer des couvercles peut vous exposer à des tensions dangereuses ou à d'autres risques. Le remontage incorrect peut par la suite protéger des risques d'électrocution.
19. Vous devriez tenir la réception chaque fois que vous mettez l'appareil en fonction.
20. Examinez les composantes afin de vérifier si celles-ci ne sont pas endommagées.
21. Soyez avisé de la perte de la confidentialité lorsque vous utilisez les unités publiques. Les conversations peuvent être entendues par d'autres personnes à proximité, à moins que la ligne ne soit privée.
22. Les enfants devraient être supervisés afin de vous assurer qu'ils ne jouent pas avec l'appareil.
23. Le produit n'est pas conçu pour être utilisé par des personnes (incluant des enfants) aux capacités physiques, sensorielles ou mentales réduites, ou encore par des personnes ne possédant ni l'expérience ni les connaissances suffisamment de supervision ou d'instructions relativement à l'utilisation de l'appareil par une personne responsable de leur sécurité.

CONSERVEZ CES INSTRUCTIONS

Mises en garde

1. Utilisez et entreposez le produit à une température entre 0 ° C (32 °) et 40 ° C (104 ° F).
2. N'exposez pas cet appareil à des fluids ou des chaleurs extrêmes, ainsi qu'à la lumière directe du soleil. Ne l'installez pas près d'une source de chaleur.
3. Le bloc-piles ne doit pas être exposé à la chaleur excessive telle que la lumière du soleil ou au feu.
4. Assurez-vous que le moniteur et le cordon de l'adaptateur sont toujours hors de portée des enfants, au moins 1 mètre (3 pieds) de l'enfant ou du berceau, pour éviter tout risque de étranguation.
5. Ne placez pas le moniteur à l'intérieur du berceau ou du parc de bébé. Ne jamais couvrir le moniteur ou l'unité (s) portative avec un article tel que celle-ci de une couverture.
6. D'autres équipements électroniques peuvent produire des interférences sur votre moniteur vidéo et audio. Tentez d'éprouver votre moniteur vidéo et audio de manière à éviter des interférences tels que des moteurs des TV, radios, téléphones cellulaires, interphones, moniteurs, téléphones, ordinateurs personnels, électroménagers et téléphones sans fil.

Stimulateurs cardiaques implanté dans l'organisme

Les simulateurs cardiaques (ou l'appareil qu'aux dispositifs numériques sans fil):

- Vous devriez maintenir les dispositifs sans fil à au moins six pouces du simulateur cardiaque.
- Ne placez pas le téléphone sans fil directement sur le stimulateur cardiaque, tel que dans une poche de chemise, lorsque celui-ci est en marche.

L'étude effectuée par l'organisme WRS n'a pas identifié de risque pour les détenteurs de simulateurs cardiaques causés par les gens qui utilisent dispositifs sans fil à possibilité de voix.

Champs électromagnétiques (EMF)

Ce produit de VTech est conforme à toutes les normes en rapportant aux champs électromagnétiques (EMF) standard. Si vous le manipulez correctement en suivant les instructions de ce guide, son utilisation sera sécuritaire pendant de nombreuses années, selon les meilleures évidences scientifiques dont nous disposons aujourd'hui.

Limited warranty

What does this limited warranty cover?

VTech Communications, Inc. ("VTech") warrants to the holder of a valid proof of purchase ("Consumer" or "you") that the Product and all accessories provided in the sales package ("Product") are free from defects in material and workmanship pursuant to the following terms and conditions, when installed and used normally and in accordance with the Product Operating Instructions. This limited warranty extends only to the Consumer for Products purchased and used in the United States of America and Canada.

What will VTech do if the Product is not free from defects in materials and workmanship during the limited warranty period ("Materially Defective Product")?

If a Product is a Materially Defective Product, VTech's authorized service representative will repair or replace at VTech's option, without charge, a Materially Defective Product. If we repair the Product, we may use new or refurbished replacement parts. If we choose to replace the Product, we may replace it with a new or refurbished Product of the same or similar design. We will retain defective parts, modules, or equipment. Repair or replacement of the Product, at VTech's option, is your exclusive remedy. VTech will return the repaired or replacement Products to you in working condition. You should expect the repair or replacement to take approximately 30 days.

How long is the limited warranty period?

The limited warranty for the Product lasts for the shorter period extends for ONE (1) YEAR from the date of purchase. If VTech repairs or replaces a Materially Defective Product under the terms of this limited warranty, this limited warranty also applies to the repaired or replacement Product for a period of either (a) 90 days from the date the repaired or replacement Product is shipped to you or (b) the time remaining on the original one-year warranty; whichever is longer.

What is not covered by this limited warranty?

This limited warranty does not cover:

1. Product that has been subjected to misuse, accident, shipping or other physical damage, improper installation, abnormal operation or handling, neglect, inundation, fire, water or other liquid intrusion; or
2. Product that has been damaged due to repair, alteration or modification by anyone other than an authorized service representative of VTech; or
3. Product to the extent that the problem experienced is caused by signal conditions, network reliability, or cable or antenna systems; or
4. Product to the extent that the problem is caused by use with non-VTech accessories; or
5. Product whose warranty has expired or has been voided, product serial number plates or electronic serial numbers have been removed, altered or rendered illegible; or
6. Product purchased, used, serviced, or shipped for repair from outside the United States of America or Canada, or used for commercial or institutional purposes (including but not limited to Products used for rental purposes); or
7. Product returned without a valid proof of purchase (see Item 2 below); or
8. Charges for installation or set up, adjustment of customer controls, and installation or repair of systems outside the unit.

How do you get warranty service?

To obtain warranty service in the USA, please visit our website at www.vtechphones.com or call 1 (800) 595-9511. In Canada, go to www.vtechcanada.com or call 1 (800) 267-7377.

NOTE: Before calling for service, please review the user's manual - a check of the Product's controls and features may save you a service call.

Except as limited by applicable law, you assume the risk of loss or damage during transit and transportation and are responsible for delivery or handling charges incurred in the transport of the Product(s) to the service location. VTech will return repaired or replaced Product under this limited warranty. Transportation, delivery or handling charges are prepaid. VTech assumes no risk for damage or loss of the Product in transit. If the Product failure is not covered by this limited warranty, or proof of purchase does not meet the terms of this limited warranty, VTech will notify you and will request that you authorize the repair for which there will be a charge. In such case, you must pay for the cost of repair and return shipping costs for the repair of Products that are not covered by this limited warranty.

What must you return with the Product to get warranty service?

1. Return the entire original package and contents including the Product to the VTech service location along with a description of the malfunction or difficulty; and
2. Include a "valid proof of purchase" (sales receipt) identifying the Product purchased (Product model) and the date of purchase or receipt; and
3. Provide your name, complete and correct mailing address, and telephone number.

Other limitations

This warranty is the complete and exclusive agreement between you and VTech. It supersedes all other written or oral communications related to this Product. VTech provides no other warranties for this Product. The warranty exclusively describes your exclusive remedy against VTech. No VTech dealer, agent or employee is authorized to make any modifications, extensions or additions to this limited warranty and you should not rely on any such modifications. State/Provincial Law Rights: This warranty gives you specific legal rights, and you may also have other rights, which vary from state to state or province to province.

Limitations: Implied warranties, including those of fitness for a particular purpose and merchantability (an unwritten warranty that the Product is fit for ordinary use) are limited to one year from the date of purchase. Some states/provinces do not allow limitations on how long an implied warranty lasts, so the above limitation may not apply to you. In no event shall VTech be liable for any indirect, special, incidental, consequential, or similar damages (including, but not limited to lost profits or revenue, inability to use the Product or other associated equipment, the cost of substitute equipment, and claims by third parties) resulting from the use of this Product. Some states/provinces do not allow the exclusion or limitation of incidental or consequential damages, so the above limitation or exclusion may not apply to you.

Please retain your original sales receipt as proof of purchase.