
	Document Appendix D for the BlackBerry® Smartphone Model RFA91LW SAR Report			Page 1(114)
	Author Data Andrew Becker	Dates of Test Aug 21 – Nov 23, 2012 Jan. 07-11, 2013	Test Report No RTS-6012-1211-32 Rev 3	FCC ID: L6ARFA90LW

APPENDIX D: PROBE & DIPOLE CALIBRATION DATA

	Document Appendix D for the BlackBerry® Smartphone Model RFA91LW SAR Report			Page 2(114)
	Author Data Andrew Becker	Dates of Test Aug 21 – Nov 23, 2012 Jan. 07-11, 2013	Test Report No RTS-6012-1211-32 Rev 3	FCC ID: L6ARFA90LW

**Calibration Laboratory of
Schmid & Partner
Engineering AG**
 Zeughausstrasse 43, 8004 Zurich, Switzerland



S Schweizerischer Kalibrierdienst
C Service suisse d'étalonnage
S Servizio svizzero di taratura
S Swiss Calibration Service

Accredited by the Swiss Accreditation Service (SAS)
 The Swiss Accreditation Service is one of the signatories to the EA
 Multilateral Agreement for the recognition of calibration certificates

Accreditation No.: **SCS 108**



Client **RTS (RIM Testing Services)**


Certificate No: **ES3-3225_Jan12**

CALIBRATION CERTIFICATE

Object	ES3DV3 + SN:3225
Calibration procedure(s)	QA-CAL-01.v8, QA-CAL-23.v4, QA-CAL-25.v4 Calibration procedure for dosimetric E-field probes
Calibration date:	January 11, 2012
<p>This calibration certificate documents the traceability to national standards, which realize the physical units of measurements (SI). The measurements and the uncertainties with confidence probability are given on the following pages and are part of the certificate.</p> <p>All calibrations have been conducted in the closed laboratory facility: environment temperature (22 ± 3)°C and humidity < 70%.</p> <p>Calibration Equipment used (M&TE critical for calibration)</p>	

Primary Standards	ID	Cal Date (Certificate No.)	Scheduled Calibration
Power meter E4419B	GB41293874	31-Mar-11 (No. 217-01372)	Apr-12
Power sensor E4412A	MY41498087	31-Mar-11 (No. 217-01372)	Apr-12
Reference 3 dB Attenuator	SN: S5054 (3c)	29-Mar-11 (No. 217-01369)	Apr-12
Reference 20 dB Attenuator	SN: S5086 (20b)	29-Mar-11 (No. 217-01367)	Apr-12
Reference 30 dB Attenuator	SN: S5129 (30b)	29-Mar-11 (No. 217-01370)	Apr-12
Reference Probe ES3DV2	SN: 3013	29-Dec-11 (No. ES3-3013_Dec11)	Dec-12
DAE4	SN: 654	3-May-11 (No. DAE4-654_May11)	May-12
Secondary Standards	ID	Check Date (in house)	Scheduled Check
RF generator HP 8648C	US3642U01700	4-Aug-99 (in house check Apr-11)	In house check: Apr-13
Network Analyzer HP 8753E	US37390585	18-Oct-01 (in house check Oct-11)	In house check: Oct-12

	Name	Function	Signature
Calibrated by:	Jeton Kastrelli	Laboratory Technician	
Approved by:	Katja Pokovic	Technical Manager	
			Issued: January 12, 2012
This calibration certificate shall not be reproduced except in full without written approval of the laboratory.			

	Document Appendix D for the BlackBerry® Smartphone Model RFA91LW SAR Report			Page 3(114)
	Author Data Andrew Becker	Dates of Test Aug 21 – Nov 23, 2012 Jan. 07-11, 2013	Test Report No RTS-6012-1211-32 Rev 3	FCC ID: L6ARFA90LW

**Calibration Laboratory of
Schmid & Partner
Engineering AG**
 Zeughausstrasse 43, 8004 Zurich, Switzerland



S Schweizerischer Kalibrierdienst
C Service suisse d'étalonnage
S Servizio svizzero di taratura
S Swiss Calibration Service

Accredited by the Swiss Accreditation Service (SAS)
 The Swiss Accreditation Service is one of the signatories to the EA
 Multilateral Agreement for the recognition of calibration certificates

Accreditation No.: **SCS 108**

Glossary:


TSL	tissue simulating liquid
NORM _{x,y,z}	sensitivity in free space
ConvF	sensitivity in TSL / NORM _{x,y,z}
DCP	diode compression point
CF	crest factor (1/duty_cycle) of the RF signal
A, B, C	modulation dependent linearization parameters
Polarization ϕ	ϕ rotation around probe axis
Polarization ϑ	ϑ rotation around an axis that is in the plane normal to probe axis (at measurement center), i.e., $\vartheta = 0$ is normal to probe axis

Calibration is Performed According to the Following Standards:

- IEEE Std 1528-2003, "IEEE Recommended Practice for Determining the Peak Spatial-Averaged Specific Absorption Rate (SAR) in the Human Head from Wireless Communications Devices: Measurement Techniques", December 2003
- IEC 62209-1, "Procedure to measure the Specific Absorption Rate (SAR) for hand-held devices used in close proximity to the ear (frequency range of 300 MHz to 3 GHz)", February 2005

Methods Applied and Interpretation of Parameters:

- NORM_{x,y,z}:** Assessed for E-field polarization $\vartheta = 0$ ($f \leq 900$ MHz in TEM-cell; $f > 1800$ MHz: R22 waveguide). NORM_{x,y,z} are only intermediate values, i.e., the uncertainties of NORM_{x,y,z} does not affect the E²-field uncertainty inside TSL (see below ConvF).
- NORM(f)_{x,y,z} = NORM_{x,y,z} * frequency_response** (see Frequency Response Chart). This linearization is implemented in DASY4 software versions later than 4.2. The uncertainty of the frequency response is included in the stated uncertainty of ConvF.
- DCP_{x,y,z}:** DCP are numerical linearization parameters assessed based on the data of power sweep with CW signal (no uncertainty required). DCP does not depend on frequency nor media.
- PAR:** PAR is the Peak to Average Ratio that is not calibrated but determined based on the signal characteristics
- A_{x,y,z}; B_{x,y,z}; C_{x,y,z}; VR_{x,y,z}:** A, B, C are numerical linearization parameters assessed based on the data of power sweep for specific modulation signal. The parameters do not depend on frequency nor media. VR is the maximum calibration range expressed in RMS voltage across the diode.
- ConvF and Boundary Effect Parameters:** Assessed in flat phantom using E-field (or Temperature Transfer Standard for $f \leq 800$ MHz) and inside waveguide using analytical field distributions based on power measurements for $f > 800$ MHz. The same setups are used for assessment of the parameters applied for boundary compensation (alpha, depth) of which typical uncertainty values are given. These parameters are used in DASY4 software to improve probe accuracy close to the boundary. The sensitivity in TSL corresponds to NORM_{x,y,z} * ConvF whereby the uncertainty corresponds to that given for ConvF. A frequency dependent ConvF is used in DASY version 4.4 and higher which allows extending the validity from ± 50 MHz to ± 100 MHz.
- Spherical isotropy (3D deviation from isotropy):** in a field of low gradients realized using a flat phantom exposed by a patch antenna.
- Sensor Offset:** The sensor offset corresponds to the offset of virtual measurement center from the probe tip (on probe axis). No tolerance required.

	Document Appendix D for the BlackBerry® Smartphone Model RFA91LW SAR Report			Page 4(114)
	Author Data Andrew Becker	Dates of Test Aug 21 – Nov 23, 2012 Jan. 07-11, 2013	Test Report No RTS-6012-1211-32 Rev 3	FCC ID: L6ARFA90LW

ES3DV3 – SN:3225


January 11, 2012

Probe ES3DV3

SN:3225

Manufactured: September 1, 2009
Calibrated: January 11, 2012

Calibrated for DASY/EASY Systems
(Note: non-compatible with DASY2 system!)

	Document Appendix D for the BlackBerry® Smartphone Model RFA91LW SAR Report			Page 5(114)
	Author Data Andrew Becker	Dates of Test Aug 21 – Nov 23, 2012 Jan. 07-11, 2013	Test Report No RTS-6012-1211-32 Rev 3	FCC ID: L6ARFA90LW

ES3DV3– SN:3225

January 11, 2012

DASY/EASY - Parameters of Probe: ES3DV3 - SN:3225

Basic Calibration Parameters

	Sensor X	Sensor Y	Sensor Z	Unc (k=2)
Norm ($\mu\text{V}/(\text{V}/\text{m})^2$) ^A	1.26	1.20	1.30	± 10.1 %
DCP (mV) ^B	101.2	100.8	101.2	

Modulation Calibration Parameters


UID	Communication System Name	PAR		A dB	B dB	C dB	VR mV	Unc ^C (k=2)
10000	CW	0.00	X	0.00	0.00	1.00	107.7	±1.7 %
			Y	0.00	0.00	1.00	113.4	
			Z	0.00	0.00	1.00	110.4	


The reported uncertainty of measurement is stated as the standard uncertainty of measurement multiplied by the coverage factor k=2, which for a normal distribution corresponds to a coverage probability of approximately 95%.

^A The uncertainties of NormX,Y,Z do not affect the E²-field uncertainty inside TSL (see Pages 5 and 6).

^B Numerical linearization parameter: uncertainty not required.

^C Uncertainty is determined using the max. deviation from linear response applying rectangular distribution and is expressed for the square of the field value.

	Document Appendix D for the BlackBerry® Smartphone Model RFA91LW SAR Report			Page 6(114)
Author Data Andrew Becker	Dates of Test Aug 21 – Nov 23, 2012 Jan. 07-11, 2013	Test Report No RTS-6012-1211-32 Rev 3	FCC ID: L6ARFA90LW	IC ID 2503A-RFA90LW

	Document Appendix D for the BlackBerry® Smartphone Model RFA91LW SAR Report			Page 7(114)
	Author Data Andrew Becker	Dates of Test Aug 21 – Nov 23, 2012 Jan. 07-11, 2013	Test Report No RTS-6012-1211-32 Rev 3	FCC ID: L6ARFA90LW

ES3DV3- SN:3225

January 11, 2012


DASY/EASY - Parameters of Probe: ES3DV3 - SN:3225


Calibration Parameter Determined in Head Tissue Simulating Media

f (MHz) ^C	Relative Permittivity ^F	Conductivity (S/m) ^F	ConvF X	ConvF Y	ConvF Z	Alpha	Depth (mm)	Unct. (k=2)
750	41.9	0.89	6.42	6.42	6.42	0.27	2.04	± 12.0 %
900	41.5	0.97	6.06	6.06	6.06	0.35	1.74	± 12.0 %
1810	40.0	1.40	5.23	5.23	5.23	0.73	1.21	± 12.0 %
1950	40.0	1.40	4.98	4.98	4.98	0.58	1.41	± 12.0 %
2450	39.2	1.80	4.50	4.50	4.50	0.79	1.26	± 12.0 %
2600	39.0	1.96	4.32	4.32	4.32	0.77	1.32	± 12.0 %

^C Frequency validity of ± 100 MHz only applies for DASY v4.4 and higher (see Page 2), else it is restricted to ± 50 MHz. The uncertainty is the RSS of the ConvF uncertainty at calibration frequency and the uncertainty for the indicated frequency band.

^F At frequencies below 3 GHz, the validity of tissue parameters (ϵ and σ) can be relaxed to ± 10% if liquid compensation formula is applied to measured SAR values. At frequencies above 3 GHz, the validity of tissue parameters (ϵ and σ) is restricted to ± 5%. The uncertainty is the RSS of the ConvF uncertainty for indicated target tissue parameters.

	Document Appendix D for the BlackBerry® Smartphone Model RFA91LW SAR Report			Page 8(114)
Author Data Andrew Becker	Dates of Test Aug 21 – Nov 23, 2012 Jan. 07-11, 2013	Test Report No RTS-6012-1211-32 Rev 3	FCC ID: L6ARFA90LW	IC ID 2503A-RFA90LW

	Document Appendix D for the BlackBerry® Smartphone Model RFA91LW SAR Report			Page 9(114)
	Author Data Andrew Becker	Dates of Test Aug 21 – Nov 23, 2012 Jan. 07-11, 2013	Test Report No RTS-6012-1211-32 Rev 3	FCC ID: L6ARFA90LW

ES3DV3- SN:3225

January 11, 2012


DASY/EASY - Parameters of Probe: ES3DV3 - SN:3225

Calibration Parameter Determined in Body Tissue Simulating Media

f (MHz) ^C	Relative Permittivity ^F	Conductivity (S/m) ^F	ConvF X	ConvF Y	ConvF Z	Alpha	Depth (mm)	Unct. (k=2)
750	55.5	0.96	6.27	6.27	6.27	0.36	1.74	± 12.0 %
900	55.0	1.05	6.07	6.07	6.07	0.29	2.02	± 12.0 %
1810	53.3	1.52	4.92	4.92	4.92	0.50	1.57	± 12.0 %
1950	53.3	1.52	4.87	4.87	4.87	0.59	1.49	± 12.0 %
2450	52.7	1.95	4.30	4.30	4.30	0.68	1.16	± 12.0 %
2600	52.5	2.16	4.12	4.12	4.12	0.80	0.99	± 12.0 %

^C Frequency validity of ± 100 MHz only applies for DASY v4.4 and higher (see Page 2), else it is restricted to ± 50 MHz. The uncertainty is the RSS of the ConvF uncertainty at calibration frequency and the uncertainty for the indicated frequency band.


^F At frequencies below 3 GHz, the validity of tissue parameters (ϵ and σ) can be relaxed to ± 10% if liquid compensation formula is applied to measured SAR values. At frequencies above 3 GHz, the validity of tissue parameters (ϵ and σ) is restricted to ± 5%. The uncertainty is the RSS of the ConvF uncertainty for indicated target tissue parameters.

	Document Appendix D for the BlackBerry® Smartphone Model RFA91LW SAR Report			Page 10(114)
	Author Data Andrew Becker	Dates of Test Aug 21 – Nov 23, 2012 Jan. 07-11, 2013	Test Report No RTS-6012-1211-32 Rev 3	FCC ID: L6ARFA90LW

ES3DV3- SN:3225

January 11, 2012

Frequency Response of E-Field (TEM-Cell:ifi110 EXX, Waveguide: R22)



Uncertainty of Frequency Response of E-field: $\pm 6.3\%$ (k=2)

Author Data
Andrew Becker

Dates of Test
**Aug 21 – Nov 23, 2012
 Jan. 07-11, 2013**

Test Report No
RTS-6012-1211-32 Rev 3



FCC ID:
L6ARFA90LW

IC ID
2503A-RFA90LW


ES3DV3– SN:3225

January 11, 2012

Receiving Pattern (ϕ), $\theta = 0^\circ$



Uncertainty of Axial Isotropy Assessment: $\pm 0.5\%$ ($k=2$)

	Document Appendix D for the BlackBerry® Smartphone Model RFA91LW SAR Report			Page 12(114)
Author Data Andrew Becker	Dates of Test Aug 21 – Nov 23, 2012 Jan. 07-11, 2013	Test Report No RTS-6012-1211-32 Rev 3	FCC ID: L6ARFA90LW	IC ID 2503A-RFA90LW

Author Data
Andrew Becker

Dates of Test
**Aug 21 – Nov 23, 2012
 Jan. 07-11, 2013**

Test Report No
RTS-6012-1211-32 Rev 3



FCC ID:
L6ARFA90LW

IC ID
2503A-RFA90LW


ES3DV3– SN:3225

January 11, 2012

Dynamic Range $f(SAR_{head})$ (TEM cell , $f = 900$ MHz)



Uncertainty of Linearity Assessment: $\pm 0.6\%$ ($k=2$)

	Document Appendix D for the BlackBerry® Smartphone Model RFA91LW SAR Report			Page 14(114)
Author Data Andrew Becker	Dates of Test Aug 21 – Nov 23, 2012 Jan. 07-11, 2013	Test Report No RTS-6012-1211-32 Rev 3	FCC ID: L6ARFA90LW	IC ID 2503A-RFA90LW

Author Data
Andrew Becker

Dates of Test
**Aug 21 – Nov 23, 2012
 Jan. 07-11, 2013**

Test Report No
RTS-6012-1211-32 Rev 3


FCC ID:
L6ARFA90LW

IC ID
2503A-RFA90LW



ES3DV3–SN:3225


January 11, 2012


Conversion Factor Assessment



Deviation from Isotropy in Liquid Error (ϕ , θ), f = 900 MHz



	Document Appendix D for the BlackBerry® Smartphone Model RFA91LW SAR Report			Page 16(114)
Author Data Andrew Becker	Dates of Test Aug 21 – Nov 23, 2012 Jan. 07-11, 2013	Test Report No RTS-6012-1211-32 Rev 3	FCC ID: L6ARFA90LW	IC ID 2503A-RFA90LW

	Document Appendix D for the BlackBerry® Smartphone Model RFA91LW SAR Report			Page 17(114)
	Author Data Andrew Becker	Dates of Test Aug 21 – Nov 23, 2012 Jan. 07-11, 2013	Test Report No RTS-6012-1211-32 Rev 3	FCC ID: L6ARFA90LW


ES3DV3– SN:3225

January 11, 2012

DASY/EASY - Parameters of Probe: ES3DV3 - SN:3225

Other Probe Parameters

Sensor Arrangement	Triangular
Connector Angle (°)	Not applicable
Mechanical Surface Detection Mode	enabled
Optical Surface Detection Mode	disabled
Probe Overall Length	337 mm
Probe Body Diameter	10 mm
Tip Length	10 mm
Tip Diameter	4 mm
Probe Tip to Sensor X Calibration Point	2 mm
Probe Tip to Sensor Y Calibration Point	2 mm
Probe Tip to Sensor Z Calibration Point	2 mm
Recommended Measurement Distance from Surface	3 mm

	Document Appendix D for the BlackBerry® Smartphone Model RFA91LW SAR Report			Page 18(114)
	Author Data Andrew Becker	Dates of Test Aug 21 – Nov 23, 2012 Jan. 07-11, 2013	Test Report No RTS-6012-1211-32 Rev 3	FCC ID: L6ARFA90LW

**Calibration Laboratory of
Schmid & Partner
Engineering AG**
 Zeughausstrasse 43, 8004 Zurich, Switzerland



S Schweizerischer Kalibrierdienst
 S Service suisse d'étalonnage
 S Servizio svizzero di taratura
 S Swiss Calibration Service

Accredited by the Swiss Accreditation Service (SAS)
 The Swiss Accreditation Service is one of the signatories to the EA
 Multilateral Agreement for the recognition of calibration certificates

Accreditation No.: **SCS 108**



Client **RTS (RIM Testing Services)**


Certificate No: **EX3-3592_Nov12**

CALIBRATION CERTIFICATE

Object: **EX3DV4 - SN:3592**
 Calibration procedure(s): **QA CAL-01.v8, QA CAL-14.v3, QA CAL-23.v4, QA CAL-25.v4
Calibration procedure for dosimetric E-field probes**
 Calibration date: **November 14, 2012**
 This calibration certificate documents the traceability to national standards, which realize the physical units of measurements (SI).
 The measurements and the uncertainties with confidence probability are given on the following pages and are part of the certificate.
 All calibrations have been conducted in the closed laboratory facility, environment temperature (22 ± 3)°C and humidity < 70%.
 Calibration Equipment used (M&TE critical for calibration)

Primary Standards	ID	Cal Date (Certificate No.)	Scheduled Calibration
Power meter E4419B	GB41293874	29-Mar-12 (No. 217-0150B)	Apr-13
Power sensor E4412A	MY41499037	29-Mar-12 (No. 217-0150B)	Apr-13
Reference 3 dB Attenuator	SN: S5054 (3c)	27-Mar-12 (No. 217-01551)	Apr-13
Reference 20 dB Attenuator	SN: S5086 (20b)	27-Mar-12 (No. 217-01529)	Apr-13
Reference 30 dB Attenuator	SN: S5125 (30b)	27-Mar-12 (No. 217-01532)	Apr-13
Reference Probe ES3DV2	SN: 3D13	29-Dec-11 (No. ES3-3013, Dec11)	Dec-12
DAE4	SN: 660	20-Jun-12 (No. DAE4-660, Jun12)	Jun-13
Secondary Standards	ID	Check Date (in house)	Scheduled Check
RF generator HP 8648C	US3642U01700	4-Aug-99 (in house check Apr-11)	In house check: Apr-13
Network Analyzer HP 8753E	US37380585	18-Oct-01 (in house check Oct-12)	In house check: Oct-13

Calibrated by: **Claudio Leubler** (Name), **Laboratory Technician** (Function),  (Signature)
 Approved by: **Katja Pokovic** (Name), **Technical Manager** (Function),  (Signature)
 Issued: November 14, 2012
 This calibration certificate shall not be reproduced except in full without written approval of the laboratory.

	Document Appendix D for the BlackBerry® Smartphone Model RFA91LW SAR Report			Page 19(114)
	Author Data Andrew Becker	Dates of Test Aug 21 – Nov 23, 2012 Jan. 07-11, 2013	Test Report No RTS-6012-1211-32 Rev 3	FCC ID: L6ARFA90LW

**Calibration Laboratory of
Schmid & Partner
Engineering AG**
 Zeughausstrasse 43, 8004 Zurich, Switzerland



S Schweizerischer Kalibrierdienst
 S Service suisse d'étalonnage
 S Servizio svizzero di taratura
 S Swiss Calibration Service

Accredited by the Swiss Accreditation Service (SAS)
 The Swiss Accreditation Service is one of the signatories to the EA
 Multilateral Agreement for the recognition of calibration certificates

Accreditation No.: **SCS 108**

Glossary:


TSL tissue simulating liquid
 NORM_{x,y,z} sensitivity in free space
 ConvF sensitivity in TSL / NORM_{x,y,z}
 DCP diode compression point
 CF crest factor (1/duty_cycle) of the RF signal
 A, B, C modulation dependent linearization parameters
 Polarization φ φ rotation around probe axis
 Polarization θ θ rotation around an axis that is in the plane normal to probe axis (at measurement center),
 i.e., θ = 0 is normal to probe axis

Calibration is Performed According to the Following Standards:

- IEEE Std 1528-2003, "IEEE Recommended Practice for Determining the Peak Spatial-Averaged Specific Absorption Rate (SAR) in the Human Head from Wireless Communications Devices: Measurement Techniques", December 2003
- IEC 62209-1, "Procedure to measure the Specific Absorption Rate (SAR) for hand-held devices used in close proximity to the ear (frequency range of 300 MHz to 3 GHz)", February 2005

Methods Applied and Interpretation of Parameters:

- NORM_{x,y,z}:** Assessed for E-field polarization θ = 0 (f ≤ 900 MHz in TEM-cell; f > 1800 MHz: R22 waveguide). NORM_{x,y,z} are only intermediate values, i.e., the uncertainties of NORM_{x,y,z} does not affect the E²-field uncertainty inside TSL (see below ConvF).
- NORM(f)_{x,y,z} = NORM_{x,y,z} * frequency_response** (see Frequency Response Chart). This linearization is implemented in DASY4 software versions later than 4.2. The uncertainty of the frequency response is included in the stated uncertainty of ConvF.
- DCP_{x,y,z}:** DCP are numerical linearization parameters assessed based on the data of power sweep with CW signal (no uncertainty required). DCP does not depend on frequency nor media.
- PAR:** PAR is the Peak to Average Ratio that is not calibrated but determined based on the signal characteristics
- A_{x,y,z}; B_{x,y,z}; C_{x,y,z}; VR_{x,y,z}:** A, B, C are numerical linearization parameters assessed based on the data of power sweep for specific modulation signal. The parameters do not depend on frequency nor media. VR is the maximum calibration range expressed in RMS voltage across the diode.
- ConvF and Boundary Effect Parameters:** Assessed in flat phantom using E-field (or Temperature Transfer Standard for f ≤ 800 MHz) and inside waveguide using analytical field distributions based on power measurements for f > 800 MHz. The same setups are used for assessment of the parameters applied for boundary compensation (alpha, depth) of which typical uncertainty values are given. These parameters are used in DASY4 software to improve probe accuracy close to the boundary. The sensitivity in TSL corresponds to NORM_{x,y,z} * ConvF whereby the uncertainty corresponds to that given for ConvF. A frequency dependent ConvF is used in DASY version 4.4 and higher which allows extending the validity from ± 50 MHz to ± 100 MHz.
- Spherical isotropy (3D deviation from isotropy):** in a field of low gradients realized using a flat phantom exposed by a patch antenna.
- Sensor Offset:** The sensor offset corresponds to the offset of virtual measurement center from the probe tip (on probe axis). No tolerance required.

	Document Appendix D for the BlackBerry® Smartphone Model RFA91LW SAR Report			Page 20(114)
	Author Data Andrew Becker	Dates of Test Aug 21 – Nov 23, 2012 Jan. 07-11, 2013	Test Report No RTS-6012-1211-32 Rev 3	FCC ID: L6ARFA90LW

EX3DV4 – SN:3592


November 14, 2012

Probe EX3DV4

SN:3592

Manufactured: September 18, 2006
Calibrated: November 14, 2012

Calibrated for DASY/EASY Systems
(Note: non-compatible with DASY2 system!)

	Document Appendix D for the BlackBerry® Smartphone Model RFA91LW SAR Report			Page 21(114)
	Author Data Andrew Becker	Dates of Test Aug 21 – Nov 23, 2012 Jan. 07-11, 2013	Test Report No RTS-6012-1211-32 Rev 3	FCC ID: L6ARFA90LW

EX3DV4- SN:3592

November 14, 2012

DASY/EASY - Parameters of Probe: EX3DV4 - SN:3592

Basic Calibration Parameters

	Sensor X	Sensor Y	Sensor Z	Unc (k=2)
Norm. ($\mu\text{V}/(\text{V}/\text{m})^2$) ^A	0.49	0.47	0.41	$\pm 10.1\%$
DCP (mV) ^B	95.2	96.1	100.6	

Modulation Calibration Parameters


UID	Communication System Name	PAR		A dB	B dB	C dB	VR mV	Unc ^C (k=2)
0	CW	0.00	X	0.0	0.0	1.0	121.4	$\pm 3.0\%$
			Y	0.0	0.0	1.0	104.3	
			Z	0.0	0.0	1.0	109.2	

The reported uncertainty of measurement is stated as the standard uncertainty of measurement multiplied by the coverage factor $k=2$, which for a normal distribution corresponds to a coverage probability of approximately 95%.

^A The uncertainties of Norm X, Y, Z do not affect the E^2 -field uncertainty inside TSI. (see Pages 5 and 6).

^B Numerical linearization parameter; uncertainty not required.

^C Uncertainty is determined using the max. deviation from linear response applying rectangular distribution and is expressed for the square of the field value.

	Document Appendix D for the BlackBerry® Smartphone Model RFA91LW SAR Report			Page 22(114)
	Author Data Andrew Becker	Dates of Test Aug 21 – Nov 23, 2012 Jan. 07-11, 2013	Test Report No RTS-6012-1211-32 Rev 3	FCC ID: L6ARFA90LW

EX3DV4- SN:3592

November 14, 2012


DASY/EASY - Parameters of Probe: EX3DV4 - SN:3592

Calibration Parameter Determined in Head Tissue Simulating Media

f (MHz) ^C	Relative Permittivity ^F	Conductivity (S/m) ^F	ConvF X	ConvF Y	ConvF Z	Alpha	Depth (mm)	Unct. (k=2)
2600	39.0	1.96	6.45	6.45	6.45	0.53	0.79	± 12.0 %
5200	36.0	4.66	4.73	4.73	4.73	0.40	1.80	± 13.1 %
5500	35.6	4.96	4.28	4.28	4.28	0.44	1.80	± 13.1 %
5800	35.3	5.27	4.12	4.12	4.12	0.48	1.80	± 13.1 %

^C Frequency validity of ± 100 MHz only applies for DASY v4.4 and higher (see Page 2), else it is restricted to ± 50 MHz. The uncertainty is the RSS of the ConvF uncertainty at calibration frequency and the uncertainty for the indicated frequency band.

^F At frequencies below 3 GHz, the validity of tissue parameters (ϵ and σ) can be relaxed to ± 10% if liquid compensation formula is applied to measured SAR values. At frequencies above 3 GHz, the validity of tissue parameters (ϵ and σ) is restricted to ± 5%. The uncertainty is the RSS of the ConvF uncertainty for indicated target tissue parameters.

	Document Appendix D for the BlackBerry® Smartphone Model RFA91LW SAR Report			Page 23(114)
	Author Data Andrew Becker	Dates of Test Aug 21 – Nov 23, 2012 Jan. 07-11, 2013	Test Report No RTS-6012-1211-32 Rev 3	FCC ID: L6ARFA90LW

EX3DV4-- SN:3592

November 14, 2012


DASY/EASY - Parameters of Probe: EX3DV4 - SN:3592

Calibration Parameter Determined in Body Tissue Simulating Media

f (MHz) ^c	Relative Permittivity ^f	Conductivity (S/m) ^f	ConvF X	ConvF Y	ConvF Z	Alpha	Depth (mm)	Unct. (k=2)
2500	52.5	2.16	6.59	6.59	6.59	0.80	0.50	± 12.0 %
5200	49.0	5.30	4.02	4.02	4.02	0.48	1.90	± 13.1 %
5500	48.6	5.65	3.66	3.66	3.66	0.55	1.90	± 13.1 %
5800	48.2	6.00	3.57	3.57	3.57	0.57	1.90	± 13.1 %

^c Frequency validity of ± 100 MHz only applies for DASY v4.4 and higher (see Page 2), else it is restricted to ± 50 MHz. The uncertainty is the RSS of the ConvF uncertainty at calibration frequency and the uncertainty for the indicated frequency band.


^f At frequencies below 3 GHz, the validity of tissue parameters (ϵ and σ) can be relaxed to ± 10% if liquid compensation formula is applied to measured SAR values. At frequencies above 3 GHz, the validity of tissue parameters (ϵ and σ) is restricted to ± 5%. The uncertainty is the RSS of the ConvF uncertainty for indicated target tissue parameters.

	Document Appendix D for the BlackBerry® Smartphone Model RFA91LW SAR Report			Page 24(114)
	Author Data Andrew Becker	Dates of Test Aug 21 – Nov 23, 2012 Jan. 07-11, 2013	Test Report No RTS-6012-1211-32 Rev 3	FCC ID: L6ARFA90LW


EX3DV4– SN:3592

November 14, 2012

Frequency Response of E-Field
(TEM-Cell:ifi110 EXX, Waveguide: R22)





Uncertainty of Frequency Response of E-field: $\pm 6.3\%$ (k=2)

	Document Appendix D for the BlackBerry® Smartphone Model RFA91LW SAR Report			Page 25(114)
	Author Data Andrew Becker	Dates of Test Aug 21 – Nov 23, 2012 Jan. 07-11, 2013	Test Report No RTS-6012-1211-32 Rev 3	FCC ID: L6ARFA90LW

EX3DV4--SN:3592

November 14, 2012

Receiving Pattern (ϕ), $\theta = 0^\circ$



Uncertainty of Axial Isotropy Assessment: $\pm 0.5\%$ ($k=2$)

Author Data
Andrew Becker

Dates of Test
Aug 21 – Nov 23, 2012
Jan. 07-11, 2013

Test Report No
RTS-6012-1211-32 Rev 3



FCC ID:
L6ARFA90LW

IC ID
2503A-RFA90LW

EX3DV4- SN:3592

November 14, 2012

Dynamic Range f(SAR_{head})
 (TEM cell , f = 900 MHz)



Uncertainty of Linearity Assessment: $\pm 0.6\%$ (k=2)

Author Data
Andrew Becker

Dates of Test
**Aug 21 – Nov 23, 2012
 Jan. 07-11, 2013**

Test Report No
RTS-6012-1211-32 Rev 3


FCC ID:
L6ARFA90LW

IC ID
2503A-RFA90LW



EX3DV4- SN:3592

November 14, 2012

Conversion Factor Assessment



Deviation from Isotropy in Liquid Error (ϕ, θ), f = 900 MHz





Author Data
Andrew Becker

Dates of Test
**Aug 21 – Nov 23, 2012
Jan. 07-11, 2013**

Test Report No
RTS-6012-1211-32 Rev 3

FCC ID:
L6ARFA90LW

IC ID
2503A-RFA90LW


EX3DV4- SN:3592

November 14, 2012

DASY/EASY - Parameters of Probe: EX3DV4 - SN:3592

Other Probe Parameters

Sensor Arrangement	Triangular
Connector Angle (°)	-13.6
Mechanical Surface Detection Mode	enabled
Optical Surface Detection Mode	disabled
Probe Overall Length	337 mm
Probe Body Diameter	10 mm
Tip Length	9 mm
Tip Diameter	2.5 mm
Probe Tip to Sensor X Calibration Point	1 mm
Probe Tip to Sensor Y Calibration Point	1 mm
Probe Tip to Sensor Z Calibration Point	1 mm
Recommended Measurement Distance from Surface	2 mm

	Document Appendix D for the BlackBerry® Smartphone Model RFA91LW SAR Report			Page 29(114)
	Author Data Andrew Becker	Dates of Test Aug 21 – Nov 23, 2012 Jan. 07-11, 2013	Test Report No RTS-6012-1211-32 Rev 3	FCC ID: L6ARFA90LW

**Calibration Laboratory of
Schmid & Partner
Engineering AG**
 Zeughausstrasse 43, 8004 Zurich, Switzerland



S Schweizerischer Kalibrierdienst
S Service suisse d'étalonnage
S Servizio svizzero di taratura
S Swiss Calibration Service

Accredited by the Swiss Accreditation Service (SAS)
 The Swiss Accreditation Service is one of the signatories to the EA
 Multilateral Agreement for the recognition of calibration certificates



Accreditation No.: **SCS 108**


Client **RTS (RIM Testing Services)**


Certificate No: **EX3-3548_Jan12**

CALIBRATION CERTIFICATE	
Object	EX3DV4 - SN:3548
Calibration procedure(s)	QA CAL-01.v8; QA CAL-14.v3; QA CAL-23.v4; QA CAL-25.v4 Calibration procedure for dosimetric E-field probes
Calibration date:	January 14, 2012
<p>This calibration certificate documents the traceability to national standards, which realize the physical units of measurements (SI). The measurements and the uncertainties with confidence probability are given on the following pages and are part of the certificate.</p> <p>All calibrations have been conducted in the closed laboratory facility: environment temperature (22 ± 3)°C and humidity < 70%.</p> <p>Calibration Equipment used (M&T critical for calibration)</p>	

Primary Standards	ID	Cal Date (Certificate No.)	Scheduled Calibration
Power meter E4419B	GB41293874	31-Mar-11 (No. 217-01372)	Apr-12
Power sensor E4412A	MY41490087	31-Mar-11 (No. 217-01372)	Apr-12
Reference 3 dB Attenuator	SN: S5054 (3c)	29-Mar-11 (No. 217-01369)	Apr-12
Reference 20 dB Attenuator	SN: S5086 (20b)	29-Mar-11 (No. 217-01367)	Apr-12
Reference 30 dB Attenuator	SN: S5129 (30b)	29-Mar-11 (No. 217-01370)	Apr-12
Reference Probe ES3DV2	SN: 3013	29-Dec-11 (No. ES3-3013_Dec11)	Dec-12
DAE4	SN: 654	3-May-11 (No. DAE4-654_May11)	May-12
Secondary Standards	ID	Check Date (in house)	Scheduled Check
RF generator HP 8648C	US3642U01700	4-Aug-99 (in house check Apr-11)	In house check: Apr-13
Network Analyzer HP 8753E	US37390585	18-Oct-01 (in house check Oct-11)	In house check: Oct-12

Calibrated by:	Name Katja Pokovic	Function Technical Manager	Signature 
Approved by:	Name Niels Kueter	Quality Manager	
Issued: January 14, 2012			
This calibration certificate shall not be reproduced except in full without written approval of the laboratory.			

	Document Appendix D for the BlackBerry® Smartphone Model RFA91LW SAR Report			Page 30(114)
Author Data Andrew Becker	Dates of Test Aug 21 – Nov 23, 2012 Jan. 07-11, 2013	Test Report No RTS-6012-1211-32 Rev 3	FCC ID: L6ARFA90LW	IC ID 2503A-RFA90LW

	Document Appendix D for the BlackBerry® Smartphone Model RFA91LW SAR Report			Page 31(114)
	Author Data Andrew Becker	Dates of Test Aug 21 – Nov 23, 2012 Jan. 07-11, 2013	Test Report No RTS-6012-1211-32 Rev 3	FCC ID: L6ARFA90LW

**Calibration Laboratory of
Schmid & Partner
Engineering AG**
 Zeughausstrasse 43, 8004 Zurich, Switzerland



S Schweizerischer Kalibrierdienst
C Service suisse d'étalonnage
S Servizio svizzero di taratura
S Swiss Calibration Service

Accredited by the Swiss Accreditation Service (SAS)
 The Swiss Accreditation Service is one of the signatories to the EA
 Multilateral Agreement for the recognition of calibration certificates

Accreditation No.: **SCS 108**

Glossary:


TSL	tissue simulating liquid
NORM _{x,y,z}	sensitivity in free space
ConvF	sensitivity in TSL / NORM _{x,y,z}
DCP	diode compression point
CF	crest factor (1/duty_cycle) of the RF signal
A, B, C	modulation dependent linearization parameters
Polarization φ	φ rotation around probe axis
Polarization ϑ	ϑ rotation around an axis that is in the plane normal to probe axis (at measurement center), i.e., $\vartheta = 0$ is normal to probe axis

Calibration is Performed According to the Following Standards:

- IEEE Std 1528-2003, "IEEE Recommended Practice for Determining the Peak Spatial-Averaged Specific Absorption Rate (SAR) in the Human Head from Wireless Communications Devices: Measurement Techniques", December 2003
- IEC 62209-1, "Procedure to measure the Specific Absorption Rate (SAR) for hand-held devices used in close proximity to the ear (frequency range of 300 MHz to 3 GHz)", February 2005

Methods Applied and Interpretation of Parameters:

- NORM_{x,y,z}:** Assessed for E-field polarization $\vartheta = 0$ ($f \leq 900$ MHz in TEM-cell; $f > 1800$ MHz: R22 waveguide). NORM_{x,y,z} are only intermediate values, i.e., the uncertainties of NORM_{x,y,z} does not affect the E²-field uncertainty inside TSL (see below ConvF).
- NORM(f)_{x,y,z} = NORM_{x,y,z} * frequency_response** (see Frequency Response Chart). This linearization is implemented in DASY4 software versions later than 4.2. The uncertainty of the frequency response is included in the stated uncertainty of ConvF.
- DCP_{x,y,z}:** DCP are numerical linearization parameters assessed based on the data of power sweep with CW signal (no uncertainty required). DCP does not depend on frequency nor media.
- PAR:** PAR is the Peak to Average Ratio that is not calibrated but determined based on the signal characteristics
- A_{x,y,z}; B_{x,y,z}; C_{x,y,z}; VR_{x,y,z}:** A, B, C are numerical linearization parameters assessed based on the data of power sweep for specific modulation signal. The parameters do not depend on frequency nor media. VR is the maximum calibration range expressed in RMS voltage across the diode.
- ConvF and Boundary Effect Parameters:** Assessed in flat phantom using E-field (or Temperature Transfer Standard for $f \leq 800$ MHz) and inside waveguide using analytical field distributions based on power measurements for $f > 800$ MHz. The same setups are used for assessment of the parameters applied for boundary compensation (alpha, depth) of which typical uncertainty values are given. These parameters are used in DASY4 software to improve probe accuracy close to the boundary. The sensitivity in TSL corresponds to NORM_{x,y,z} * ConvF whereby the uncertainty corresponds to that given for ConvF. A frequency dependent ConvF is used in DASY version 4.4 and higher which allows extending the validity from ± 50 MHz to ± 100 MHz.
- Spherical isotropy (3D deviation from isotropy):** in a field of low gradients realized using a flat phantom exposed by a patch antenna.
- Sensor Offset:** The sensor offset corresponds to the offset of virtual measurement center from the probe tip (on probe axis). No tolerance required.

	Document Appendix D for the BlackBerry® Smartphone Model RFA91LW SAR Report			Page 32(114)
	Author Data Andrew Becker	Dates of Test Aug 21 – Nov 23, 2012 Jan. 07-11, 2013	Test Report No RTS-6012-1211-32 Rev 3	FCC ID: L6ARFA90LW

EX3DV4 – SN:3548


January 14, 2012

Probe EX3DV4

SN:3548

Manufactured: November 16, 2004
Calibrated: January 14, 2012

Calibrated for DASY/EASY Systems
(Note: non-compatible with DASY2 system!)

	Document Appendix D for the BlackBerry® Smartphone Model RFA91LW SAR Report			Page 33(114)
	Author Data Andrew Becker	Dates of Test Aug 21 – Nov 23, 2012 Jan. 07-11, 2013	Test Report No RTS-6012-1211-32 Rev 3	FCC ID: L6ARFA90LW

EX3DV4– SN:3548

January 14, 2012

DASY/EASY - Parameters of Probe: EX3DV4 - SN:3548

Basic Calibration Parameters

	Sensor X	Sensor Y	Sensor Z	Unc (k=2)
Norm ($\mu\text{V}/(\text{V}/\text{m})^2$) ^A	0.36	0.44	0.43	± 10.1 %
DCP (mV) ^B	101.1	99.7	97.8	

Modulation Calibration Parameters


UID	Communication System Name	PAR		A dB	B dB	C dB	VR mV	Unc ^E (k=2)
10000	CW	0.00	X	0.00	0.00	1.00	93.0	±2.5 %
			Y	0.00	0.00	1.00	100.4	
			Z	0.00	0.00	1.00	107.4	


The reported uncertainty of measurement is stated as the standard uncertainty of measurement multiplied by the coverage factor k=2, which for a normal distribution corresponds to a coverage probability of approximately 95%.

^A The uncertainties of NormX,Y,Z do not affect the E²-field uncertainty inside TSL (see Pages 5 and 6).

^B Numerical linearization parameter: uncertainty not required.

^E Uncertainty is determined using the max. deviation from linear response applying rectangular distribution and is expressed for the square of the field value.

	Document Appendix D for the BlackBerry® Smartphone Model RFA91LW SAR Report			Page 34(114)
Author Data Andrew Becker	Dates of Test Aug 21 – Nov 23, 2012 Jan. 07-11, 2013	Test Report No RTS-6012-1211-32 Rev 3	FCC ID: L6ARFA90LW	IC ID 2503A-RFA90LW

	Document Appendix D for the BlackBerry® Smartphone Model RFA91LW SAR Report			Page 35(114)
	Author Data Andrew Becker	Dates of Test Aug 21 – Nov 23, 2012 Jan. 07-11, 2013	Test Report No RTS-6012-1211-32 Rev 3	FCC ID: L6ARFA90LW


DASY/EASY - Parameters of Probe: EX3DV4 - SN:3548

Calibration Parameter Determined in Head Tissue Simulating Media

f (MHz) ^c	Relative Permittivity ^f	Conductivity (S/m) ^f	ConvF X	ConvF Y	ConvF Z	Alpha	Depth (mm)	Unct. (k=2)
2600	39.0	1.96	7.15	7.15	7.15	0.34	1.00	± 12.0 %
5200	36.0	4.66	4.98	4.98	4.98	0.40	1.80	± 13.1 %
5500	35.6	4.96	4.80	4.80	4.80	0.42	1.80	± 13.1 %
5800	35.3	5.27	4.44	4.44	4.44	0.50	1.80	± 13.1 %

^c Frequency validity of ± 100 MHz only applies for DASY v4.4 and higher (see Page 2), else it is restricted to ± 50 MHz. The uncertainty is the RSS of the ConvF uncertainty at calibration frequency and the uncertainty for the indicated frequency band.

^f At frequencies below 3 GHz, the validity of tissue parameters (ϵ and σ) can be relaxed to ± 10% if liquid compensation formula is applied to measured SAR values. At frequencies above 3 GHz, the validity of tissue parameters (ϵ and σ) is restricted to ± 5%. The uncertainty is the RSS of the ConvF uncertainty for indicated target tissue parameters.

	Document Appendix D for the BlackBerry® Smartphone Model RFA91LW SAR Report			Page 36(114)
	Author Data Andrew Becker	Dates of Test Aug 21 – Nov 23, 2012 Jan. 07-11, 2013	Test Report No RTS-6012-1211-32 Rev 3	FCC ID: L6ARFA90LW

EX3DV4– SN:3548

January 14, 2012


DASY/EASY - Parameters of Probe: EX3DV4 - SN:3548


Calibration Parameter Determined in Body Tissue Simulating Media

f (MHz) ^C	Relative Permittivity ^F	Conductivity (S/m) ^F	ConvF X	ConvF Y	ConvF Z	Alpha	Depth (mm)	Unct. (k=2)
2600	52.5	2.16	7.40	7.40	7.40	0.80	0.64	± 12.0 %
5200	49.0	5.30	4.55	4.55	4.55	0.58	1.90	± 13.1 %
5500	48.6	5.65	4.08	4.08	4.08	0.58	1.90	± 13.1 %
5800	48.2	6.00	4.19	4.19	4.19	0.58	1.90	± 13.1 %

^C Frequency validity of ± 100 MHz only applies for DASY v4.4 and higher (see Page 2), else it is restricted to ± 50 MHz. The uncertainty is the RSS of the ConvF uncertainty at calibration frequency and the uncertainty for the indicated frequency band.

^F At frequencies below 3 GHz, the validity of tissue parameters (ϵ and σ) can be relaxed to ± 10% if liquid compensation formula is applied to measured SAR values. At frequencies above 3 GHz, the validity of tissue parameters (ϵ and σ) is restricted to ± 5%. The uncertainty is the RSS of the ConvF uncertainty for indicated target tissue parameters.


	Document Appendix D for the BlackBerry® Smartphone Model RFA91LW SAR Report			Page 37(114)
Author Data Andrew Becker	Dates of Test Aug 21 – Nov 23, 2012 Jan. 07-11, 2013	Test Report No RTS-6012-1211-32 Rev 3	FCC ID: L6ARFA90LW	IC ID 2503A-RFA90LW

	Document Appendix D for the BlackBerry® Smartphone Model RFA91LW SAR Report			Page 38(114)
	Author Data Andrew Becker	Dates of Test Aug 21 – Nov 23, 2012 Jan. 07-11, 2013	Test Report No RTS-6012-1211-32 Rev 3	FCC ID: L6ARFA90LW


EX3DV4– SN:3548

January 14, 2012

Frequency Response of E-Field (TEM-Cell:ifi110 EXX, Waveguide: R22)



Uncertainty of Frequency Response of E-field: $\pm 6.3\%$ (k=2)

	Document Appendix D for the BlackBerry® Smartphone Model RFA91LW SAR Report			Page 39(114)
Author Data Andrew Becker	Dates of Test Aug 21 – Nov 23, 2012 Jan. 07-11, 2013	Test Report No RTS-6012-1211-32 Rev 3	FCC ID: L6ARFA90LW	IC ID 2503A-RFA90LW

Author Data
Andrew Becker

Dates of Test
**Aug 21 – Nov 23, 2012
 Jan. 07-11, 2013**

Test Report No
RTS-6012-1211-32 Rev 3

FCC ID:
L6ARFA90LW


IC ID
2503A-RFA90LW

EX3DV4-- SN:3548



January 14, 2012

Receiving Pattern (ϕ), $\theta = 0^\circ$


f=600 MHz, TEM



f=1800 MHz, R22



Uncertainty of Axial Isotropy Assessment: $\pm 0.5\%$ (k=2)

	Document Appendix D for the BlackBerry® Smartphone Model RFA91LW SAR Report			Page 41(114)
Author Data Andrew Becker	Dates of Test Aug 21 – Nov 23, 2012 Jan. 07-11, 2013	Test Report No RTS-6012-1211-32 Rev 3	FCC ID: L6ARFA90LW	IC ID 2503A-RFA90LW

Author Data
Andrew Becker

Dates of Test
**Aug 21 – Nov 23, 2012
 Jan. 07-11, 2013**

Test Report No
RTS-6012-1211-32 Rev 3



FCC ID:
L6ARFA90LW

IC ID
2503A-RFA90LW


EX3DV4– SN:3548

January 14, 2012

Dynamic Range f(SAR_{head}) (TEM cell , f = 900 MHz)



Uncertainty of Linearity Assessment: ± 0.6% (k=2)

	Document Appendix D for the BlackBerry® Smartphone Model RFA91LW SAR Report			Page 43(114)
Author Data Andrew Becker	Dates of Test Aug 21 – Nov 23, 2012 Jan. 07-11, 2013	Test Report No RTS-6012-1211-32 Rev 3	FCC ID: L6ARFA90LW	IC ID 2503A-RFA90LW

Author Data
Andrew Becker

Dates of Test
**Aug 21 – Nov 23, 2012
 Jan. 07-11, 2013**

Test Report No
RTS-6012-1211-32 Rev 3


FCC ID:
L6ARFA90LW

IC ID
2503A-RFA90LW


EX3DV4– SN:3548


January 14, 2012


Conversion Factor Assessment



Deviation from Isotropy in Liquid Error (ϕ , θ), $f = 900$ MHz



	Document Appendix D for the BlackBerry® Smartphone Model RFA91LW SAR Report			Page 45(114)
Author Data Andrew Becker	Dates of Test Aug 21 – Nov 23, 2012 Jan. 07-11, 2013	Test Report No RTS-6012-1211-32 Rev 3	FCC ID: L6ARFA90LW	IC ID 2503A-RFA90LW

	Document Appendix D for the BlackBerry® Smartphone Model RFA91LW SAR Report			Page 46(114)
	Author Data Andrew Becker	Dates of Test Aug 21 – Nov 23, 2012 Jan. 07-11, 2013	Test Report No RTS-6012-1211-32 Rev 3	FCC ID: L6ARFA90LW


EX3DV4– SN:3548

January 14, 2012

DASY/EASY - Parameters of Probe: EX3DV4 - SN:3548

Other Probe Parameters

Sensor Arrangement	Triangular
Connector Angle (°)	Not applicable
Mechanical Surface Detection Mode	enabled
Optical Surface Detection Mode	disabled
Probe Overall Length	337 mm
Probe Body Diameter	10 mm
Tip Length	9 mm
Tip Diameter	2.5 mm
Probe Tip to Sensor X Calibration Point	1 mm
Probe Tip to Sensor Y Calibration Point	1 mm
Probe Tip to Sensor Z Calibration Point	1 mm
Recommended Measurement Distance from Surface	2 mm

	Document Appendix D for the BlackBerry® Smartphone Model RFA91LW SAR Report			Page 47(114)
	Author Data Andrew Becker	Dates of Test Aug 21 – Nov 23, 2012 Jan. 07-11, 2013	Test Report No RTS-6012-1211-32 Rev 3	FCC ID: L6ARFA90LW

**Calibration Laboratory of
Schmid & Partner
Engineering AG**
 Zeughausstrasse 43, 8004 Zurich, Switzerland



S Schweizerischer Kalibrierdienst
C Service suisse d'étalonnage
S Servizio svizzero di taratura
S Swiss Calibration Service

Accredited by the Swiss Accreditation Service (SAS)
 The Swiss Accreditation Service is one of the signatories to the EA
 Multilateral Agreement for the recognition of calibration certificates

Accreditation No.: **SCS 108**

Client **RIM**

Certificate No: **D750V3-1021_Jan11**

CALIBRATION CERTIFICATE



Object **D750V3 - SN: 1021**
 Calibration procedure(s) **QA CAL-05.v8
Calibration procedure for dipole validation kits**
 Calibration date: **January 05, 2011**

This calibration certificate documents the traceability to national standards, which realize the physical units of measurements (SI).
 The measurements and the uncertainties with confidence probability are given on the following pages and are part of the certificate.

All calibrations have been conducted in the closed laboratory facility: environment temperature (22 ± 3)°C and humidity < 70%.


Calibration Equipment used (M&TE critical for calibration)


Primary Standards	ID #	Cal Date (Certificate No.)	Scheduled Calibration
Power meter EPM-442A	GB37480704	06-Oct-10 (No. 217-01266)	Oct-11
Power sensor HP 8481A	US37292783	06-Oct-10 (No. 217-01266)	Oct-11
Reference 20 dB Attenuator	SN: 5086 (20g)	30-Mar-10 (No. 217-01158)	Mar-11
Type-N mismatch combination	SN: 5047.2 / 06327	30-Mar-10 (No. 217-01162)	Mar-11
Reference Probe ES3DV3	SN: 3205	30-Apr-10 (No. ES3-3205_Apr10)	Apr-11
DAE4	SN: 601	10-Jun-10 (No. DAE4-601_Jun10)	Jun-11
Secondary Standards	ID #	Check Date (in house)	Scheduled Check
Power sensor HP 8481A	MY41092317	18-Oct-02 (in house check Oct-09)	in house check: Oct-11
RF generator R&S SMT-06	100005	4-Aug-99 (in house check Oct-09)	in house check: Oct-11
Network Analyzer HP 8753E	US37390585 S4206	18-Oct-01 (in house check Oct-10)	in house check: Oct-11

Calibrated by: **Jeton Kastrioti** (Name) / **Laboratory Technician** (Function) /  (Signature)
 Approved by: **Katja Pokovic** (Name) / **Technical Manager** (Function) /  (Signature)

Issued: January 6, 2011

This calibration certificate shall not be reproduced except in full without written approval of the laboratory.

	Document Appendix D for the BlackBerry® Smartphone Model RFA91LW SAR Report			Page 48(114)
Author Data Andrew Becker	Dates of Test Aug 21 – Nov 23, 2012 Jan. 07-11, 2013	Test Report No RTS-6012-1211-32 Rev 3	FCC ID: L6ARFA90LW	IC ID 2503A-RFA90LW

	Document Appendix D for the BlackBerry® Smartphone Model RFA91LW SAR Report			Page 49(114)
	Author Data Andrew Becker	Dates of Test Aug 21 – Nov 23, 2012 Jan. 07-11, 2013	Test Report No RTS-6012-1211-32 Rev 3	FCC ID: L6ARFA90LW

**Calibration Laboratory of
Schmid & Partner
Engineering AG**
 Zeughausstrasse 43, 8004 Zurich, Switzerland



S Schweizerischer Kalibrierdienst
C Service suisse d'étalonnage
S Servizio svizzero di taratura
S Swiss Calibration Service

Accredited by the Swiss Accreditation Service (SAS)
 The Swiss Accreditation Service is one of the signatories to the EA
 Multilateral Agreement for the recognition of calibration certificates

Accreditation No.: **SCS 108**

Glossary:

TSL tissue simulating liquid
 ConvF sensitivity in TSL / NORM x,y,z
 N/A not applicable or not measured

Calibration is Performed According to the Following Standards:


- a) IEEE Std 1528-2003, "IEEE Recommended Practice for Determining the Peak Spatial-Averaged Specific Absorption Rate (SAR) in the Human Head from Wireless Communications Devices: Measurement Techniques", December 2003
- b) IEC 62209-1, "Procedure to measure the Specific Absorption Rate (SAR) for hand-held devices used in close proximity to the ear (frequency range of 300 MHz to 3 GHz)", February 2005
- c) Federal Communications Commission Office of Engineering & Technology (FCC OET), "Evaluating Compliance with FCC Guidelines for Human Exposure to Radiofrequency Electromagnetic Fields; Additional Information for Evaluating Compliance of Mobile and Portable Devices with FCC Limits for Human Exposure to Radiofrequency Emissions", Supplement C (Edition 01-01) to Bulletin 65

Additional Documentation:

- d) DASY4/5 System Handbook

Methods Applied and Interpretation of Parameters:

- *Measurement Conditions:* Further details are available from the Validation Report at the end of the certificate. All figures stated in the certificate are valid at the frequency indicated.
- *Antenna Parameters with TSL:* The dipole is mounted with the spacer to position its feed point exactly below the center marking of the flat phantom section, with the arms oriented parallel to the body axis.
- *Feed Point Impedance and Return Loss:* These parameters are measured with the dipole positioned under the liquid filled phantom. The impedance stated is transformed from the measurement at the SMA connector to the feed point. The Return Loss ensures low reflected power. No uncertainty required.
- *Electrical Delay:* One-way delay between the SMA connector and the antenna feed point. No uncertainty required.
- *SAR measured:* SAR measured at the stated antenna input power.
- *SAR normalized:* SAR as measured, normalized to an input power of 1 W at the antenna connector.
- *SAR for nominal TSL parameters:* The measured TSL parameters are used to calculate the nominal SAR result.

	Document Appendix D for the BlackBerry® Smartphone Model RFA91LW SAR Report			Page 50(114)
	Author Data Andrew Becker	Dates of Test Aug 21 – Nov 23, 2012 Jan. 07-11, 2013	Test Report No RTS-6012-1211-32 Rev 3	FCC ID: L6ARFA90LW

Measurement Conditions

DASY system configuration, as far as not given on page 1.

DASY Version	DASY5	V52.6
Extrapolation	Advanced Extrapolation	
Phantom	Modular Flat Phantom V4.9	
Distance Dipole Center - TSL	15 mm	with Spacer
Zoom Scan Resolution	dx, dy, dz = 5 mm	
Frequency	750 MHz ± 1 MHz	

Head TSL parameters


The following parameters and calculations were applied.

	Temperature	Permittivity	Conductivity
Nominal Head TSL parameters	22.0 °C	41.9	0.89 mho/m
Measured Head TSL parameters	(22.0 ± 0.2) °C	42.3 ± 6 %	0.91 mho/m ± 6 %
Head TSL temperature during test	(22.0 ± 0.2) °C	----	----

SAR result with Head TSL

SAR averaged over 1 cm ³ (1 g) of Head TSL	Condition	
SAR measured	250 mW input power	2.12 mW / g
SAR normalized	normalized to 1W	8.48 mW / g
SAR for nominal Head TSL parameters	normalized to 1W	8.36 mW / g ± 17.0 % (k=2)

SAR averaged over 10 cm ³ (10 g) of Head TSL	condition	
SAR measured	250 mW input power	1.38 mW / g
SAR normalized	normalized to 1W	5.52 mW / g
SAR for nominal Head TSL parameters	normalized to 1W	5.45 mW / g ± 16.5 % (k=2)

	Document Appendix D for the BlackBerry® Smartphone Model RFA91LW SAR Report			Page 51(114)
	Author Data Andrew Becker	Dates of Test Aug 21 – Nov 23, 2012 Jan. 07-11, 2013	Test Report No RTS-6012-1211-32 Rev 3	FCC ID: L6ARFA90LW

Appendix

Antenna Parameters with Head TSL

Impedance, transformed to feed point	53.1 Ω - 1.7 $\mu\Omega$
Return Loss	- 29.3 dB

General Antenna Parameters and Design

Electrical Delay (one direction)	1.033 ns
----------------------------------	----------


After long term use with 100W radiated power, only a slight warming of the dipole near the feedpoint can be measured.


The dipole is made of standard semirigid coaxial cable. The center conductor of the feeding line is directly connected to the second arm of the dipole. The antenna is therefore short-circuited for DC-signals.

No excessive force must be applied to the dipole arms, because they might bend or the soldered connections near the feedpoint may be damaged.

Additional EUT Data

Manufactured by	SPEAG
Manufactured on	December 01, 2010

	Document Appendix D for the BlackBerry® Smartphone Model RFA91LW SAR Report			Page 52(114)
Author Data Andrew Becker	Dates of Test Aug 21 – Nov 23, 2012 Jan. 07-11, 2013	Test Report No RTS-6012-1211-32 Rev 3	FCC ID: L6ARFA90LW	IC ID 2503A-RFA90LW

	Document Appendix D for the BlackBerry® Smartphone Model RFA91LW SAR Report			Page 53(114)
	Author Data Andrew Becker	Dates of Test Aug 21 – Nov 23, 2012 Jan. 07-11, 2013	Test Report No RTS-6012-1211-32 Rev 3	FCC ID: L6ARFA90LW

DASY5 Validation Report for Head TSL

Date/Time: 05.01.2011 15:51:17

Test Laboratory: SPEAG, Zurich, Switzerland

DUT: Dipole 750 MHz; Type: D750V3; Serial: D750V3 - SN:1021

Communication System: CW; Frequency: 750 MHz; Duty Cycle: 1:1

Medium: HSL750

Medium parameters used: $f = 750 \text{ MHz}$; $\sigma = 0.91 \text{ mho/m}$; $\epsilon_r = 42.3$; $\rho = 1000 \text{ kg/m}^3$

Phantom section: Flat Section

Measurement Standard: DASY5 (IEEE/IEC/ANSI C63.19-2007)

DASY5 Configuration:

- Probe: ES3DV3 - SN3205; ConvF(6.37, 6.37, 6.37); Calibrated: 30.04.2010
- Sensor-Surface: 3mm (Mechanical Surface Detection)
- Electronics: DAE4 Sn601; Calibrated: 10.06.2010
- Phantom: Flat Phantom 4.9L; Type: QD000P49AA; Serial: 1001
- Measurement SW: DASY52, V52.6 Build (401)
- Postprocessing SW: SEMCAD X, V14.4.2 Build (2595)

Pin=250mW; dip=15mm; dist=3.0mm/Zoom Scan (7x7x7)/Cube 0: Measurement grid:


$dx=5\text{mm}$, $dy=5\text{mm}$, $dz=5\text{mm}$

Reference Value = 53.5 V/m; Power Drift = -0.00432 dB


Peak SAR (extrapolated) = 3.24 W/kg


SAR(1 g) = 2.12 mW/g; SAR(10 g) = 1.38 mW/g

Maximum value of SAR (measured) = 2.48 mW/g





0 dB = 2.48mW/g


	Document Appendix D for the BlackBerry® Smartphone Model RFA91LW SAR Report			Page 54(114)
Author Data Andrew Becker	Dates of Test Aug 21 – Nov 23, 2012 Jan. 07-11, 2013	Test Report No RTS-6012-1211-32 Rev 3	FCC ID: L6ARFA90LW	IC ID 2503A-RFA90LW


	Document Appendix D for the BlackBerry® Smartphone Model RFA91LW SAR Report			Page 55(114)
	Author Data Andrew Becker	Dates of Test Aug 21 – Nov 23, 2012 Jan. 07-11, 2013	Test Report No RTS-6012-1211-32 Rev 3	FCC ID: L6ARFA90LW

Impedance Measurement Plot for Head TSL



	Document Appendix D for the BlackBerry® Smartphone Model RFA91LW SAR Report			Page 56(114)
Author Data Andrew Becker	Dates of Test Aug 21 – Nov 23, 2012 Jan. 07-11, 2013	Test Report No RTS-6012-1211-32 Rev 3	FCC ID: L6ARFA90LW	IC ID 2503A-RFA90LW

	Document Appendix D for the BlackBerry® Smartphone Model RFA91LW SAR Report			Page 57(114)
Author Data Andrew Becker	Dates of Test Aug 21 – Nov 23, 2012 Jan. 07-11, 2013	Test Report No RTS-6012-1211-32 Rev 3	FCC ID: L6ARFA90LW	IC ID 2503A-RFA90LW

	Document Appendix D for the BlackBerry® Smartphone Model RFA91LW SAR Report			Page 58(114)
	Author Data Andrew Becker	Dates of Test Aug 21 – Nov 23, 2012 Jan. 07-11, 2013	Test Report No RTS-6012-1211-32 Rev 3	FCC ID: L6ARFA90LW

**Calibration Laboratory of
Schmid & Partner
Engineering AG**
 Zeughausstrasse 43, 8004 Zurich, Switzerland



S Schweizerischer Kalibrierdienst
C Service suisse d'étalonnage
S Servizio svizzero di taratura
S Swiss Calibration Service



Accredited by the Swiss Accreditation Service (SAS)
 The Swiss Accreditation Service is one of the signatories to the EA
 Multilateral Agreement for the recognition of calibration certificates

Accreditation No.: **SCS 108**

Client **RTS (RIM Testing Services)**


Certificate No: **D835V2-446_Jan11**

CALIBRATION CERTIFICATE

Object	D835V2 - SN: 446		
Calibration procedure(s)	QA CAL-05.v8 Calibration procedure for dipole validation kits		
Calibration date:	January 21, 2011		
<p>This calibration certificate documents the traceability to national standards, which realize the physical units of measurements (SI). The measurements and the uncertainties with confidence probability are given on the following pages and are part of the certificate.</p> <p>All calibrations have been conducted in the closed laboratory facility: environment temperature (22 ± 3)°C and humidity < 70%.</p> <p>Calibration Equipment used (M&TE critical for calibration)</p>			
Primary Standards	ID #	Cal Date (Certificate No.)	Scheduled Calibration
Power meter EPM-442A	GB37480704	06-Oct-10 (No. 217-01266)	Oct-11
Power sensor HP 8481A	US37292783	06-Oct-10 (No. 217-01266)	Oct-11
Reference 20 dB Attenuator	SN: 5086 (20g)	30-Mar-10 (No. 217-01158)	Mar-11
Type-N mismatch combination	SN: 5047.2 / 06327	30-Mar-10 (No. 217-01162)	Mar-11
Reference Probe ES3DV3	SN: 3205	30-Apr-10 (No. ES3-3205_Apr10)	Apr-11
DAE4	SN: 601	10-Jun-10 (No. DAE4-601_Jun10)	Jun-11
Secondary Standards	ID #	Check Date (in house)	Scheduled Check
Power sensor HP 8481A	MY41092317	18-Oct-02 (in house check Oct-09)	In house check: Oct-11
RF generator R&S SMT-06	100005	4-Aug-99 (in house check Oct-09)	In house check: Oct-11
Network Analyzer HP 8753E	US37390585 S4206	18-Oct-01 (in house check Oct-10)	In house check: Oct-11
Calibrated by:	Name Dimce Iliev	Function Laboratory Technician	Signature 
Approved by:	Name Katja Pokovic	Function Technical Manager	Signature 
			Issued: January 21, 2011
This calibration certificate shall not be reproduced except in full without written approval of the laboratory.			

Certificate No: D835V2-446_Jan11

Page 1 of 6

	Document Appendix D for the BlackBerry® Smartphone Model RFA91LW SAR Report			Page 59(114)
	Author Data Andrew Becker	Dates of Test Aug 21 – Nov 23, 2012 Jan. 07-11, 2013	Test Report No RTS-6012-1211-32 Rev 3	FCC ID: L6ARFA90LW

Calibration Laboratory of Schmid & Partner Engineering AG
 Zeughausstrasse 43, 8004 Zurich, Switzerland



S Schweizerischer Kalibrierdienst
C Service suisse d'étalonnage
S Servizio svizzero di taratura
S Swiss Calibration Service

Accredited by the Swiss Accreditation Service (SAS)
 The Swiss Accreditation Service is one of the signatories to the EA Multilateral Agreement for the recognition of calibration certificates

Accreditation No.: **SCS 108**

Glossary:

TSL tissue simulating liquid
 ConvF sensitivity in TSL / NORM x,y,z
 N/A not applicable or not measured

Calibration is Performed According to the Following Standards:


- IEEE Std 1528-2003, "IEEE Recommended Practice for Determining the Peak Spatial-Averaged Specific Absorption Rate (SAR) in the Human Head from Wireless Communications Devices: Measurement Techniques", December 2003
- IEC 62209-1, "Procedure to measure the Specific Absorption Rate (SAR) for hand-held devices used in close proximity to the ear (frequency range of 300 MHz to 3 GHz)", February 2005
- Federal Communications Commission Office of Engineering & Technology (FCC OET), "Evaluating Compliance with FCC Guidelines for Human Exposure to Radiofrequency Electromagnetic Fields; Additional Information for Evaluating Compliance of Mobile and Portable Devices with FCC Limits for Human Exposure to Radiofrequency Emissions", Supplement C (Edition 01-01) to Bulletin 65

Additional Documentation:

- DASY4/5 System Handbook

Methods Applied and Interpretation of Parameters:

- Measurement Conditions:** Further details are available from the Validation Report at the end of the certificate. All figures stated in the certificate are valid at the frequency indicated.
- Antenna Parameters with TSL:** The dipole is mounted with the spacer to position its feed point exactly below the center marking of the flat phantom section, with the arms oriented parallel to the body axis.
- Feed Point Impedance and Return Loss:** These parameters are measured with the dipole positioned under the liquid filled phantom. The impedance stated is transformed from the measurement at the SMA connector to the feed point. The Return Loss ensures low reflected power. No uncertainty required.
- Electrical Delay:** One-way delay between the SMA connector and the antenna feed point. No uncertainty required.
- SAR measured:** SAR measured at the stated antenna input power.
- SAR normalized:** SAR as measured, normalized to an input power of 1 W at the antenna connector.
- SAR for nominal TSL parameters:** The measured TSL parameters are used to calculate the nominal SAR result.

	Document Appendix D for the BlackBerry® Smartphone Model RFA91LW SAR Report			Page 60(114)
	Author Data Andrew Becker	Dates of Test Aug 21 – Nov 23, 2012 Jan. 07-11, 2013	Test Report No RTS-6012-1211-32 Rev 3	FCC ID: L6ARFA90LW

Measurement Conditions

DASY system configuration, as far as not given on page 1.

DASY Version	DASY5	V52.6
Extrapolation	Advanced Extrapolation	
Phantom	Modular Flat Phantom V4.9	
Distance Dipole Center - TSL	15 mm	with Spacer
Zoom Scan Resolution	dx, dy, dz = 5 mm	
Frequency	835 MHz ± 1 MHz	

Head TSL parameters


The following parameters and calculations were applied.

	Temperature	Permittivity	Conductivity
Nominal Head TSL parameters	22.0 °C	41.5	0.90 mho/m
Measured Head TSL parameters	(22.0 ± 0.2) °C	41.3 ± 6 %	0.89 mho/m ± 6 %
Head TSL temperature during test	(21.8 ± 0.2) °C	----	----

SAR result with Head TSL

SAR averaged over 1 cm³ (1 g) of Head TSL	Condition	
SAR measured	250 mW input power	2.39 mW / g
SAR normalized	normalized to 1W	9.56 mW / g
SAR for nominal Head TSL parameters	normalized to 1W	9.63 mW / g ± 17.0 % (k=2)

SAR averaged over 10 cm³ (10 g) of Head TSL	condition	
SAR measured	250 mW input power	1.56 mW / g
SAR normalized	normalized to 1W	6.24 mW / g
SAR for nominal Head TSL parameters	normalized to 1W	6.27 mW / g ± 16.5 % (k=2)

	Document Appendix D for the BlackBerry® Smartphone Model RFA91LW SAR Report			Page 61(114)
	Author Data Andrew Becker	Dates of Test Aug 21 – Nov 23, 2012 Jan. 07-11, 2013	Test Report No RTS-6012-1211-32 Rev 3	FCC ID: L6ARFA90LW

Appendix

Antenna Parameters with Head TSL

Impedance, transformed to feed point	49.6 Ω - 7.7 $j\Omega$
Return Loss	- 22.2 dB

General Antenna Parameters and Design

Electrical Delay (one direction)	1.386 ns
----------------------------------	----------


After long term use with 100W radiated power, only a slight warming of the dipole near the feedpoint can be measured.

The dipole is made of standard semirigid coaxial cable. The center conductor of the feeding line is directly connected to the second arm of the dipole. The antenna is therefore short-circuited for DC-signals.

No excessive force must be applied to the dipole arms, because they might bend or the soldered connections near the feedpoint may be damaged.

Additional EUT Data

Manufactured by	SPEAG
Manufactured on	October 24, 2001

	Document Appendix D for the BlackBerry® Smartphone Model RFA91LW SAR Report			Page 62(114)
	Author Data Andrew Becker	Dates of Test Aug 21 – Nov 23, 2012 Jan. 07-11, 2013	Test Report No RTS-6012-1211-32 Rev 3	FCC ID: L6ARFA90LW

DASY5 Validation Report for Head TSL

Date/Time: 21.01.2011 10:18:05

Test Laboratory: SPEAG, Zurich, Switzerland

DUT: Dipole 835 MHz; Type: D835V2; Serial: D835V2 - SN:446

Communication System: CW; Frequency: 835 MHz; Duty Cycle: 1:1
 Medium: HSL900

Medium parameters used: $f = 835 \text{ MHz}$; $\sigma = 0.89 \text{ mho/m}$; $\epsilon_r = 41.2$; $\rho = 1000 \text{ kg/m}^3$

Phantom section: Flat Section

Measurement Standard: DASY5 (IEEE/IEC/ANSI C63.19-2007)

DASY5 Configuration:

- Probe: ES3DV3 - SN3205; ConvF(6.03, 6.03, 6.03); Calibrated: 30.04.2010
- Sensor-Surface: 3mm (Mechanical Surface Detection)
- Electronics: DAE4 Sn601; Calibrated: 10.06.2010
- Phantom: Flat Phantom 4.9L; Type: QD000P49AA; Serial: 1001
- Measurement SW: DASY52, V52.6.1 Build (408)
- Postprocessing SW: SEMCAD X, V14.4.2 Build (2595)

Pin=250 mW /d=15mm, dist=3.0mm (ES-Probe)/Zoom Scan (7x7x7) /Cube 0: Measurement


grid: dx=5mm, dy=5mm, dz=5mm


Reference Value = 57.426 V/m; Power Drift = 0.04 dB

Peak SAR (extrapolated) = 3.600 W/kg


SAR(1 g) = 2.39 mW/g; SAR(10 g) = 1.56 mW/g


Maximum value of SAR (measured) = 2.790 mW/g




	Document Appendix D for the BlackBerry® Smartphone Model RFA91LW SAR Report			Page 63(114)
	Author Data Andrew Becker	Dates of Test Aug 21 – Nov 23, 2012 Jan. 07-11, 2013	Test Report No RTS-6012-1211-32 Rev 3	FCC ID: L6ARFA90LW

Impedance Measurement Plot for Head TSL



	Document Appendix D for the BlackBerry® Smartphone Model RFA91LW SAR Report			Page 64(114)
Author Data Andrew Becker	Dates of Test Aug 21 – Nov 23, 2012 Jan. 07-11, 2013	Test Report No RTS-6012-1211-32 Rev 3	FCC ID: L6ARFA90LW	IC ID 2503A-RFA90LW

	Document Appendix D for the BlackBerry® Smartphone Model RFA91LW SAR Report			Page 65(114)
	Author Data Andrew Becker	Dates of Test Aug 21 – Nov 23, 2012 Jan. 07-11, 2013	Test Report No RTS-6012-1211-32 Rev 3	FCC ID: L6ARFA90LW

**Calibration Laboratory of
Schmid & Partner
Engineering AG**
 Zeughausstrasse 43, 8004 Zurich, Switzerland





S Schweizerischer Kalibrierdienst
S Service suisse d'étalonnage
C Servizio svizzero di tarature
S Swiss Calibration Service

Accredited by the Swiss Accreditation Service (SAS)
 The Swiss Accreditation Service is one of the signatories to the EA
 Multilateral Agreement for the recognition of calibration certificates

Accreditation No.: **SCS 108**


Client **RTS (RIM Testing Services)**


Certificate No: **D835V2-4d043_Apr11**

CALIBRATION CERTIFICATE			
Object	D835V2 - SN: 4d043		
Calibration procedure(s)	QA CAL-05.v8 Calibration procedure for dipole validation kits		
Calibration date:	April 07, 2011		
<p>This calibration certificate documents the traceability to national standards, which realize the physical units of measurements (SI). The measurements and the uncertainties with confidence probability are given on the following pages and are part of the certificate.</p> <p>All calibrations have been conducted in the closed laboratory facility, environment temperature (22 ± 3)°C and humidity < 70%</p> <p>Calibration Equipment used (M&TE critical for calibration)</p>			
Primary Standards	ID #	Cal Date (Certificate No.)	Scheduled Calibration
Power meter EPM-442A	GB37480704	06-Oct-10 (No. 217-01266)	Oct-11
Power sensor HP 8481A	US37292789	06-Oct-10 (No. 217-01266)	Oct-11
Reference 20 dB Attenuator	SN: 5086 (20g)	29-Mar-11 (No. 217-01368)	Apr-12
Type-N mismatch combination	SN: 5047.2 / 06327	29-Mar-11 (No. 217-01371)	Apr-12
Reference Probe ES3DV3	SN: 3205	30-Apr-10 (No. ES3-3205_Apr10)	Apr-11
DAE4	SN: 601	10-Jun-10 (No. DAE4-601_Jun10)	Jun-11
Secondary Standards	ID #	Check Date (in house)	Scheduled Check
Power sensor HP 8481A	MY41092317	18-Oct-02 (in house check Oct-09)	In house check: Oct-11
RF generator R&S SMT-06	100005	4-Aug-99 (in house check Oct-09)	In house check: Oct-11
Network Analyzer HP 8753E	US37390585 S4206	18-Oct-01 (in house check Oct-10)	In house check: Oct-11
Calibrated by:	Name Jeton Kasiraj	Function Laboratory Technician	Signature  
Approved by:	Name Katja Pokovic	Function Technical Manager	
Issued: April 7, 2011 This calibration certificate shall not be reproduced except in full without written approval of the laboratory.			

Certificate No: **D835V2-4d043_Apr11**

Page 1 of 6

	Document Appendix D for the BlackBerry® Smartphone Model RFA91LW SAR Report			Page 66(114)
Author Data Andrew Becker	Dates of Test Aug 21 – Nov 23, 2012 Jan. 07-11, 2013	Test Report No RTS-6012-1211-32 Rev 3	FCC ID: L6ARFA90LW	IC ID 2503A-RFA90LW

	Document Appendix D for the BlackBerry® Smartphone Model RFA91LW SAR Report			Page 67(114)
	Author Data Andrew Becker	Dates of Test Aug 21 – Nov 23, 2012 Jan. 07-11, 2013	Test Report No RTS-6012-1211-32 Rev 3	FCC ID: L6ARFA90LW

**Calibration Laboratory of
Schmid & Partner
Engineering AG**
Zeughausstrasse 43, 8004 Zurich, Switzerland



S Schweizerischer Kalibrierdienst
S Service suisse d'étalonnage
C Servizio svizzero di taratura
S Swiss Calibration Service

Accredited by the Swiss Accreditation Service (SAS)
The Swiss Accreditation Service is one of the signatories to the EA
Multilateral Agreement for the recognition of calibration certificates

Accreditation No.: **SCS 108**

Glossary:

TSL tissue simulating liquid
ConvF sensitivity in TSL / NORM x,y,z
N/A not applicable or not measured

Calibration is Performed According to the Following Standards:


- IEEE Std 1528-2003, "IEEE Recommended Practice for Determining the Peak Spatial-Averaged Specific Absorption Rate (SAR) in the Human Head from Wireless Communications Devices: Measurement Techniques", December 2003
- IEC 62209-1, "Procedure to measure the Specific Absorption Rate (SAR) for hand-held devices used in close proximity to the ear (frequency range of 300 MHz to 3 GHz)", February 2005
- Federal Communications Commission Office of Engineering & Technology (FCC OET), "Evaluating Compliance with FCC Guidelines for Human Exposure to Radiofrequency Electromagnetic Fields; Additional Information for Evaluating Compliance of Mobile and Portable Devices with FCC Limits for Human Exposure to Radiofrequency Emissions", Supplement C (Edition 01-01) to Bulletin 65


Additional Documentation:

- DASY4/5 System Handbook

Methods Applied and Interpretation of Parameters:

- Measurement Conditions:** Further details are available from the Validation Report at the end of the certificate. All figures stated in the certificate are valid at the frequency indicated.
- Antenna Parameters with TSL:** The dipole is mounted with the spacer to position its feed point exactly below the center marking of the flat phantom section, with the arms oriented parallel to the body axis.
- Feed Point Impedance and Return Loss:** These parameters are measured with the dipole positioned under the liquid filled phantom. The impedance stated is transformed from the measurement at the SMA connector to the feed point. The Return Loss ensures low reflected power. No uncertainty required.
- Electrical Delay:** One-way delay between the SMA connector and the antenna feed point. No uncertainty required.
- SAR measured:** SAR measured at the stated antenna input power.
- SAR normalized:** SAR as measured, normalized to an input power of 1 W at the antenna connector.
- SAR for nominal TSL parameters:** The measured TSL parameters are used to calculate the nominal SAR result.

	Document Appendix D for the BlackBerry® Smartphone Model RFA91LW SAR Report			Page 68(114)
Author Data Andrew Becker	Dates of Test Aug 21 – Nov 23, 2012 Jan. 07-11, 2013	Test Report No RTS-6012-1211-32 Rev 3	FCC ID: L6ARFA90LW	IC ID 2503A-RFA90LW

	Document Appendix D for the BlackBerry® Smartphone Model RFA91LW SAR Report			Page 69(114)
	Author Data Andrew Becker	Dates of Test Aug 21 – Nov 23, 2012 Jan. 07-11, 2013	Test Report No RTS-6012-1211-32 Rev 3	FCC ID: L6ARFA90LW

Measurement Conditions

DASY system configuration, as far as not given on page 1.

DASY Version	DASY5	V52.6.2
Extrapolation	Advanced Extrapolation	
Phantom	Modular Flat Phantom V4.9	
Distance Dipole Center - TSL	15 mm	with Spacer
Zoom Scan Resolution	dx, dy, dz = 5 mm	
Frequency	835 MHz ± 1 MHz	

Head TSL parameters


The following parameters and calculations were applied.


	Temperature	Permittivity	Conductivity
Nominal Head TSL parameters	22.0 °C	41.5	0.90 mho/m
Measured Head TSL parameters	(22.0 ± 0.2) °C	40.6 ± 6 %	0.88 mho/m ± 6 %
Head TSL temperature during test	(22.0 ± 0.2) °C	---	---

SAR result with Head TSL

SAR averaged over 1 cm³ (1 g) of Head TSL	Condition	
SAR measured	250 mW input power	2.33 mW / g
SAR normalized	normalized to 1W	9.32 mW / g
SAR for nominal Head TSL parameters	normalized to 1W	9.43 mW / g ± 17.0 % (k=2)

SAR averaged over 10 cm³ (10 g) of Head TSL	condition	
SAR measured	250 mW input power	1.52 mW / g
SAR normalized	normalized to 1W	6.08 mW / g
SAR for nominal Head TSL parameters	normalized to 1W	6.14 mW / g ± 16.5 % (k=2)

	Document Appendix D for the BlackBerry® Smartphone Model RFA91LW SAR Report			Page 70(114)
Author Data Andrew Becker	Dates of Test Aug 21 – Nov 23, 2012 Jan. 07-11, 2013	Test Report No RTS-6012-1211-32 Rev 3	FCC ID: L6ARFA90LW	IC ID 2503A-RFA90LW

	Document Appendix D for the BlackBerry® Smartphone Model RFA91LW SAR Report			Page 71(114)
	Author Data Andrew Becker	Dates of Test Aug 21 – Nov 23, 2012 Jan. 07-11, 2013	Test Report No RTS-6012-1211-32 Rev 3	FCC ID: L6ARFA90LW

Appendix

Antenna Parameters with Head TSL

Impedance, transformed to feed point	52.9 Ω - 3.4 j Ω
Return Loss	- 27.2 dB

General Antenna Parameters and Design

Electrical Delay (one direction)	1.391 ns
----------------------------------	----------

After long term use with 100W radiated power, only a slight warming of the dipole near the feedpoint can be measured.

The dipole is made of standard semirigid coaxial cable. The center conductor of the feeding line is directly connected to the second arm of the dipole. The antenna is therefore short-circuited for DC-signals.


No excessive force must be applied to the dipole arms, because they might bend or the soldered connections near the feedpoint may be damaged.


Design Modification by End User

The dipole has been modified with Teflon Rings (TR) placed within identified markings close to the end of each dipole arm. Calibration has been performed with TR attached to the dipole.

Additional EUT Data

Manufactured by	SPEAG
Manufactured on	April 07, 2006

	Document Appendix D for the BlackBerry® Smartphone Model RFA91LW SAR Report			Page 72(114)
Author Data Andrew Becker	Dates of Test Aug 21 – Nov 23, 2012 Jan. 07-11, 2013	Test Report No RTS-6012-1211-32 Rev 3	FCC ID: L6ARFA90LW	IC ID 2503A-RFA90LW

	Document Appendix D for the BlackBerry® Smartphone Model RFA91LW SAR Report			Page 73(114)
	Author Data Andrew Becker	Dates of Test Aug 21 – Nov 23, 2012 Jan. 07-11, 2013	Test Report No RTS-6012-1211-32 Rev 3	FCC ID: L6ARFA90LW

DASY5 Validation Report for Head TSL

Date/Time: 07.04.2011 09:28:21

Test Laboratory: SPEAG, Zurich, Switzerland

DUT: Dipole 835 MHz; Type: D835V2; Serial: D835V2 - SN:4d043

Communication System: CW; Frequency: 835 MHz; Duty Cycle: 1:1

Medium: HSL900

Medium parameters used: $f = 835 \text{ MHz}$; $\sigma = 0.88 \text{ mho/m}$; $\epsilon_r = 40.6$; $\rho = 1000 \text{ kg/m}^3$

Phantom section: Flat Section

Measurement Standard: DASY5 (IEEE/IEC/ANSI C63.19-2007)

DASY5 Configuration:

- Probe: ES3DV3 - SN3205; ConvF(6.03, 6.03, 6.03); Calibrated: 30.04.2010
- Sensor-Surface: 3mm (Mechanical Surface Detection)
- Electronics: DAE4 Sn601; Calibrated: 10.06.2010
- Phantom: Flat Phantom 4.9L; Type: QD000P49AA; Serial: 1001
- Measurement SW: DASY52, V52.6.2 Build (424)
- Postprocessing SW: SEMCAD X, V14.4.4 Build (2829)

Pin=250 mW /d=15mm/Cube 0:


Measurement grid: $dx=5\text{mm}$, $dy=5\text{mm}$, $dz=5\text{mm}$


Reference Value = 57.201 V/m; Power Drift = 0.07 dB


Peak SAR (extrapolated) = 3.504 W/kg

SAR(1 g) = 2.33 mW/g; SAR(10 g) = 1.52 mW/g


Maximum value of SAR (measured) = 2.730 mW/g





	Document Appendix D for the BlackBerry® Smartphone Model RFA91LW SAR Report			Page 74(114)
Author Data Andrew Becker	Dates of Test Aug 21 – Nov 23, 2012 Jan. 07-11, 2013	Test Report No RTS-6012-1211-32 Rev 3	FCC ID: L6ARFA90LW	IC ID 2503A-RFA90LW


	Document Appendix D for the BlackBerry® Smartphone Model RFA91LW SAR Report			Page 75(114)
	Author Data Andrew Becker	Dates of Test Aug 21 – Nov 23, 2012 Jan. 07-11, 2013	Test Report No RTS-6012-1211-32 Rev 3	FCC ID: L6ARFA90LW

Impedance Measurement Plot for Head TSL



	Document Appendix D for the BlackBerry® Smartphone Model RFA91LW SAR Report			Page 76(114)
Author Data Andrew Becker	Dates of Test Aug 21 – Nov 23, 2012 Jan. 07-11, 2013	Test Report No RTS-6012-1211-32 Rev 3	FCC ID: L6ARFA90LW	IC ID 2503A-RFA90LW

	Document Appendix D for the BlackBerry® Smartphone Model RFA91LW SAR Report			Page 77(114)
Author Data Andrew Becker	Dates of Test Aug 21 – Nov 23, 2012 Jan. 07-11, 2013	Test Report No RTS-6012-1211-32 Rev 3	FCC ID: L6ARFA90LW	IC ID 2503A-RFA90LW

	Document Appendix D for the BlackBerry® Smartphone Model RFA91LW SAR Report			Page 78(114)
	Author Data Andrew Becker	Dates of Test Aug 21 – Nov 23, 2012 Jan. 07-11, 2013	Test Report No RTS-6012-1211-32 Rev 3	FCC ID: L6ARFA90LW

**Calibration Laboratory of
Schmid & Partner
Engineering AG**
 Zeughausstrasse 43, 8004 Zurich, Switzerland



S Schweizerischer Kalibrierdienst
S Service suisse d'étalonnage
S Servizio svizzero di taratura
S Swiss Calibration Service

Accredited by the Swiss Accreditation Service (SAS)
 The Swiss Accreditation Service is one of the signatories to the EA
 Multilateral Agreement for the recognition of calibration certificates

Accreditation No.: **SCS 108**

Client **RTS (RIM Testing Services)**

Certificate No: **D1900V2-545_Jan11**

CALIBRATION CERTIFICATE

Object: **D1900V2 - SN: 545**
 Calibration procedure(s): **QA CAL-05.v8
Calibration procedure for dipole validation kits**
 Calibration date: **January 13, 2011**

This calibration certificate documents the traceability to national standards, which realize the physical units of measurements (SI).
 The measurements and the uncertainties with confidence probability are given on the following pages and are part of the certificate.

All calibrations have been conducted in the closed laboratory facility: environment temperature (22 ± 3)°C and humidity < 70%.

Calibration Equipment used (M&TE critical for calibration)


Primary Standards	ID #	Cal Date (Certificate No.)	Scheduled Calibration
Power meter EPM-442A	GB37480704	06-Oct-10 (No. 217-01266)	Oct-11
Power sensor HP B481A	US37292783	06-Oct-10 (No. 217-01266)	Oct-11
Reference 20 dB Attenuator	SN: 5086 (20g)	30-Mar-10 (No. 217-01158)	Mar-11
Type-N mismatch combination	SN: 5047.2 / 06327	30-Mar-10 (No. 217-01162)	Mar-11
Reference Probe ES3DV3	SN: 3205	30-Apr-10 (No. ES3-3205_Apr10)	Apr-11
DAE4	SN: 601	10-Jun-10 (No. DAE4-601_Jun10)	Jun-11

Secondary Standards	ID #	Check Date (in house)	Scheduled Check
Power sensor HP B481A	MY41092317	18-Oct-02 (in house check Oct-09)	In house check: Oct-11
RF generator R&S SMT-06	100005	4-Aug-99 (in house check Oct-09)	In house check: Oct-11
Network Analyzer HP 8753E	US37390585 S4206	18-Oct-01 (in house check Oct-10)	In house check: Oct-11

Calibrated by: **Dimce Iliev** Laboratory Technician *[Signature]*
 Approved by: **Katja Pokovic** Technical Manager *[Signature]*

Issued: January 14, 2011

This calibration certificate shall not be reproduced except in full without written approval of the laboratory.

	Document Appendix D for the BlackBerry® Smartphone Model RFA91LW SAR Report			Page 79(114)
	Author Data Andrew Becker	Dates of Test Aug 21 – Nov 23, 2012 Jan. 07-11, 2013	Test Report No RTS-6012-1211-32 Rev 3	FCC ID: L6ARFA90LW

**Calibration Laboratory of
Schmid & Partner
Engineering AG**
 Zeughausstrasse 43, 8004 Zurich, Switzerland



S Schweizerischer Kalibrierdienst
C Service suisse d'étalonnage
S Servizio svizzero di taratura
S Swiss Calibration Service

Accredited by the Swiss Accreditation Service (SAS)
 The Swiss Accreditation Service is one of the signatories to the EA
 Multilateral Agreement for the recognition of calibration certificates

Accreditation No.: **SCS 108**

Glossary:

TSL tissue simulating liquid
 ConvF sensitivity in TSL / NORM x,y,z
 N/A not applicable or not measured

Calibration is Performed According to the Following Standards:


- a) IEEE Std 1528-2003, "IEEE Recommended Practice for Determining the Peak Spatial-Averaged Specific Absorption Rate (SAR) in the Human Head from Wireless Communications Devices: Measurement Techniques", December 2003
- b) IEC 62209-1, "Procedure to measure the Specific Absorption Rate (SAR) for hand-held devices used in close proximity to the ear (frequency range of 300 MHz to 3 GHz)", February 2005
- c) Federal Communications Commission Office of Engineering & Technology (FCC OET), "Evaluating Compliance with FCC Guidelines for Human Exposure to Radiofrequency Electromagnetic Fields; Additional Information for Evaluating Compliance of Mobile and Portable Devices with FCC Limits for Human Exposure to Radiofrequency Emissions", Supplement C (Edition 01-01) to Bulletin 65

Additional Documentation:

- d) DASY4/5 System Handbook

Methods Applied and Interpretation of Parameters:

- *Measurement Conditions:* Further details are available from the Validation Report at the end of the certificate. All figures stated in the certificate are valid at the frequency indicated.
- *Antenna Parameters with TSL:* The dipole is mounted with the spacer to position its feed point exactly below the center marking of the flat phantom section, with the arms oriented parallel to the body axis.
- *Feed Point Impedance and Return Loss:* These parameters are measured with the dipole positioned under the liquid filled phantom. The impedance stated is transformed from the measurement at the SMA connector to the feed point. The Return Loss ensures low reflected power. No uncertainty required.
- *Electrical Delay:* One-way delay between the SMA connector and the antenna feed point. No uncertainty required.
- *SAR measured:* SAR measured at the stated antenna input power.
- *SAR normalized:* SAR as measured, normalized to an input power of 1 W at the antenna connector.
- *SAR for nominal TSL parameters:* The measured TSL parameters are used to calculate the nominal SAR result.

	Document Appendix D for the BlackBerry® Smartphone Model RFA91LW SAR Report			Page 80(114)
	Author Data Andrew Becker	Dates of Test Aug 21 – Nov 23, 2012 Jan. 07-11, 2013	Test Report No RTS-6012-1211-32 Rev 3	FCC ID: L6ARFA90LW

Measurement Conditions

DASY system configuration, as far as not given on page 1.

DASY Version	DASY5	V52.6
Extrapolation	Advanced Extrapolation	
Phantom	Modular Flat Phantom V5.0	
Distance Dipole Center - TSL	10 mm	with Spacer
Zoom Scan Resolution	dx, dy, dz = 5 mm	
Frequency	1900 MHz ± 1 MHz	

Head TSL parameters


The following parameters and calculations were applied.

	Temperature	Permittivity	Conductivity
Nominal Head TSL parameters	22.0 °C	40.0	1.40 mho/m
Measured Head TSL parameters	(22.0 ± 0.2) °C	38.5 ± 6 %	1.43 mho/m ± 6 %
Head TSL temperature during test	(21.2 ± 0.2) °C	----	----

SAR result with Head TSL

SAR averaged over 1 cm³ (1 g) of Head TSL	Condition	
SAR measured	250 mW input power	10.2 mW / g
SAR normalized	normalized to 1W	40.8 mW / g
SAR for nominal Head TSL parameters	normalized to 1W	40.0 mW / g ± 17.0 % (k=2)

SAR averaged over 10 cm³ (10 g) of Head TSL	condition	
SAR measured	250 mW input power	5.26 mW / g
SAR normalized	normalized to 1W	21.0 mW / g
SAR for nominal Head TSL parameters	normalized to 1W	20.8 mW / g ± 16.5 % (k=2)

	Document Appendix D for the BlackBerry® Smartphone Model RFA91LW SAR Report			Page 81(114)
	Author Data Andrew Becker	Dates of Test Aug 21 – Nov 23, 2012 Jan. 07-11, 2013	Test Report No RTS-6012-1211-32 Rev 3	FCC ID: L6ARFA90LW

Appendix

Antenna Parameters with Head TSL

Impedance, transformed to feed point	50.8 Ω + 1.8 $j\Omega$
Return Loss	- 34.4 dB

General Antenna Parameters and Design

Electrical Delay (one direction)	1.199 ns
----------------------------------	----------


After long term use with 100W radiated power, only a slight warming of the dipole near the feedpoint can be measured.

The dipole is made of standard semirigid coaxial cable. The center conductor of the feeding line is directly connected to the second arm of the dipole. The antenna is therefore short-circuited for DC-signals.

No excessive force must be applied to the dipole arms, because they might bend or the soldered connections near the feedpoint may be damaged.

Additional EUT Data

Manufactured by	SPEAG
Manufactured on	November 15, 2001

	Document Appendix D for the BlackBerry® Smartphone Model RFA91LW SAR Report			Page 82(114)
	Author Data Andrew Becker	Dates of Test Aug 21 – Nov 23, 2012 Jan. 07-11, 2013	Test Report No RTS-6012-1211-32 Rev 3	FCC ID: L6ARFA90LW

DASY5 Validation Report for Head TSL

Date/Time: 13.01.2011 14:52:49

Test Laboratory: SPEAG, Zurich, Switzerland


DUT: Dipole 1900 MHz; Type: D1900V2; Serial: D1900V2 - SN:545


Communication System: CW; Frequency: 1900 MHz; Duty Cycle: 1:1
 Medium: HSL U12 BB
 Medium parameters used: $f = 1900 \text{ MHz}$; $\sigma = 1.43 \text{ mho/m}$; $\epsilon_r = 38.6$; $\rho = 1000 \text{ kg/m}^3$
 Phantom section: Flat Section
 Measurement Standard: DASY5 (IEEE/IEC/ANSI C63.19-2007)

DASY5 Configuration:


- Probe: ES3DV3 - SN3205; ConvF(5.09, 5.09, 5.09); Calibrated: 30.04.2010
- Sensor-Surface: 3mm (Mechanical Surface Detection)
- Electronics: DAE4 Sn601; Calibrated: 10.06.2010
- Phantom: Flat Phantom 5.0 (front); Type: QD000P50AA; Serial: 1001
- Measurement SW: DASY52, V52.6.1 Build (408)
- Postprocessing SW: SEMCAD X, V14.4.2 Build (2595)


Pin=250 mW /d=10mm, dist=3.0mm (ES-Probe)/Zoom Scan (7x7x7) /Cube 0: Measurement
 grid: dx=5mm, dy=5mm, dz=5mm
 Reference Value = 98.053 V/m; Power Drift = 0.03 dB
 Peak SAR (extrapolated) = 18.648 W/kg
SAR(1 g) = 10.2 mW/g; SAR(10 g) = 5.26 mW/g
 Maximum value of SAR (measured) = 12.743 mW/g



	Document Appendix D for the BlackBerry® Smartphone Model RFA91LW SAR Report			Page 83(114)
	Author Data Andrew Becker	Dates of Test Aug 21 – Nov 23, 2012 Jan. 07-11, 2013	Test Report No RTS-6012-1211-32 Rev 3	FCC ID: L6ARFA90LW

Impedance Measurement Plot for Head TSL



	Document			Page
	Appendix D for the BlackBerry® Smartphone Model RFA91LW SAR Report			84(114)
Author Data	Dates of Test	Test Report No	FCC ID:	IC ID
Andrew Becker	Aug 21 – Nov 23, 2012 Jan. 07-11, 2013	RTS-6012-1211-32 Rev 3	L6ARFA90LW	2503A-RFA90LW

Calibration Laboratory of Schmid & Partner Engineering AG
 Zeughausstrasse 43, 8004 Zurich, Switzerland



S Schweizerischer Kalibrierdienst
S Service suisse d'étalonnage
C Servizio svizzero di taratura
S Swiss Calibration Service

Accredited by the Swiss Accreditation Service (SAS)
 The Swiss Accreditation Service is one of the signatories to the EA Multilateral Agreement for the recognition of calibration certificates

Accreditation No.: **SCS 108**

Client **RTS (RIM Testing Services)**

Certificate No: **D1900V2-5d075_Apr11**

CALIBRATION CERTIFICATE

Object **D1900V2 - SN: 5d075**
 Calibration procedure(s) **QA CAL-05.v8**
Calibration procedure for dipole validation kits
 Calibration date: **April 5, 2011**



This calibration certificate documents the traceability to national standards, which realize the physical units of measurements (SI). The measurements and the uncertainties with confidence probability are given on the following pages and are part of the certificate.

All calibrations have been conducted in the closed laboratory facility: environment temperature (22 ± 3)°C and humidity < 70%.

Calibration Equipment used (M&TE critical for calibration):


Primary Standards	ID #	Cal Date (Certificate No.)	Scheduled Calibration
Power meter EPM-442A	GB37480704	06-Oct-10 (No. 217-01266)	Oct-11
Power sensor HP B481A	US37292783	06-Oct-10 (No. 217-01266)	Oct-11
Reference 20 dB Attenuator	SN: 5086 (20g)	29-Mar-11 (No. 217-01368)	Apr-12
Type-N mismatch combination	SN: 5047.2 / 06327	29-Mar-11 (No. 217-01371)	Apr-12
Reference Probe ES3DV3	SN: 3205	30-Apr-10 (No. ES3-3205_Apr10)	Apr-11
DAE4	SN: 601	10-Jun-10 (No. DAE4-601_Jun10)	Jun-11


Secondary Standards	ID #	Check Date (in house)	Scheduled Check
Power sensor HP B481A	MY41092317	16-Oct-02 (in house check Oct-09)	In house check: Oct-11
RF generator R&S SMT-06	100005	4-Aug-99 (in house check Oct-09)	In house check: Oct-11
Network Analyzer HP 8753E	US37390585 S4206	18-Oct-01 (in house check Oct-10)	In house check: Oct-11

Calibrated by:	Name Mike Melli	Function Laboratory Technician	Signature 
Approved by:	Name Katja Pokovic	Function Technical Manager	

Issued: April 8, 2011

This calibration certificate shall not be reproduced except in full without written approval of the laboratory.

	Document Appendix D for the BlackBerry® Smartphone Model RFA91LW SAR Report			Page 85(114)
Author Data Andrew Becker	Dates of Test Aug 21 – Nov 23, 2012 Jan. 07-11, 2013	Test Report No RTS-6012-1211-32 Rev 3	FCC ID: L6ARFA90LW	IC ID 2503A-RFA90LW

	Document Appendix D for the BlackBerry® Smartphone Model RFA91LW SAR Report			Page 86(114)
	Author Data Andrew Becker	Dates of Test Aug 21 – Nov 23, 2012 Jan. 07-11, 2013	Test Report No RTS-6012-1211-32 Rev 3	FCC ID: L6ARFA90LW

**Calibration Laboratory of
Schmid & Partner
Engineering AG**
 Zeughausstrasse 43, 8004 Zurich, Switzerland



S Schweizerischer Kalibrierdienst
S Service suisse d'étalonnage
C Servizio svizzero di taratura
S Swiss Calibration Service

Accredited by the Swiss Accreditation Service (SAS)
 The Swiss Accreditation Service is one of the signatories to the EA
 Multilateral Agreement for the recognition of calibration certificates

Accreditation No.: **SCS 108**

Glossary:

TSL tissue simulating liquid
 ConvF sensitivity in TSL / NORM x,y,z
 N/A not applicable or not measured

Calibration is Performed According to the Following Standards:


- a) IEEE Std 1528-2003, "IEEE Recommended Practice for Determining the Peak Spatial-Averaged Specific Absorption Rate (SAR) in the Human Head from Wireless Communications Devices: Measurement Techniques", December 2003
- b) IEC 62209-1, "Procedure to measure the Specific Absorption Rate (SAR) for hand-held devices used in close proximity to the ear (frequency range of 300 MHz to 3 GHz)", February 2005
- c) Federal Communications Commission Office of Engineering & Technology (FCC OET), "Evaluating Compliance with FCC Guidelines for Human Exposure to Radiofrequency Electromagnetic Fields; Additional Information for Evaluating Compliance of Mobile and Portable Devices with FCC Limits for Human Exposure to Radiofrequency Emissions", Supplement C (Edition 01-01) to Bulletin 65


Additional Documentation:

- d) DASY4/5 System Handbook

Methods Applied and Interpretation of Parameters:

- *Measurement Conditions:* Further details are available from the Validation Report at the end of the certificate. All figures stated in the certificate are valid at the frequency indicated.
- *Antenna Parameters with TSL:* The dipole is mounted with the spacer to position its feed point exactly below the center marking of the flat phantom section, with the arms oriented parallel to the body axis.
- *Feed Point Impedance and Return Loss:* These parameters are measured with the dipole positioned under the liquid filled phantom. The impedance stated is transformed from the measurement at the SMA connector to the feed point. The Return Loss ensures low reflected power. No uncertainty required.
- *Electrical Delay:* One-way delay between the SMA connector and the antenna feed point. No uncertainty required.
- *SAR measured:* SAR measured at the stated antenna input power.
- *SAR normalized:* SAR as measured, normalized to an input power of 1 W at the antenna connector.
- *SAR for nominal TSL parameters:* The measured TSL parameters are used to calculate the nominal SAR result.

	Document Appendix D for the BlackBerry® Smartphone Model RFA91LW SAR Report			Page 87(114)
Author Data Andrew Becker	Dates of Test Aug 21 – Nov 23, 2012 Jan. 07-11, 2013	Test Report No RTS-6012-1211-32 Rev 3	FCC ID: L6ARFA90LW	IC ID 2503A-RFA90LW

	Document Appendix D for the BlackBerry® Smartphone Model RFA91LW SAR Report			Page 88(114)
	Author Data Andrew Becker	Dates of Test Aug 21 – Nov 23, 2012 Jan. 07-11, 2013	Test Report No RTS-6012-1211-32 Rev 3	FCC ID: L6ARFA90LW

Measurement Conditions

DASY system configuration, as far as not given on page 1.

DASY Version	DASY5	V52.6.2
Extrapolation	Advanced Extrapolation	
Phantom	Modular Flat Phantom V5.0	
Distance Dipole Center - TSL	10 mm	with Spacer
Zoom Scan Resolution	dx, dy, dz = 5 mm	
Frequency	1900 MHz ± 1 MHz	

Head TSL parameters


The following parameters and calculations were applied.


	Temperature	Permittivity	Conductivity
Nominal Head TSL parameters	22.0 °C	40.0	1.40 mho/m
Measured Head TSL parameters	(22.0 ± 0.2) °C	39.8 ± 6 %	1.41 mho/m ± 6 %
Head TSL temperature during test	(21.3 ± 0.2) °C	----	----

SAR result with Head TSL

SAR averaged over 1 cm ² (1 g) of Head TSL	Condition	
SAR measured	250 mW input power	10.2 mW / g
SAR normalized	normalized to 1W	40.8 mW / g
SAR for nominal Head TSL parameters	normalized to 1W	40.4 mW / g ± 17.0 % (k=2)

SAR averaged over 10 cm ² (10 g) of Head TSL	condition	
SAR measured	250 mW input power	5.29 mW / g
SAR normalized	normalized to 1W	21.2 mW / g
SAR for nominal Head TSL parameters	normalized to 1W	21.0 mW / g ± 16.5 % (k=2)

	Document Appendix D for the BlackBerry® Smartphone Model RFA91LW SAR Report			Page 89(114)
Author Data Andrew Becker	Dates of Test Aug 21 – Nov 23, 2012 Jan. 07-11, 2013	Test Report No RTS-6012-1211-32 Rev 3	FCC ID: L6ARFA90LW	IC ID 2503A-RFA90LW

	Document Appendix D for the BlackBerry® Smartphone Model RFA91LW SAR Report			Page 90(114)
	Author Data Andrew Becker	Dates of Test Aug 21 – Nov 23, 2012 Jan. 07-11, 2013	Test Report No RTS-6012-1211-32 Rev 3	FCC ID: L6ARFA90LW

Appendix

Antenna Parameters with Head TSL

Impedance, transformed to feed point	53.5 Ω + 6.1 j Ω
Return Loss	- 23.3 dB

General Antenna Parameters and Design

Electrical Delay (one direction)	1.197 ns
----------------------------------	----------


After long term use with 100W radiated power, only a slight warming of the dipole near the feedpoint can be measured.


The dipole is made of standard semirigid coaxial cable. The center conductor of the feeding line is directly connected to the second arm of the dipole. The antenna is therefore short-circuited for DC-signals.

No excessive force must be applied to the dipole arms, because they might bend or the soldered connections near the feedpoint may be damaged.

Additional EUT Data

Manufactured by	SPEAG
Manufactured on	January 24, 2006

	Document Appendix D for the BlackBerry® Smartphone Model RFA91LW SAR Report			Page 91(114)
Author Data Andrew Becker	Dates of Test Aug 21 – Nov 23, 2012 Jan. 07-11, 2013	Test Report No RTS-6012-1211-32 Rev 3	FCC ID: L6ARFA90LW	IC ID 2503A-RFA90LW

	Document Appendix D for the BlackBerry® Smartphone Model RFA91LW SAR Report			Page 92(114)
	Author Data Andrew Becker	Dates of Test Aug 21 – Nov 23, 2012 Jan. 07-11, 2013	Test Report No RTS-6012-1211-32 Rev 3	FCC ID: L6ARFA90LW

DASY5 Validation Report for Head TSL

Date/Time: 05.04.2011 12:41:39

Test Laboratory: SPEAG, Zurich, Switzerland

DUT: Dipole 1900 MHz; Type: D1900V2; Serial: D1900V2 - SN:5d075

Communication System: CW; Frequency: 1900 MHz; Duty Cycle: 1:1

Medium: HSL U12 BB

Medium parameters used: $f = 1900$ MHz; $\sigma = 1.41$ mho/m; $\epsilon_r = 39$; $\rho = 1000$ kg/m³

Phantom section: Flat Section

Measurement Standard: DASY5 (IEEE/IEC/ANSI C63.19-2007)

DASY5 Configuration:

- Probe: ES3DV3 - SN3205; ConvF(5.09, 5.09, 5.09); Calibrated: 30.04.2010
- Sensor-Surface: 3mm (Mechanical Surface Detection)
- Electronics: DAE4 Sn601; Calibrated: 10.06.2010
- Phantom: Flat Phantom 5.0 (front); Type: QD000P50AA; Serial: 1001
- Measurement SW: DASY52, V52.6.2 Build (424)
- Postprocessing SW: SEMCAD X, V14.4.4 Build (2829)

Head / d=10mm, Pin=250 mW / Cube 0:


Measurement grid: dx=5mm, dy=5mm, dz=5mm

Reference Value = 97.376 V/m; Power Drift = 0.04 dB


Peak SAR (extrapolated) = 18.796 W/kg

SAR(1 g) = 10.2 mW/g; SAR(10 g) = 5.29 mW/g


Maximum value of SAR (measured) = 12.476 mW/g





0 dB = 12.480mW/g

	Document Appendix D for the BlackBerry® Smartphone Model RFA91LW SAR Report			Page 93(114)
	Author Data Andrew Becker	Dates of Test Aug 21 – Nov 23, 2012 Jan. 07-11, 2013	Test Report No RTS-6012-1211-32 Rev 3	FCC ID: L6ARFA90LW

Impedance Measurement Plot for Head TSL



	Document Appendix D for the BlackBerry® Smartphone Model RFA91LW SAR Report			Page 94(114)
Author Data Andrew Becker	Dates of Test Aug 21 – Nov 23, 2012 Jan. 07-11, 2013	Test Report No RTS-6012-1211-32 Rev 3	FCC ID: L6ARFA90LW	IC ID 2503A-RFA90LW

	Document Appendix D for the BlackBerry® Smartphone Model RFA91LW SAR Report			Page 95(114)
	Author Data Andrew Becker	Dates of Test Aug 21 – Nov 23, 2012 Jan. 07-11, 2013	Test Report No RTS-6012-1211-32 Rev 3	FCC ID: L6ARFA90LW

**Calibration Laboratory of
Schmid & Partner
Engineering AG**
 Zeughausstrasse 43, 8004 Zurich, Switzerland



S Schweizerischer Kalibrierdienst
S Service suisse d'étalonnage
S Servizio svizzero di taratura
S Swiss Calibration Service



Accredited by the Swiss Accreditation Service (SAS)
 The Swiss Accreditation Service is one of the signatories to the EA
 Multilateral Agreement for the recognition of calibration certificates


Accreditation No.: **SCS 108**

Client **RTS (RIM Testing Services)**

Certificate No: **D2450V2-747_Nov11**

CALIBRATION CERTIFICATE

Object	D2450V2 - SN: 747		
Calibration procedure(s)	QA CAL-05.v8 Calibration procedure for dipole validation kits above 700 MHz		
Calibration date:	November 09, 2011		
<p>This calibration certificate documents the traceability to national standards, which realize the physical units of measurements (SI). The measurements and the uncertainties with confidence probability are given on the following pages and are part of the certificate.</p> <p>All calibrations have been conducted in the closed laboratory facility: environment temperature (22 ± 3)°C and humidity < 70%.</p> <p>Calibration Equipment used (M&TE critical for calibration)</p>			
Primary Standards	ID #	Cal Date (Certificate No.)	Scheduled Calibration
Power meter EPM-442A	GB37480704	05-Oct-11 (No. 217-01451)	Oct-12
Power sensor HP 8481A	US37292783	05-Oct-11 (No. 217-01451)	Oct-12
Reference 20 dB Attenuator	SN: 5086 (20g)	29-Mar-11 (No. 217-01368)	Apr-12
Type-N mismatch combination	SN: 5047.2 / 06327	29-Mar-11 (No. 217-01371)	Apr-12
Reference Probe ES3DV3	SN: 3205	29-Apr-11 (No. ES3-3205_Apr11)	Apr-12
DAE4	SN: 601	04-Jul-11 (No. DAE4-601_Jul11)	Jul-12
Secondary Standards	ID #	Check Date (in house)	Scheduled Check
Power sensor HP 8481A	MY41092317	18-Oct-02 (in house check Oct-11)	In house check: Oct-13
RF generator R&S SMT-06	100005	04-Aug-99 (in house check Oct-11)	In house check: Oct-13
Network Analyzer HP 8753E	US37390585 S4206	18-Oct-01 (in house check Oct-11)	In house check: Oct-12
Calibrated by:	Name Jeton Kastrati	Function Laboratory Technician	Signature 
Approved by:	Name Katja Pokovic	Technical Manager	
Issued: November 9, 2011			
This calibration certificate shall not be reproduced except in full without written approval of the laboratory.			

	Document Appendix D for the BlackBerry® Smartphone Model RFA91LW SAR Report			Page 96(114)
	Author Data Andrew Becker	Dates of Test Aug 21 – Nov 23, 2012 Jan. 07-11, 2013	Test Report No RTS-6012-1211-32 Rev 3	FCC ID: L6ARFA90LW

**Calibration Laboratory of
Schmid & Partner
Engineering AG**
 Zeughausstrasse 43, 8004 Zurich, Switzerland



S Schweizerischer Kalibrierdienst
C Service suisse d'étalonnage
S Servizio svizzero di taratura
S Swiss Calibration Service

Accredited by the Swiss Accreditation Service (SAS)
 The Swiss Accreditation Service is one of the signatories to the EA
 Multilateral Agreement for the recognition of calibration certificates

Accreditation No.: **SCS 108**

Glossary:

TSL tissue simulating liquid
 ConvF sensitivity in TSL / NORM x,y,z
 N/A not applicable or not measured

Calibration is Performed According to the Following Standards:


- a) IEEE Std 1528-2003, "IEEE Recommended Practice for Determining the Peak Spatial-Averaged Specific Absorption Rate (SAR) in the Human Head from Wireless Communications Devices: Measurement Techniques", December 2003
- b) IEC 62209-1, "Procedure to measure the Specific Absorption Rate (SAR) for hand-held devices used in close proximity to the ear (frequency range of 300 MHz to 3 GHz)", February 2005
- c) Federal Communications Commission Office of Engineering & Technology (FCC OET), "Evaluating Compliance with FCC Guidelines for Human Exposure to Radiofrequency Electromagnetic Fields; Additional Information for Evaluating Compliance of Mobile and Portable Devices with FCC Limits for Human Exposure to Radiofrequency Emissions", Supplement C (Edition 01-01) to Bulletin 65


Additional Documentation:

- d) DASY4/5 System Handbook

Methods Applied and Interpretation of Parameters:

- *Measurement Conditions:* Further details are available from the Validation Report at the end of the certificate. All figures stated in the certificate are valid at the frequency indicated.
- *Antenna Parameters with TSL:* The dipole is mounted with the spacer to position its feed point exactly below the center marking of the flat phantom section, with the arms oriented parallel to the body axis.
- *Feed Point Impedance and Return Loss:* These parameters are measured with the dipole positioned under the liquid filled phantom. The impedance stated is transformed from the measurement at the SMA connector to the feed point. The Return Loss ensures low reflected power. No uncertainty required.
- *Electrical Delay:* One-way delay between the SMA connector and the antenna feed point. No uncertainty required.
- *SAR measured:* SAR measured at the stated antenna input power.
- *SAR normalized:* SAR as measured, normalized to an input power of 1 W at the antenna connector.
- *SAR for nominal TSL parameters:* The measured TSL parameters are used to calculate the nominal SAR result.

	Document Appendix D for the BlackBerry® Smartphone Model RFA91LW SAR Report			Page 97(114)
Author Data Andrew Becker	Dates of Test Aug 21 – Nov 23, 2012 Jan. 07-11, 2013	Test Report No RTS-6012-1211-32 Rev 3	FCC ID: L6ARFA90LW	IC ID 2503A-RFA90LW

	Document Appendix D for the BlackBerry® Smartphone Model RFA91LW SAR Report			Page 98(114)
	Author Data Andrew Becker	Dates of Test Aug 21 – Nov 23, 2012 Jan. 07-11, 2013	Test Report No RTS-6012-1211-32 Rev 3	FCC ID: L6ARFA90LW

Measurement Conditions

DASY system configuration, as far as not given on page 1.

DASY Version	DASY5	V52.6.2
Extrapolation	Advanced Extrapolation	
Phantom	Modular Flat Phantom	
Distance Dipole Center - TSL	10 mm	with Spacer
Zoom Scan Resolution	dx, dy, dz = 5 mm	
Frequency	2450 MHz ± 1 MHz	

Head TSL parameters


The following parameters and calculations were applied.

	Temperature	Permittivity	Conductivity
Nominal Head TSL parameters	22.0 °C	39.2	1.80 mho/m
Measured Head TSL parameters	(22.0 ± 0.2) °C	37.7 ± 6 %	1.84 mho/m ± 6 %
Head TSL temperature change during test	< 0.5 °C	----	----

SAR result with Head TSL

SAR averaged over 1 cm³ (1 g) of Head TSL	Condition	
SAR measured	250 mW input power	13.8 mW / g
SAR for nominal Head TSL parameters	normalized to 1W	54.1 mW /g ± 17.0 % (k=2)

SAR averaged over 10 cm³ (10 g) of Head TSL	condition	
SAR measured	250 mW input power	6.39 mW / g
SAR for nominal Head TSL parameters	normalized to 1W	25.3 mW /g ± 16.5 % (k=2)

	Document Appendix D for the BlackBerry® Smartphone Model RFA91LW SAR Report			Page 99(114)
	Author Data Andrew Becker	Dates of Test Aug 21 – Nov 23, 2012 Jan. 07-11, 2013	Test Report No RTS-6012-1211-32 Rev 3	FCC ID: L6ARFA90LW

Appendix

Antenna Parameters with Head TSL

Impedance, transformed to feed point	52.5 Ω + 1.3 j Ω
Return Loss	- 31.2 dB

General Antenna Parameters and Design

Electrical Delay (one direction)	1.161 ns
----------------------------------	----------


After long term use with 100W radiated power, only a slight warming of the dipole near the feedpoint can be measured.


The dipole is made of standard semirigid coaxial cable. The center conductor of the feeding line is directly connected to the second arm of the dipole. The antenna is therefore short-circuited for DC-signals.

No excessive force must be applied to the dipole arms, because they might bend or the soldered connections near the feedpoint may be damaged.

Additional EUT Data

Manufactured by	SPEAG
Manufactured on	December 01, 2003

	Document Appendix D for the BlackBerry® Smartphone Model RFA91LW SAR Report			Page 100(114)
Author Data Andrew Becker	Dates of Test Aug 21 – Nov 23, 2012 Jan. 07-11, 2013	Test Report No RTS-6012-1211-32 Rev 3	FCC ID: L6ARFA90LW	IC ID 2503A-RFA90LW

	Document Appendix D for the BlackBerry® Smartphone Model RFA91LW SAR Report			Page 101(114)
	Author Data Andrew Becker	Dates of Test Aug 21 – Nov 23, 2012 Jan. 07-11, 2013	Test Report No RTS-6012-1211-32 Rev 3	FCC ID: L6ARFA90LW

DASY5 Validation Report for Head TSL

Date: 09.11.2011

Test Laboratory: SPEAG, Zurich, Switzerland

DUT: Dipole 2450 MHz; Type: D2450V2; Serial: D2450V2 - SN: 747


Communication System: CW; Frequency: 2450 MHz
 Medium parameters used: $f = 2450 \text{ MHz}$; $\sigma = 1.84 \text{ mho/m}$; $\epsilon_r = 37.7$; $\rho = 1000 \text{ kg/m}^3$
 Phantom section: Flat Section
 Measurement Standard: DASY5 (IEEE/IEC/ANSI C63.19-2007)


DASY52 Configuration:


- Probe: ES3DV3 - SN3205; ConvF(4.45, 4.45, 4.45); Calibrated: 29.04.2011
- Sensor-Surface: 3mm (Mechanical Surface Detection)
- Electronics: DAE4 Sn601; Calibrated: 04.07.2011
- Phantom: Flat Phantom 5.0 (front); Type: QD000P50AA; Serial: 1001
- DASY52 52.6.2(482); SEMCAD X 14.4.5(3634)

Dipole Calibration for Head Tissue/Pin=250 mW, d=10mm/Zoom Scan (7x7x7)/Cube 0:


Measurement grid: $dx=5\text{mm}$, $dy=5\text{mm}$, $dz=5\text{mm}$
 Reference Value = 102.1 V/m; Power Drift = 0.04 dB
 Peak SAR (extrapolated) = 28.853 W/kg
SAR(1 g) = 13.8 mW/g; SAR(10 g) = 6.39 mW/g
 Maximum value of SAR (measured) = 17.782 mW/g





	Document Appendix D for the BlackBerry® Smartphone Model RFA91LW SAR Report			Page 102(114)
Author Data Andrew Becker	Dates of Test Aug 21 – Nov 23, 2012 Jan. 07-11, 2013	Test Report No RTS-6012-1211-32 Rev 3	FCC ID: L6ARFA90LW	IC ID 2503A-RFA90LW

	Document Appendix D for the BlackBerry® Smartphone Model RFA91LW SAR Report			Page 103(114)
	Author Data Andrew Becker	Dates of Test Aug 21 – Nov 23, 2012 Jan. 07-11, 2013	Test Report No RTS-6012-1211-32 Rev 3	FCC ID: L6ARFA90LW

Impedance Measurement Plot for Head TSL



	Document Appendix D for the BlackBerry® Smartphone Model RFA91LW SAR Report			Page 104(114)
Author Data Andrew Becker	Dates of Test Aug 21 – Nov 23, 2012 Jan. 07-11, 2013	Test Report No RTS-6012-1211-32 Rev 3	FCC ID: L6ARFA90LW	IC ID 2503A-RFA90LW

	Document Appendix D for the BlackBerry® Smartphone Model RFA91LW SAR Report			Page 105(114)
	Author Data Andrew Becker	Dates of Test Aug 21 – Nov 23, 2012 Jan. 07-11, 2013	Test Report No RTS-6012-1211-32 Rev 3	FCC ID: L6ARFA90LW

**Calibration Laboratory of
Schmid & Partner
Engineering AG**
 Zeughausstrasse 43, 8004 Zurich, Switzerland



S Schweizerischer Kalibrierdienst
C Service suisse d'étalonnage
S Servizio svizzero di taratura
S Swiss Calibration Service

Accredited by the Swiss Accreditation Service (SAS)
 The Swiss Accreditation Service is one of the signatories to the EA
 Multilateral Agreement for the recognition of calibration certificates

Accreditation No.: **SCS 108**

Client **RTS (RIM Testing Services)**

Certificate No: **D5GHzV2-1033_Nov11**

CALIBRATION CERTIFICATE



Object: **D5GHzV2 - SN: 1033**
 Calibration procedure(s): **QA CAL-22.v1
Calibration procedure for dipole validation kits between 3-6 GHz**
 Calibration date: **November 15, 2011**

This calibration certificate documents the traceability to national standards, which realize the physical units of measurements (SI).
 The measurements and the uncertainties with confidence probability are given on the following pages and are part of the certificate.

All calibrations have been conducted in the closed laboratory facility: environment temperature (22 ± 3)°C and humidity < 70%.


Calibration Equipment used (M&TE critical for calibration)

Primary Standards	ID #	Cal Date (Certificate No.)	Scheduled Calibration
Power meter EPM-442A	GB37480704	05-Oct-11 (No. 217-01451)	Oct-12
Power sensor HP B481A	US37292783	05-Oct-11 (No. 217-01451)	Oct-12
Reference 20 dB Attenuator	SN: 5086 (20g)	29-Mar-11 (No. 217-01368)	Apr-12
Type-N mismatch combination	SN: 5047.2 / 06327	29-Mar-11 (No. 217-01371)	Apr-12
Reference Probe EX3DV4	SN: 3503	04-Mar-11 (No. EX3-3503_Mar11)	Mar-12
DAE4	SN: 601	04-Jul-11 (No. DAE4-601_Jul11)	Jul-12
Secondary Standards	ID #	Check Date (in house)	Scheduled Check
Power sensor HP B481A	MY41092317	18-Oct-02 (in house check Oct-11)	In house check: Oct-13
RF generator R&S SMT-06	100005	04-Aug-99 (in house check Oct-11)	In house check: Oct-13
Network Analyzer HP 8753E	US37390585 S4206	18-Oct-01 (in house check Oct-11)	In house check: Oct-12

Calibrated by: **Dimce Iliev**, Laboratory Technician, Signature: 
 Approved by: **Katja Pokovic**, Technical Manager, Signature: 

Issued: November 16, 2011

This calibration certificate shall not be reproduced except in full without written approval of the laboratory.

	Document Appendix D for the BlackBerry® Smartphone Model RFA91LW SAR Report			Page 106(114)
	Author Data Andrew Becker	Dates of Test Aug 21 – Nov 23, 2012 Jan. 07-11, 2013	Test Report No RTS-6012-1211-32 Rev 3	FCC ID: L6ARFA90LW

**Calibration Laboratory of
Schmid & Partner
Engineering AG**
 Zeughausstrasse 43, 8004 Zurich, Switzerland



S Schweizerischer Kalibrierdienst
C Service suisse d'étalonnage
S Servizio svizzero di taratura
S Swiss Calibration Service

Accredited by the Swiss Accreditation Service (SAS)
 The Swiss Accreditation Service is one of the signatories to the EA
 Multilateral Agreement for the recognition of calibration certificates

Accreditation No.: **SCS 108**

Glossary:

TSL tissue simulating liquid
 ConvF sensitivity in TSL / NORM x,y,z
 N/A not applicable or not measured

Calibration is Performed According to the Following Standards:


- a) IEEE Std 1528-2003, "IEEE Recommended Practice for Determining the Peak Spatial-Averaged Specific Absorption Rate (SAR) in the Human Head from Wireless Communications Devices: Measurement Techniques", December 2003
- b) IEC 62209-1, "Procedure to measure the Specific Absorption Rate (SAR) for hand-held devices used in close proximity to the ear (frequency range of 300 MHz to 3 GHz)", February 2005
- c) Federal Communications Commission Office of Engineering & Technology (FCC OET), "Evaluating Compliance with FCC Guidelines for Human Exposure to Radiofrequency Electromagnetic Fields; Additional Information for Evaluating Compliance of Mobile and Portable Devices with FCC Limits for Human Exposure to Radiofrequency Emissions", Supplement C (Edition 01-01) to Bulletin 65

Additional Documentation:

- d) DASY4/5 System Handbook

Methods Applied and Interpretation of Parameters:

- *Measurement Conditions:* Further details are available from the Validation Report at the end of the certificate. All figures stated in the certificate are valid at the frequency indicated.
- *Antenna Parameters with TSL:* The dipole is mounted with the spacer to position its feed point exactly below the center marking of the flat phantom section, with the arms oriented parallel to the body axis.
- *Feed Point Impedance and Return Loss:* These parameters are measured with the dipole positioned under the liquid filled phantom. The impedance stated is transformed from the measurement at the SMA connector to the feed point. The Return Loss ensures low reflected power. No uncertainty required.
- *Electrical Delay:* One-way delay between the SMA connector and the antenna feed point. No uncertainty required.
- *SAR measured:* SAR measured at the stated antenna input power.
- *SAR normalized:* SAR as measured, normalized to an input power of 1 W at the antenna connector.
- *SAR for nominal TSL parameters:* The measured TSL parameters are used to calculate the nominal SAR result.

	Document Appendix D for the BlackBerry® Smartphone Model RFA91LW SAR Report			Page 107(114)
	Author Data Andrew Becker	Dates of Test Aug 21 – Nov 23, 2012 Jan. 07-11, 2013	Test Report No RTS-6012-1211-32 Rev 3	FCC ID: L6ARFA90LW

Measurement Conditions

DASY system configuration, as far as not given on page 1.

DASY Version	DASY5	V52.6.2
Extrapolation	Advanced Extrapolation	
Phantom	Modular Flat Phantom V5.0	
Distance Dipole Center - TSL	10 mm	with Spacer
Zoom Scan Resolution	dx, dy = 4.0 mm, dz = 1.4 mm	Graded Ratio = 1.4 (Z direction)
Frequency	5200 MHz ± 1 MHz 5500 MHz ± 1 MHz 5800 MHz ± 1 MHz	

Head TSL parameters at 5200 MHz

The following parameters and calculations were applied.

	Temperature	Permittivity	Conductivity
Nominal Head TSL parameters	22.0 °C	36.0	4.66 mho/m
Measured Head TSL parameters	(22.0 ± 0.2) °C	34.6 ± 6 %	4.46 mho/m ± 6 %
Head TSL temperature change during test	< 0.5 °C	----	----

SAR result with Head TSL at 5200 MHz

SAR averaged over 1 cm ³ (1 g) of Head TSL	Condition	
SAR measured	100 mW input power	8.16 mW / g
SAR for nominal Head TSL parameters	normalized to 1W	80.8 mW / g ± 17.0 % (k=2)

SAR averaged over 10 cm ³ (10 g) of Head TSL	condition	
SAR measured	100 mW input power	2.33 mW / g
SAR for nominal Head TSL parameters	normalized to 1W	23.0 mW / g ± 16.5 % (k=2)

Head TSL parameters at 5500 MHz


The following parameters and calculations were applied.

	Temperature	Permittivity	Conductivity
Nominal Head TSL parameters	22.0 °C	35.6	4.96 mho/m
Measured Head TSL parameters	(22.0 ± 0.2) °C	34.2 ± 6 %	4.75 mho/m ± 6 %
Head TSL temperature change during test	< 0.5 °C	----	----

SAR result with Head TSL at 5500 MHz

SAR averaged over 1 cm ³ (1 g) of Head TSL	Condition	
SAR measured	100 mW input power	8.82 mW / g
SAR for nominal Head TSL parameters	normalized to 1W	87.3 mW / g ± 17.0 % (k=2)

SAR averaged over 10 cm ³ (10 g) of Head TSL	condition	
SAR measured	100 mW input power	2.50 mW / g
SAR for nominal Head TSL parameters	normalized to 1W	24.7 mW / g ± 16.5 % (k=2)

	Document Appendix D for the BlackBerry® Smartphone Model RFA91LW SAR Report			Page 108(114)
	Author Data Andrew Becker	Dates of Test Aug 21 – Nov 23, 2012 Jan. 07-11, 2013	Test Report No RTS-6012-1211-32 Rev 3	FCC ID: L6ARFA90LW

Head TSL parameters at 5800 MHz


The following parameters and calculations were applied.


	Temperature	Permittivity	Conductivity
Nominal Head TSL parameters	22.0 °C	35.3	5.27 mho/m
Measured Head TSL parameters	(22.0 ± 0.2) °C	33.7 ± 6 %	5.03 mho/m ± 6 %
Head TSL temperature change during test	< 0.5 °C	----	----

SAR result with Head TSL at 5800 MHz

SAR averaged over 1 cm ³ (1 g) of Head TSL	Condition	
SAR measured	100 mW input power	8.03 mW / g
SAR for nominal Head TSL parameters	normalized to 1W	79.4 mW / g ± 17.0 % (k=2)

SAR averaged over 10 cm ³ (10 g) of Head TSL	condition	
SAR measured	100 mW input power	2.28 mW / g
SAR for nominal Head TSL parameters	normalized to 1W	22.5 mW / g ± 16.5 % (k=2)

	Document Appendix D for the BlackBerry® Smartphone Model RFA91LW SAR Report			Page 109(114)
Author Data Andrew Becker	Dates of Test Aug 21 – Nov 23, 2012 Jan. 07-11, 2013	Test Report No RTS-6012-1211-32 Rev 3	FCC ID: L6ARFA90LW	IC ID 2503A-RFA90LW

	Document Appendix D for the BlackBerry® Smartphone Model RFA91LW SAR Report			Page 110(114)
	Author Data Andrew Becker	Dates of Test Aug 21 – Nov 23, 2012 Jan. 07-11, 2013	Test Report No RTS-6012-1211-32 Rev 3	FCC ID: L6ARFA90LW

Appendix

Antenna Parameters with Head TSL at 5200 MHz

Impedance, transformed to feed point	51.1 Ω - 8.7 $j\Omega$
Return Loss	- 21.2 dB

Antenna Parameters with Head TSL at 5500 MHz

Impedance, transformed to feed point	52.3 Ω - 2.7 $j\Omega$
Return Loss	- 29.2 dB

Antenna Parameters with Head TSL at 5800 MHz

Impedance, transformed to feed point	56.7 Ω - 4.3 $j\Omega$
Return Loss	- 22.6 dB

General Antenna Parameters and Design

Electrical Delay (one direction)	1.202 ns
----------------------------------	----------


After long term use with 100W radiated power, only a slight warming of the dipole near the feedpoint can be measured.

The dipole is made of standard semirigid coaxial cable. The center conductor of the feeding line is directly connected to the second arm of the dipole. The antenna is therefore short-circuited for DC-signals.

No excessive force must be applied to the dipole arms, because they might bend or the soldered connections near the feedpoint may be damaged.

Additional EUT Data

Manufactured by	SPEAG
Manufactured on	July 09, 2004

	Document Appendix D for the BlackBerry® Smartphone Model RFA91LW SAR Report			Page 111(114)
	Author Data Andrew Becker	Dates of Test Aug 21 – Nov 23, 2012 Jan. 07-11, 2013	Test Report No RTS-6012-1211-32 Rev 3	FCC ID: L6ARFA90LW

DASY5 Validation Report for Head TSL

Date: 15.11.201

Test Laboratory: SPEAG, Zurich, Switzerland

DUT: Dipole 5GHz; Type: D5GHzV2; Serial: D5GHzV2 - SN: 1033

Communication System: CW; Frequency: 5200 MHz, Frequency: 5500 MHz, Frequency: 5800 MHz
Medium parameters used: $f = 5200$ MHz; $\sigma = 4.46$ mho/m; $\epsilon_r = 34.6$; $\rho = 1000$ kg/m³, Medium parameters used: $f = 5500$ MHz; $\sigma = 4.75$ mho/m; $\epsilon_r = 34.2$; $\rho = 1000$ kg/m³, Medium parameters used: $f = 5800$ MHz; $\sigma = 5.03$ mho/m; $\epsilon_r = 33.7$; $\rho = 1000$ kg/m³
Phantom section: Flat Section
Measurement Standard: DASY5 (IEEE/IEC/ANSI C63.19-2007)


DASY52 Configuration:

- Probe: EX3DV4 - SN3503; ConvF(5.41, 5.41, 5.41), ConvF(4.91, 4.91, 4.91), ConvF(4.81, 4.81, 4.81); Calibrated: 04.03.2011
- Sensor-Surface: 1.4mm (Mechanical Surface Detection)
- Electronics: DAE4 Sn601; Calibrated: 04.07.2011
- Phantom: Flat Phantom 5.0 (front); Type: QD000P50AA; Serial: 1001
- DASY52 52.6.2(482); SEMCAD X 14.4.5(3634)

Dipole Calibration for Head Tissue/Pin=100mW, dist=10mm, f=5200 MHz/Zoom Scan, dist=1.4mm (8x8x7)/Cube 0: Measurement grid: dx=4mm, dy=4mm, dz=1.4mm
Reference Value = 65.595 V/m; Power Drift = 0.07 dB
Peak SAR (extrapolated) = 30.134 W/kg
SAR(1 g) = 8.16 mW/g; SAR(10 g) = 2.33 mW/g
Maximum value of SAR (measured) = 18.725 mW/g

Dipole Calibration for Head Tissue/Pin=100mW, dist=10mm, f=5500 MHz/Zoom Scan, dist=1.4mm (8x8x7)/Cube 0: Measurement grid: dx=4mm, dy=4mm, dz=1.4mm
Reference Value = 66.819 V/m; Power Drift = 0.03 dB
Peak SAR (extrapolated) = 35.056 W/kg
SAR(1 g) = 8.82 mW/g; SAR(10 g) = 2.5 mW/g
Maximum value of SAR (measured) = 21.019 mW/g

Dipole Calibration for Head Tissue/Pin=100mW, dist=10mm, f=5800 MHz/Zoom Scan, dist=1.4mm (8x8x7)/Cube 0: Measurement grid: dx=4mm, dy=4mm, dz=1.4mm
Reference Value = 62.220 V/m; Power Drift = 0.04 dB
Peak SAR (extrapolated) = 33.743 W/kg
SAR(1 g) = 8.03 mW/g; SAR(10 g) = 2.28 mW/g
Maximum value of SAR (measured) = 19.463 mW/g

	Document Appendix D for the BlackBerry® Smartphone Model RFA91LW SAR Report			Page 112(114)
Author Data Andrew Becker	Dates of Test Aug 21 – Nov 23, 2012 Jan. 07-11, 2013	Test Report No RTS-6012-1211-32 Rev 3	FCC ID: L6ARFA90LW	IC ID 2503A-RFA90LW


Author Data
Andrew Becker

Dates of Test
**Aug 21 – Nov 23, 2012
Jan. 07-11, 2013**

Test Report No
RTS-6012-1211-32 Rev 3

FCC ID:
L6ARFA90LW

IC ID
2503A-RFA90LW



0 dB = 19.460mW/g

Author Data
Andrew Becker

Dates of Test
**Aug 21 – Nov 23, 2012
 Jan. 07-11, 2013**

Test Report No
RTS-6012-1211-32 Rev 3

FCC ID:
L6ARFA90LW

IC ID
2503A-RFA90LW

Impedance Measurement Plot for Head TSL

