



Figure 1 - LABEL LOCATION

FINAL  
PROOF  
APR 09 1993

## WanderGuard E Remote Reset and Bypass

See Instruction manual for complete instructions & warnings.

**To reset:** Hold within 4' of WG-E door module. Press button **once**. LED turns green and alarm stops.

**To bypass:** Hold within 4' of WG-E door module. Press button **twice**. LED turns red. Door can be opened without sounding alarm.

0507-104

#18035 WG-E Remote Reset & Bypass FCC ID: LA5 WERB001 Canada 2459102936

Model

200% size

WG-E remote bypass label 3/98 lh7 Bill Shaffer (402) 475-4002 ext. 3413

