



Shenzhen Certification Technologh Service Co., Ltd
2F, Building B, East Area of Nanchang Second Industrial Zone,
Gushu 2nd Road, Bao'an District, Shenzhen 518126, P.R. China

TEST REPORT

FCC ID: LU7-TS100

Applicant : Shenzhen YIDONG Technology Co., Ltd.
Address : Floor 1-5,Building B, Area B, Yuanfen Industrial Zone, Dalang,
Bao'an District, Shenzhen, China

Equipment under Test (EUT):

Name : Flat Computer

Model : TS100, EMR3074

Standards : FCC PART 15, Subpart B (Class B): 2012
Report No. : CST-TCB131217003-1

Date of Test : December 18-31, 2013

Date of Issue : January 4, 2014

| | |
|----------------------|---------------|
| Test Result : | PASS * |
|----------------------|---------------|

* In the configuration tested, the EUT complied with the standards specified above

Authorized Signature

(Mark Zhu)
General Manager

The manufacture should ensure that all the products in series production are in conformity with the product sample detailed in this report.

If the product in this report is used in any configuration other than that detailed in the report, the manufacturer must ensure the new system complies with all relevant standards. Any mention of Shenzhen Certification Technology Service Co., Ltd. Or test done by Shenzhen Certification Technology Service Co., Ltd. Approvals in connection with, distribution or use of the product described in this report must be approved by Shenzhen Certification Technology Service Co., Ltd. Approvals in writing.

TABLE OF CONTENTS

| <u>Description</u> | <u>Page</u> |
|---|-------------|
| Test Report Declaration | 3 |
| 1. Summary of standards and results | 4 |
| 1.1. Description of Standards and Results..... | 4 |
| 2. GENERAL INFORMATION | 5 |
| 2.1. Description of Device (EUT) | 5 |
| 2.2. Tested Supporting System Details | 6 |
| 2.3. Block Diagram of connection between EUT and simulators | 6 |
| 2.4. Test Facility | 7 |
| 2.5. Measurement Uncertainty | 7 |
| 3. POWER LINE CONDUCTED Emission test | 8 |
| 3.1. Test Equipment..... | 8 |
| 3.2. Block Diagram of Test Setup | 8 |
| 3.3. Power Line Conducted Emission Test Limits | 8 |
| 3.4. Configuration of EUT on Test..... | 9 |
| 3.5. Operating Condition of EUT | 9 |
| 3.6. Test Procedure | 9 |
| 3.7. Conducted Disturbance at Mains Terminals Test Results..... | 9 |
| 4. Radiated emission Test | 18 |
| 4.1. Test Equipment..... | 18 |
| 4.2. Block Diagram of Test Setup | 18 |
| 4.3. Radiated Emission Limit | 19 |
| 4.4. EUT Configuration on Test | 19 |
| 4.5. Operating Condition of EUT | 20 |
| 4.6. Test Procedure | 20 |
| 4.7. Radiated Disturbance Test Results..... | 20 |
| 5. Photograph | 37 |
| 5.1. Photos of Power Line Conducted Emission Test | 37 |
| 5.2. Photos of Radiated Emission Test (In Anechoic Chamber)..... | 38 |
| 6. Photos of the EUT | 40 |

TEST REPORT VERIFICATION

Applicant : Shenzhen YIDONG Technology Co., Ltd.
Manufacturer : Shenzhen YIDONG Technology Co., Ltd.
EUT Description : Flat Computer
(A) Model No. : TS100, EMR3074
(B) Trademark : N/A
(C) DIFF : Only different in Model No, the other the same.
The test model: TS100
(C) Power Supply : DC 5V From Adapter
(D) Test Voltage : DC 5V From Adapter AC 120V/60Hz

Measurement Standard Used:

FCC PART 15, Subpart B (Class B): 2012

The device described above is tested by Shenzhen Certification Technology Service Co., Ltd. to determine the maximum emission levels emanating from the device. The maximum emission levels are compared to the FCC Part 15 Subpart B Class B limits both conducted and radiated emissions. The test results are contained in this test report and Shenzhen Certification Technology Service Co., Ltd. is assumed of full responsibility for the accuracy and completeness of these tests.

After the test, our opinion is that EUT compliance with the requirement of the above standards.

This report applies to above tested sample only. This report shall not be reproduced in parts without written approval of Shenzhen Certification Technology Service Co., Ltd.

1. SUMMARY OF STANDARDS AND RESULTS

1.1. Description of Standards and Results

The EUT have been tested according to the applicable standards as referenced below.

| EMISSION | | | |
|------------------------------------|---------------------------------------|---------------|----------------|
| Description of Test Item | Standard | Limits | Results |
| Power Line Conducted Emission Test | FCC Part 15: 2012 ANSI C63.4: 2003 | Class B | PASS |
| Radiated Emission Test | FCC Part 15: 2012 ANSI C63.4: 2003 | Class B | PASS |

2. GENERAL INFORMATION

2.1. Description of Device (EUT)

Description : Flat Computer

Model Number : TS100

Trademark : N/A

Power Supply : DC 5V From Adapter

Adapter 1 : Information: Switching power adapter

Model: WRP2U-050200C

Input: AC 100-240V, 50/60Hz 0.3A

Output: DC 5V, 1.5A

Adapter 2 : Information: Switching power adapter

Model: SCT-A520B-D

Input: AC 100-240V, 50/60Hz 0.4A max

Output: DC 5V, 1.5A

Applicant : Shenzhen YIDONG Technology Co.,Ltd.

Floor 1-5, Building B, Area B, Yuanfen Industrial Zone, Dalang,

Bao'an District, Shenzhen, China

Manufacturer : Shenzhen YIDONG Technology Co.,Ltd.

Floor 1-5, Building B, Area B, Yuanfen Industrial Zone, Dalang,

Bao'an District, Shenzhen, China

Date of Test : December 18-31, 2013



Sample Type : Series production

2.2. Tested Supporting System Details

| No. | Description | Manufacturer | Model | Serial Number |
|-----|-------------------|--------------|--------------|------------------------|
| 1. | Personal Computer | ACER | ASPIRE M1830 | PTSF90C00305005CAC3000 |
| 2. | Monitor | ACER | G205HV | SNID:10306738385 |
| 3. | USB Keyboard | ACER | SK-9625 | KBUSB1580500037E0100 |
| 4. | USB Mouse | ACER | MS.11200.014 | M-UAY-ACR2 |
| 5. | Printer | HP | HP1020 | CNCJ410726 |

Note: These equipment has FCC DOC certificate.

2.3. Block Diagram of connection between EUT and simulators



※ EUT: Flat Computer

2.4. Test Facility

JAN 13, 2012 File on Federal Communication Commission
Registration Number: 197647

October 11, 2011 Certificated by IC
Registration Number: 8528B

2.5. Measurement Uncertainty

(95% confidence levels, k=2)


| Test Item | Uncertainty |
|---|------------------------------------|
| Uncertainty for Conduction emission test | 2.50dB |
| Uncertainty for Radiation Emission test | 3.04 dB (Distance: 3m Polarize: V) |
| | 3.02 dB (Distance: 3m Polarize: H) |
| Uncertainty for Radiation Emission test (1GHz-18GHz) | 3.56 dB (Distance: 3m Polarize: V) |
| | 3.84 dB (Distance: 3m Polarize: H) |
| Uncertainty for test site temperature and humidity | 0.6°C |
| | 3% |

3. POWER LINE CONDUCTED EMISSION TEST

3.1. Test Equipment

| Item | Equipment | Manufacturer | Model No. | Serial No. | Last Cal. | Cal. Interval |
|------|-------------------|---------------|-----------------|-----------------------|-------------|---------------|
| 1. | Test Receiver | Rohde&Schwarz | ESCI | 1166.5950K03 -1011 | Oct. 30, 13 | 1 Year |
| 2. | L.I.S.N. | Schwarzbeck | NSLK8126 | 8126466 | Oct. 30, 13 | 1 Year |
| 3. | L.I.S.N.-2 | Kyoritsu | KNW-407 | 8-1628-5 | Oct. 30, 13 | 1 Year |
| 4. | Terminator | Hubersuhner | 50Ω | No. 1 | Oct. 30, 13 | 1 Year |
| 5. | RF Cable | Schwarzbeck | 9111505/20 0 | 5995-12-161-6 890# | Oct. 30, 13 | 1 Year |
| 6. | Coaxial Switch | Schwarzbeck | CX-210 | N/A | Oct. 30, 13 | 1 Year |
| 7. | Pulse Limiter | Schwarzbeck | VTSD9516 F | 9618 | Oct. 30, 13 | 1 Year |

3.2. Block Diagram of Test Setup



3.3. Power Line Conducted Emission Test Limits

| Frequency | Maximum RF Line Voltage | |
|-----------------|----------------------------|-------------------------|
| | Quasi-Peak Level dB(µV) | Average Level dB(µV) |
| 150kHz ~ 500kHz | 66 ~ 56* | 56 ~ 46* |
| 500kHz ~ 5MHz | 56 | 46 |
| 5MHz ~ 30MHz | 60 | 50 |

Notes: 1. Emission level=Read level+ LISN factor+Preamp factor+ Cable loss

2* Decreasing linearly with logarithm of frequency.

3. The lower limit shall apply at the transition frequencies.

3.4. Configuration of EUT on Test

The following equipment are installed on Power Line Conducted Emission Test to meet the commission requirement and operating regulations in a manner which tends to maximize its emission characteristics in a normal application.

Support Equipments : As Tested Supporting System Detail, in Section 2.2.

3.5. Operating Condition of EUT

- 3.5.1. Setup the EUT and simulator as shown as Section 3.2.
- 3.5.2. Turn on the power of all equipment.
- 3.5.3. Let the EUT work in test mode (ON) and measure it.

3.6. Test Procedure

The EUT was placed on a non-metallic table, 80cm above the ground plane. The EUT Power connected to the power mains through a line impedance stabilization network (L.I.S.N. 1#). The other peripheral devices power cord connected to the power mains through a line impedance stabilization network (L.I.S.N. #2), this provided a 50-ohm coupling impedance for the EUT (Please refer to the block diagram of the test setup and photographs). Both sides of power line were checked for maximum conducted interference. In order to find the maximum emission, the relative positions of equipments and all of the interface cables were changed according to ANSI C63.4-2003 on conducted Emission test.

The bandwidth of test receiver (R&S TEST RECEIVER ESCI) is set at 10kHz.

The frequency range from 150KHz to 30MHz is checked. The test result are reported on Section 3.7.

3.7. Conducted Disturbance at Mains Terminals Test Results

PASS. (All emissions not reported below are too low against the prescribed limits.)

The EUT with the following test mode was tested and read Q.P values and average values, the test results are listed in next pages.


Temperature: 24°C Humidity: 56%

The details of test mode is as follows :

| NO. | Test Mode |
|-----|--|
| 1. | Charge And Data Transmitting for adapter 1 |
| 2. | Charge And Play Video for adapter 1 |
| 3. | Charge And Data Transmitting for adapter 2 |
| 4. | Charge And Play Video for adapter 2 |



Shenzhen Certification Technology Service Co., Ltd.
2F, Building B, East Area of Nanchang Second Industrial Zone,
Gushu 2nd Road, Bao'an District, Shenzhen 518126, P.R. China
Tel: 4006786199 Fax: +86-755-26736857
Website: <http://www.cessz.com> Email: Service@cessz.com



Condition : FCC PART 15 B QP POL: NEUTRAL Temp:20 °C Hum:53 %
 EUT : Flat Computer
 Model No : TS100
 Test Mode : Charging and Playing Video
 Power : DC 5V From Adapter AC 120V/60Hz
 Test Engineer: Store
 Remark : WRP2U-050200C

| Item | Freq | Read | LISN | Preamp | Cable | Level | Limit | Margin | Remark |
|------|--------|-------|--------|--------|--------|-------|-------|--------|---------|
| | | | Factor | Factor | Factor | dBuV | dBuV | dBuV | |
| | MHz | dBuV | dB | dB | dB | | | | |
| 1 | 0.190 | 50.12 | 0.03 | -9.72 | 0.10 | 59.97 | 64.02 | -4.05 | QP |
| 2 | 0.190 | 37.12 | 0.03 | -9.72 | 0.10 | 46.97 | 54.02 | -7.05 | Average |
| 3 | 0.317 | 43.90 | 0.03 | -9.72 | 0.10 | 53.75 | 59.80 | -6.05 | QP |
| 4 | 0.317 | 28.90 | 0.03 | -9.72 | 0.10 | 38.75 | 49.80 | -11.05 | Average |
| 5 | 0.444 | 40.30 | 0.03 | -9.72 | 0.10 | 50.15 | 56.98 | -6.83 | QP |
| 6 | 0.444 | 24.30 | 0.03 | -9.72 | 0.10 | 34.15 | 46.98 | -12.83 | Average |
| 7 | 0.567 | 38.22 | 0.03 | -9.72 | 0.10 | 48.07 | 56.00 | -7.93 | QP |
| 8 | 0.567 | 22.22 | 0.03 | -9.72 | 0.10 | 32.07 | 46.00 | -13.93 | Average |
| 9 | 2.900 | 26.93 | 0.07 | -9.70 | 0.12 | 36.82 | 56.00 | -19.18 | QP |
| 10 | 2.900 | 10.93 | 0.07 | -9.70 | 0.12 | 20.82 | 46.00 | -25.18 | Average |
| 11 | 10.905 | 27.36 | 0.23 | -9.49 | 0.22 | 37.30 | 60.00 | -22.70 | QP |
| 12 | 10.905 | 12.36 | 0.23 | -9.49 | 0.22 | 22.30 | 50.00 | -27.70 | Average |

Remarks: Level = Read + LISN Factor - Preamp Factor + Cable loss




Shenzhen Certification Technology Service Co., Ltd.
2F, Building B, East Area of Nanchang Second Industrial Zone,
Gushu 2nd Road, Bao'an District, Shenzhen 518126, P.R. China
Tel: 4006786199 Fax: +86-755-26736857
Website: <http://www.cessz.com> Email: Service@cessz.com

Data: 29

File: E:\TEST REPORT\WuXian\YiDong\Conduction CN-1.EM6 (42)

Date: 2013-12-24 Time: 13:58:19




Condition : FCC PART 15 B QP POL: LINE Temp:20 °C Hum:53 %
 EUT : Flat Computer
 Model No : TS100
 Test Mode : Charging and Playing Video
 Power : DC 5V From Adapter AC 120V/60Hz
 Test Engineer: Store
 Remark : WRP2U-050200C

| Item | Freq | Read | LISN | Preamp | Cable | Level | Limit | Margin | Remark |
|------|-------|-------|--------|--------|--------|-------|-------|--------|---------|
| | | | Factor | Factor | Factor | dBuV | dBuV | dBuV | |
| | MHz | dBuV | dB | dB | dB | | | | |
| 1 | 0.190 | 47.61 | 0.03 | -9.72 | 0.10 | 57.46 | 64.02 | -6.56 | QP |
| 2 | 0.190 | 36.61 | 0.03 | -9.72 | 0.10 | 46.46 | 54.02 | -7.56 | Average |
| 3 | 0.317 | 39.20 | 0.03 | -9.72 | 0.10 | 49.05 | 59.80 | -10.75 | QP |
| 4 | 0.317 | 25.20 | 0.03 | -9.72 | 0.10 | 35.05 | 49.80 | -14.75 | Average |
| 5 | 0.567 | 34.36 | 0.03 | -9.72 | 0.10 | 44.21 | 56.00 | -11.79 | QP |
| 6 | 0.567 | 23.36 | 0.03 | -9.72 | 0.10 | 33.21 | 46.00 | -12.79 | Average |
| 7 | 1.585 | 25.78 | 0.05 | -9.71 | 0.10 | 35.64 | 56.00 | -20.36 | QP |
| 8 | 1.585 | 16.78 | 0.05 | -9.71 | 0.10 | 26.64 | 46.00 | -19.36 | Average |
| 9 | 2.839 | 21.44 | 0.07 | -9.70 | 0.12 | 31.33 | 56.00 | -24.67 | QP |
| 10 | 2.839 | 12.44 | 0.07 | -9.70 | 0.12 | 22.33 | 46.00 | -23.67 | Average |
| 11 | 7.852 | 20.65 | 0.14 | -9.49 | 0.16 | 30.44 | 60.00 | -29.56 | QP |
| 12 | 7.852 | 7.65 | 0.14 | -9.49 | 0.16 | 17.44 | 50.00 | -32.56 | Average |

Remarks: Level = Read + LISN Factor - Preamp Factor + Cable loss



Shenzhen Certification Technology Service Co., Ltd.
2F, Building B, East Area of Nanchang Second Industrial Zone,
Gushu 2nd Road, Bao'an District, Shenzhen 518126, P.R. China
Tel: 4006786199 Fax: +86-755-26736857
Website: <http://www.cessz.com> Email: Service@cessz.com



Condition : FCC PART 15 B QP POL: LINE Temp: 24 °C Hum: 56 %
 EUT : Flat Computer
 Model No : TS100
 Test Mode : Charging And Data Transmitting
 Power : DC 5V From Adapter AC 120V/60Hz
 Test Engineer: Store
 Remark : WRP2U-050200C

| Item | Freq | Read | LISN | Preamp | Cable | Level | Limit | Margin | Remark |
|------|-------|-------|--------|--------|-------|-------|-------|--------|---------|
| | | | Factor | Factor | Loss | dBuV | dBuV | dBuV | |
| | MHz | dBuV | dB | dB | dB | | | | |
| 1 | 0.182 | 49.62 | 0.03 | -9.72 | 0.10 | 59.47 | 64.42 | -4.95 | QP |
| 2 | 0.182 | 31.62 | 0.03 | -9.72 | 0.10 | 41.47 | 54.42 | -12.95 | Average |
| 3 | 0.242 | 45.60 | 0.03 | -9.72 | 0.10 | 55.45 | 62.04 | -6.59 | QP |
| 4 | 0.242 | 32.60 | 0.03 | -9.72 | 0.10 | 42.45 | 52.04 | -9.59 | Average |
| 5 | 0.541 | 38.28 | 0.03 | -9.72 | 0.10 | 48.13 | 56.00 | -7.87 | QP |
| 6 | 0.541 | 21.28 | 0.03 | -9.72 | 0.10 | 31.13 | 46.00 | -14.87 | Average |
| 7 | 0.963 | 35.90 | 0.04 | -9.71 | 0.10 | 45.75 | 56.00 | -10.25 | QP |
| 8 | 0.963 | 22.90 | 0.04 | -9.71 | 0.10 | 32.75 | 46.00 | -13.25 | Average |
| 9 | 2.707 | 38.44 | 0.07 | -9.70 | 0.11 | 48.32 | 56.00 | -7.68 | QP |
| 10 | 2.707 | 19.44 | 0.07 | -9.70 | 0.11 | 29.32 | 46.00 | -16.68 | Average |
| 11 | 6.557 | 29.97 | 0.12 | -9.57 | 0.15 | 39.81 | 60.00 | -20.19 | QP |
| 12 | 6.557 | 14.97 | 0.12 | -9.57 | 0.15 | 24.81 | 50.00 | -25.19 | Average |

Remarks: Level = Read + LISN Factor - Preamp Factor + Cable loss




Shenzhen Certification Technology Service Co., Ltd.
2F, Building B, East Area of Nanchang Second Industrial Zone,
Gushu 2nd Road, Bao'an District, Shenzhen 518126, P.R. China
Tel: 4006786199 Fax: +86-755-26736857
Website: <http://www.cessz.com> Email: Service@cessz.com

Data: 39

File: E:\TEST REPORT\WuXian\YiDong\Conduction CN-1.EM6 (42)

Date: 2013-12-22 Time: 10:12:29



Condition : FCC PART 15 B QP POL: NEUTRAL Temp: 24 °C Hum: 56 %
 EUT : Flat Computer
 Model No : TS100
 Test Mode : Charge And Data transmitting
 Power : DC 5V From Adapter AC 120V/60Hz
 Test Engineer: Store
 Remark : WRP2U-050200C

| Item | Freq | Read | LISN | Preamp | Cable | Level | Limit | Margin | Remark |
|------|--------|-------|--------|--------|-------|-------|-------|--------|---------|
| | | | Factor | Factor | Loss | dBuV | dBuV | dBuV | |
| | MHz | dBuV | dB | dB | dB | | | | |
| 1 | 0.182 | 48.46 | 0.03 | -9.72 | 0.10 | 58.31 | 64.42 | -6.11 | QP |
| 2 | 0.182 | 31.46 | 0.03 | -9.72 | 0.10 | 41.31 | 54.42 | -13.11 | Average |
| 3 | 0.844 | 36.91 | 0.04 | -9.71 | 0.10 | 46.76 | 56.00 | -9.24 | QP |
| 4 | 0.844 | 15.91 | 0.04 | -9.71 | 0.10 | 25.76 | 46.00 | -20.24 | Average |
| 5 | 2.707 | 31.14 | 0.07 | -9.70 | 0.11 | 41.02 | 56.00 | -14.98 | QP |
| 6 | 2.707 | 15.14 | 0.07 | -9.70 | 0.11 | 25.02 | 46.00 | -20.98 | Average |
| 7 | 3.901 | 31.79 | 0.08 | -9.69 | 0.12 | 41.68 | 56.00 | -14.32 | QP |
| 8 | 3.901 | 12.79 | 0.08 | -9.69 | 0.12 | 22.68 | 46.00 | -23.32 | Average |
| 9 | 5.594 | 32.21 | 0.10 | -9.64 | 0.13 | 42.08 | 60.00 | -17.92 | QP |
| 10 | 5.594 | 17.21 | 0.10 | -9.64 | 0.13 | 27.08 | 50.00 | -22.92 | Average |
| 11 | 15.226 | 23.81 | 0.24 | -9.38 | 0.24 | 33.67 | 60.00 | -26.33 | QP |
| 12 | 15.226 | 8.81 | 0.24 | -9.38 | 0.24 | 18.67 | 50.00 | -31.33 | Average |


Remarks: Level = Read + LISN Factor - Preamp Factor + Cable loss



Shenzhen Certification Technology Service Co., Ltd.
2F, Building B, East Area of Nanchang Second Industrial Zone,
Gushu 2nd Road, Bao'an District, Shenzhen 518126, P.R. China
Tel: 4006786199 Fax: +86-755-26736857
Website: <http://www.cessz.com> Email: Service@cessz.com

Data: 41 File: E:\TEST REPORT\WuXian\YiDong\Conduction CN-1.EM6 (48)

Date: 2013-12-23 Time: 16:07:57




Condition : FCC PART 15 B QP POL: NEUTRAL Temp:24 °C Hum:56 %
 EUT : Flat Computer
 Model No : TS100
 Test Mode : Charging and Data Transmitting
 Power : DC 5V From Adapter AC 120V/60Hz
 Test Engineer: Store
 Remark : STC-A520B-D

| Item | Freq | Read | LISN | Preamp | Cable | Level | Limit | Margin | Remark |
|------|-------|-------|------|--------|-------|--------|--------|--------|---------|
| | | | | | | Factor | Factor | Loss | |
| | MHz | dBuV | dB | dB | dB | | | | |
| 1 | 0.188 | 45.29 | 0.03 | -9.72 | 0.10 | 55.14 | 64.11 | -8.97 | QP |
| 2 | 0.188 | 29.29 | 0.03 | -9.72 | 0.10 | 39.14 | 54.11 | -14.97 | Average |
| 3 | 0.313 | 37.61 | 0.03 | -9.72 | 0.10 | 47.46 | 59.88 | -12.42 | QP |
| 4 | 0.313 | 20.61 | 0.03 | -9.72 | 0.10 | 30.46 | 49.88 | -19.42 | Average |
| 5 | 0.567 | 35.40 | 0.03 | -9.72 | 0.10 | 45.25 | 56.00 | -10.75 | QP |
| 6 | 0.567 | 16.40 | 0.03 | -9.72 | 0.10 | 26.25 | 46.00 | -19.75 | Average |
| 7 | 1.568 | 30.41 | 0.05 | -9.71 | 0.10 | 40.27 | 56.00 | -15.73 | QP |
| 8 | 1.568 | 12.41 | 0.05 | -9.71 | 0.10 | 22.27 | 46.00 | -23.73 | Average |
| 9 | 2.809 | 25.90 | 0.07 | -9.70 | 0.12 | 35.79 | 56.00 | -20.21 | QP |
| 10 | 2.809 | 10.90 | 0.07 | -9.70 | 0.12 | 20.79 | 46.00 | -25.21 | Average |
| 11 | 7.977 | 23.10 | 0.14 | -9.48 | 0.16 | 32.88 | 60.00 | -27.12 | QP |
| 12 | 7.977 | 1.10 | 0.14 | -9.48 | 0.16 | 10.88 | 50.00 | -39.12 | Average |

Remarks: Level = Read + LISN Factor - Preamp Factor + Cable loss



Shenzhen Certification Technology Service Co., Ltd.
2F, Building B, East Area of Nanchang Second Industrial Zone,
Gushu 2nd Road, Bao'an District, Shenzhen 518126, P.R. China
Tel: 4006786199 Fax: +86-755-26736857
Website: <http://www.cessz.com> Email: Service@cessz.com




Condition : FCC PART 15 B QP POL: LINE Temp:24 °C Hum:56 %
 EUT : Flat Computer
 Model No : TS100
 Test Mode : Charging and Data Transmitting
 Power : DC 5V From Adapter AC 120V/60Hz
 Test Engineer: Store
 Remark : STC-A520B-D

| Item | Freq | Read | LISN | Preamp | Cable | Level | Limit | Margin | Remark |
|------|-------|-------|------|--------|-------|--------|--------|--------|---------|
| | | | | | | Factor | Factor | Loss | |
| | MHz | dBuV | dB | dB | dB | | | | |
| 1 | 0.186 | 45.25 | 0.03 | -9.72 | 0.10 | 55.10 | 64.20 | -9.10 | QP |
| 2 | 0.186 | 29.25 | 0.03 | -9.72 | 0.10 | 39.10 | 54.20 | -15.10 | Average |
| 3 | 0.375 | 37.21 | 0.03 | -9.72 | 0.10 | 47.06 | 58.39 | -11.33 | QP |
| 4 | 0.375 | 24.21 | 0.03 | -9.72 | 0.10 | 34.06 | 48.39 | -14.33 | Average |
| 5 | 0.989 | 28.81 | 0.04 | -9.71 | 0.10 | 38.66 | 56.00 | -17.34 | QP |
| 6 | 0.989 | 18.81 | 0.04 | -9.71 | 0.10 | 28.66 | 46.00 | -17.34 | Average |
| 7 | 1.610 | 28.09 | 0.05 | -9.71 | 0.10 | 37.95 | 56.00 | -18.05 | QP |
| 8 | 1.610 | 20.09 | 0.05 | -9.71 | 0.10 | 29.95 | 46.00 | -16.05 | Average |
| 9 | 3.547 | 22.02 | 0.08 | -9.69 | 0.12 | 31.91 | 56.00 | -24.09 | QP |
| 10 | 3.547 | 4.02 | 0.08 | -9.69 | 0.12 | 13.91 | 46.00 | -32.09 | Average |
| 11 | 7.935 | 18.73 | 0.14 | -9.48 | 0.16 | 28.51 | 60.00 | -31.49 | QP |
| 12 | 7.935 | 2.73 | 0.14 | -9.48 | 0.16 | 12.51 | 50.00 | -37.49 | Average |

Remarks: Level = Read + LISN Factor - Preamp Factor + Cable loss



Shenzhen Certification Technology Service Co., Ltd.
2F, Building B, East Area of Nanchang Second Industrial Zone,
Gushu 2nd Road, Bao'an District, Shenzhen 518126, P.R. China
Tel: 4006786199 Fax: +86-755-26736857
Website: <http://www.cessz.com> Email: Service@cessz.com




Condition : FCC PART 15 B QP POL: LINE Temp: 24 °C Hum: 56 %
 EUT : Flat Computer
 Model No : TS100
 Test Mode : Charging and Playing Video
 Power : DC 5V From Adapter AC 120V/60Hz
 Test Engineer: Store
 Remark : STC-A520B-D

| Item | Freq | Read | LISN | Preamp | Cable | Level | Limit | Margin | Remark |
|------|-------|-------|------|--------|-------|--------|--------|--------|---------|
| | | | | | | Factor | Factor | Loss | |
| | MHz | dBuV | dB | dB | dB | | | | |
| 1 | 0.192 | 45.33 | 0.03 | -9.72 | 0.10 | 55.18 | 63.93 | -8.75 | QP |
| 2 | 0.192 | 32.33 | 0.03 | -9.72 | 0.10 | 42.18 | 53.93 | -11.75 | Average |
| 3 | 0.385 | 32.62 | 0.03 | -9.72 | 0.10 | 42.47 | 58.17 | -15.70 | QP |
| 4 | 0.385 | 19.62 | 0.03 | -9.72 | 0.10 | 29.47 | 48.17 | -18.70 | Average |
| 5 | 1.480 | 24.02 | 0.05 | -9.71 | 0.10 | 33.88 | 56.00 | -22.12 | QP |
| 6 | 1.480 | 14.02 | 0.05 | -9.71 | 0.10 | 23.88 | 46.00 | -22.12 | Average |
| 7 | 2.622 | 21.51 | 0.06 | -9.70 | 0.11 | 31.38 | 56.00 | -24.62 | QP |
| 8 | 2.622 | 13.51 | 0.06 | -9.70 | 0.11 | 23.38 | 46.00 | -22.62 | Average |
| 9 | 4.874 | 17.25 | 0.10 | -9.68 | 0.12 | 27.15 | 56.00 | -28.85 | QP |
| 10 | 4.874 | 8.25 | 0.10 | -9.68 | 0.12 | 18.15 | 46.00 | -27.85 | Average |
| 11 | 7.606 | 18.49 | 0.14 | -9.50 | 0.16 | 28.29 | 60.00 | -31.71 | QP |
| 12 | 7.606 | 5.49 | 0.14 | -9.50 | 0.16 | 15.29 | 50.00 | -34.71 | Average |

Remarks: Level = Read + LISN Factor - Preamp Factor + Cable loss



Shenzhen Certification Technology Service Co., Ltd.
2F, Building B, East Area of Nanchang Second Industrial Zone,
Gushu 2nd Road, Bao'an District, Shenzhen 518126, P.R. China
Tel: 4006786199 Fax: +86-755-26736857
Website: <http://www.cessz.com> Email: Service@cessz.com



Condition : FCC PART 15 B QP POL: NEUTRAL Temp:24 °C Hum:56 %
 EUT : Flat Computer
 Model No : TS100
 Test Mode : Charging and Playing Video
 Power : DC 5V From Adapter AC 120V/60Hz
 Test Engineer: Store
 Remark : STC-A520B-D

| Item | Freq | Read | LISN | Preamp | Cable | Level | Limit | Margin | Remark |
|------|-------|-------|------|--------|-------|--------|--------|--------|---------|
| | | | | | | Factor | Factor | Loss | |
| | MHz | dBuV | dB | dB | dB | | | | |
| 1 | 0.192 | 47.45 | 0.03 | -9.72 | 0.10 | 57.30 | 63.93 | -6.63 | QP |
| 2 | 0.192 | 31.45 | 0.03 | -9.72 | 0.10 | 41.30 | 53.93 | -12.63 | Average |
| 3 | 0.256 | 42.32 | 0.03 | -9.72 | 0.10 | 52.17 | 61.56 | -9.39 | QP |
| 4 | 0.256 | 27.32 | 0.03 | -9.72 | 0.10 | 37.17 | 51.56 | -14.39 | Average |
| 5 | 0.447 | 35.85 | 0.03 | -9.72 | 0.10 | 45.70 | 56.93 | -11.23 | QP |
| 6 | 0.447 | 21.85 | 0.03 | -9.72 | 0.10 | 31.70 | 46.93 | -15.23 | Average |
| 7 | 1.535 | 26.75 | 0.05 | -9.71 | 0.10 | 36.61 | 56.00 | -19.39 | QP |
| 8 | 1.535 | 15.75 | 0.05 | -9.71 | 0.10 | 25.61 | 46.00 | -20.39 | Average |
| 9 | 2.809 | 22.78 | 0.07 | -9.70 | 0.12 | 32.67 | 56.00 | -23.33 | QP |
| 10 | 2.809 | 11.78 | 0.07 | -9.70 | 0.12 | 21.67 | 46.00 | -24.33 | Average |
| 11 | 7.606 | 22.53 | 0.14 | -9.50 | 0.16 | 32.33 | 60.00 | -27.67 | QP |
| 12 | 7.606 | 7.53 | 0.14 | -9.50 | 0.16 | 17.33 | 50.00 | -32.67 | Average |

Remarks: Level = Read + LISN Factor - Preamp Factor + Cable loss

4. RADIATED EMISSION TEST

4.1. Test Equipment


| Item | Equipment | Manufacturer | Model No. | Serial No. | Last Cal. | Cal. Interval |
|------|---------------|---------------|-----------|-------------------|-------------|---------------|
| 1 | Test Receiver | Rohde&Schwarz | ESCI | 1166.5950K06-1012 | Oct. 30, 13 | 1 Year |
| 2 | Amplifier | Schwarzbeck | BBV9743 | 9743-019 | Oct. 30, 13 | 1 Year |
| 3 | Bilog Antenna | Schwarzbeck | VULB 9168 | VULB9168-438 | Mar.12, 13 | 1 Year |
| 4 | RF Cable | Schwarzbeck | AK9515E | 95891-2m | Oct. 30, 13 | 1 Year |
| 5 | RF Cable | Schwarzbeck | AK9515E | 95891-11m | Oct. 30, 13 | 1 Year |
| 6 | RF Cable | Schwarzbeck | AK9515E | 95891-0.5m | Oct. 30, 13 | |

For frequency range 1GHz~5GHz (At Semi Anechoic Chamber)


| Item | Equipment | Manufacturer | Model No. | Serial No. | Last Cal. | Cal. Interval |
|------|-------------------|--------------|--------------|------------|-------------|---------------|
| 1 | Spectrum Analyzer | Agilent | E4446A | US44300459 | Oct. 30, 13 | 1 Year |
| 2 | Horn Antenna | EMCO | BBV9743 | 9743-019 | Mar.12, 13 | 1 Year |
| 3 | Amplifier | Schwarzbeck | SCHWARZBEC K | N/A | Oct. 30, 13 | 1 Year |
| 4 | RF Cable | Hubersuhner | SUCOFLEX102 | 28620/2 | Oct. 30, 13 | 1 Year |
| 5 | RF Cable | Hubersuhner | SUCOFLEX102 | 271471/4 | Oct. 30, 13 | 1 Year |
| 6 | RF Cable | Hubersuhner | SUCOFLEX102 | 29086/2 | Oct. 30, 13 | 1 Year |

4.2. Block Diagram of Test Setup

4.2.1. In Semi Anechoic Chamber (3m) Test Setup Diagram for 30MHz~1000MHz



4.2.2. In Semi Anechoic Chamber (3m) Test Setup Diagram for 1-5GHz



4.3. Radiated Emission Limit

| Frequency MHz | Distance (Meters) | Field Strengths Limits dB(μ V)/m |
|------------------|----------------------|--|
| 30 ~ 88 | 3 | 40.0 |
| 88 ~ 216 | 3 | 43.5 |
| 216 ~ 960 | 3 | 46.0 |
| 960 ~ 1000 | 3 | 54.0 |
| 1000 ~ 6000 | 3 | 74(Peak) 54(Average) |

Remark: (1) Emission level = Read level + Antenna Factor + Preamp Factor + Cable Loss
 (2) The smaller limit shall apply at the cross point between two frequency bands.
 (3) Distance is the distance in meters between the measuring instrument, antenna and the closest point of any part of the device or system.

4.4. EUT Configuration on Test

The following equipment are installed on Radiated Emission Test to meet the commission requirements and operating regulations in a manner that tends to maximize its emission characteristics in normal application.

4.4.1. Support Equipments : As Tested Supporting System Detail, in Section 2.2.

4.5. Operating Condition of EUT

- 4.5.1. Setup the EUT as shown in Section 4.2.
- 4.5.2. Turn on the power of all equipment.
- 4.5.3. Let the EUT work in test mode (ON) and test it.

4.6. Test Procedure

The EUT was placed on a non-metallic table, 80 cm above the ground plane inside a semi-anechoic chamber. An antenna was located 3m from the EUT on an adjustable mast. A pre-scan was first performed in order to find prominent radiated emissions. For final emissions measurements at each frequency of interest, the EUT were rotated and the antenna height was varied between 1m and 4m in order to maximize the emission. Measurements in both horizontal and vertical polarities were made and the data was recorded. In order to find the maximum emission, the relative positions of equipments and all of the interface cables were changed according to ANSI C63.4-2003 on Radiated Emission test.

The bandwidth setting on the test receiver (ROHDE&SCHWARZ TEST RECEIVER ESCI) is 120 kHz.

The resolution bandwidth of the Agilent Spectrum Analyzer E4446A was set at 1MHz. (For above 1GHz)

The frequency range from 30MHz to 1000MHz was pre-scanned with a peak detector and all final readings of measurement from Test Receiver are Quasi-Peak values.

The frequency range from 1GHz to 5GHz was checked with peak and average detector, measurement distance is 3m in 3m chamber.

Finally, selected operating situations at Anechoic Chamber measurement, all the test results are listed in section 4.7.

4.7. Radiated Disturbance Test Results

PASS. (All emissions not reported below are too low against the prescribed limits.)

For frequency range 30MHz~6000MHz

The EUT with the following test mode was tested and read Q.P values, all the test results listed in next pages.


Temperature: 25.2°C Humidity: 56%

The details of test mode is as follows :

| NO. | Test Mode |
|-----|--|
| 1. | Charge And Data Transmitting for adapter 1 |
| 2. | Charge And Play Video for adapter 1 |
| 3. | Charge And Data Transmitting for adapter 2 |
| 4. | Charge And Play Video for adapter 2 |




Shenzhen Certification Technology Service Co., Ltd.
2F, Building B, East Area of Nanchang Second Industrial Zone
Gushu, 2nd Road, Bao'an District, Shenzhen 518126, P.R. China
Tel: 400





Shenzhen Certification Technology Service Co., Ltd.
2F, Building B, East Area of Nanchang Second Industrial Zone
Gushu 2nd Road, Bao'an District, Shenzhen 518126, P.R. China
Tel: 4006786199 FAX: +86-755-26736857
Website: <http://www.cessz.com> Email: Service@cessz.com

Data: 2




Condition : FCC PART 15 B 3m POL: VERTICAL
 EUT : Flat Computer
 Model No : TS100
 Test Mode : Charging And Playing Video
 Power : DC 5V From Adapter AC 120V/60Hz
 Test Engineer : Store
 Remark : WRP2U-050200C
 Temp : 24.2°C
 Hum : 50%

| Item | Freq | Read | Antenna | Preamp | Cable | Level | Limit | Margin | Remark |
|------|--------|-------|---------|--------|-------|-------|-------|--------|--------|
| | | Level | Factor | Factor | Loss | | | | |
| | MHz | dBuV | dB | dB | dB | dBuV | dBuV | dBuV | |
| 1 | 41.57 | 37.62 | 13.93 | 27.81 | 0.19 | 23.93 | 40.00 | -16.07 | QP |
| 2 | 58.00 | 37.76 | 12.91 | 27.86 | 0.23 | 23.04 | 40.00 | -16.96 | QP |
| 3 | 122.40 | 49.61 | 12.35 | 26.88 | 0.43 | 35.51 | 43.50 | -7.99 | QP |
| 4 | 239.99 | 44.80 | 11.45 | 27.09 | 0.53 | 29.69 | 46.00 | -16.31 | QP |
| 5 | 510.04 | 36.51 | 16.68 | 27.64 | 0.68 | 26.23 | 46.00 | -19.77 | QP |
| 6 | 721.73 | 41.45 | 19.92 | 27.73 | 1.26 | 34.90 | 46.00 | -11.10 | QP |

Remark: Level = Read Level + Antenna Factor - Preamp Factor + Cable Loss



Shenzhen Certification Technology Service Co., Ltd.
 2F, Building B, East Area of Nanchang Second Industrial Zone,
 Gushu 2nd Road, Bao'an District, Shenzhen 518126, P.R. China
 Tel: 4006786199 FAX: +86-755-26736857
 Website: <http://www.cessz.com> Email: Service@cessz.com




Condition : FCC PART 15_18G PEAK 3m POL: VERTICAL
 EUT : Flat Computer
 Model No : TS100
 Test Mode : Charging And Playing Video
 Power : DC 5V From Adapter AC 120V/60Hz
 Test Engineer : Store
 Remark : WRP2U-050200C
 Temp : 24.2°C
 Hum : 50%

| Item | Freq | Read | Antenna | Preamp | Cable | Level | Limit | Margin | Remark |
|------|---------|-------|---------|--------|------------|-------|-------|--------|---------|
| | | Level | Factor | Factor | Cable Loss | dBuV | dBuV | dBuV | |
| | MHz | dBuV | dB | dB | dB | | | | |
| 1 | 1195.00 | 55.47 | 24.32 | 34.90 | 2.31 | 47.20 | 54.00 | -6.80 | Average |
| 2 | 1195.00 | 68.47 | 24.32 | 34.90 | 2.31 | 60.20 | 74.00 | -13.80 | Peak |
| 3 | 1780.00 | 58.89 | 24.92 | 34.83 | 3.38 | 52.36 | 74.00 | -21.64 | Peak |
| 4 | 2375.00 | 50.94 | 27.65 | 34.97 | 3.91 | 47.53 | 54.00 | -6.47 | Average |
| 5 | 2375.00 | 58.94 | 27.65 | 34.97 | 3.91 | 55.53 | 74.00 | -18.47 | Peak |
| 6 | 2770.00 | 55.19 | 27.89 | 34.98 | 4.23 | 52.33 | 74.00 | -21.67 | Peak |
| 7 | 3475.00 | 50.76 | 28.40 | 34.91 | 4.83 | 49.08 | 54.00 | -4.92 | Average |
| 8 | 3475.00 | 55.76 | 28.40 | 34.91 | 4.83 | 54.08 | 74.00 | -19.92 | Peak |
| 9 | 4335.00 | 48.05 | 30.23 | 34.53 | 5.39 | 49.14 | 74.00 | -24.86 | Peak |

Remark: Level = Read Level + Antenna Factor - Preamp Factor + Cable Loss



Shenzhen Certification Technology Service Co., Ltd.
 2F, Building B, East Area of Nanchang Second Industrial Zone,
 Gushu 2nd Road, Bao'an District, Shenzhen 518126, P.R. China
 Tel: 4006786199 FAX: +86-755-26736857
 Website: <http://www.cessz.com> Email: Service@cessz.com




Condition : FCC PART 15_18G PEAK 3m POL: HORIZONTAL
 EUT : Flat Computer
 Model No : TS100
 Test Mode : Charging And Playing Video
 Power : DC 5V From Adapter AC 120V/60Hz
 Test Engineer : Store
 Remark : WRP2U-050200C
 Temp : 24.2°C
 Hum : 50%

| Item | Freq | Read | Antenna | Preamp | Cable | Level | Limit | Margin | Remark |
|------|---------|-------|---------|--------|-------|-------|-------|--------|---------|
| | | Level | Factor | Factor | Cable | dBuV | dBuV | dBuV | |
| | MHz | dBuV | dB | dB | Loss | | | | |
| 1 | 1190.00 | 56.49 | 24.32 | 34.90 | 2.31 | 48.22 | 54.00 | -5.78 | Average |
| 2 | 1190.00 | 62.49 | 24.32 | 34.90 | 2.31 | 54.22 | 74.00 | -19.78 | Peak |
| 3 | 1865.00 | 56.91 | 25.22 | 34.87 | 3.50 | 50.76 | 74.00 | -23.24 | Peak |
| 4 | 2375.00 | 57.13 | 27.65 | 34.97 | 3.91 | 53.72 | 74.00 | -20.28 | Peak |
| 5 | 2640.00 | 50.00 | 27.79 | 34.98 | 4.13 | 46.94 | 54.00 | -7.06 | Average |
| 6 | 2640.00 | 59.00 | 27.79 | 34.98 | 4.13 | 55.94 | 74.00 | -18.06 | Peak |
| 7 | 3405.00 | 55.38 | 27.89 | 34.92 | 4.77 | 53.12 | 74.00 | -20.88 | Peak |
| 8 | 4200.00 | 49.60 | 29.99 | 34.60 | 5.31 | 50.30 | 74.00 | -23.70 | Peak |

Remark: Level = Read Level + Antenna Factor - Preamp Factor + Cable Loss



Shenzhen Certification Technology Service Co., Ltd.
 2F, Building B, East Area of Nanchang Second Industrial Zone,
 Gushu 2nd Road, Bao'an District, Shenzhen 518126, P.R. China
 Tel: 4006786199 FAX: +86-755-26736857
 Website: <http://www.cessz.com> Email: Service@cessz.com




Condition : FCC PART 15 B 3m POL: VERTICAL
 EUT : Flat Computer
 Model No : TS100
 Test Mode : Charging And Data Transmitting
 Power : DC 5V From Adapter AC 120V/60Hz
 Test Engineer : Store
 Remark : WRP2U-050200C
 Temp : 21.2°C
 Hum : 45%

| Item | Freq | Read | Antenna | Preamp | Cable | Level | Limit | Margin | Remark |
|------|--------|-------|---------|--------|-------|-------|-------|--------|--------|
| | | Level | Factor | Factor | Cable | dBuV | dBuV | dBuV | |
| | MHz | dBuV | dB | dB | Loss | | | | |
| 1 | 32.98 | 36.67 | 13.33 | 27.58 | 0.11 | 22.53 | 40.00 | -17.47 | QP |
| 2 | 71.83 | 42.98 | 10.51 | 26.77 | 0.19 | 26.91 | 40.00 | -13.09 | QP |
| 3 | 157.56 | 48.62 | 14.15 | 26.91 | 0.39 | 36.25 | 43.50 | -7.25 | QP |
| 4 | 299.32 | 43.61 | 12.80 | 27.19 | 0.69 | 29.91 | 46.00 | -16.09 | QP |
| 5 | 601.43 | 44.81 | 18.36 | 27.82 | 1.07 | 36.42 | 46.00 | -9.58 | QP |
| 6 | 958.79 | 40.37 | 22.16 | 27.61 | 1.97 | 36.89 | 46.00 | -9.11 | QP |

Remark: Level = Read Level + Antenna Factor - Preamp Factor + Cable Loss



Shenzhen Certification Technology Service Co., Ltd.
 2F, Building B, East Area of Nanchang Second Industrial Zone,
 Gushu 2nd Road, Bao'an District, Shenzhen 518126, P.R. China
 Tel: 4006786199 FAX: +86-755-26736857
 Website: <http://www.cessz.com> Email: Service@cessz.com



Condition : FCC PART 15 B 3m POL: HORIZONTAL
 EUT : Flat Computer
 Model No : TS100
 Test Mode : Charging And Data Transmitting
 Power : DC 5V From Adapter AC 120V/60Hz
 Test Engineer : Store
 Remark : WRP2U-050200C
 Temp : 21.2°C
 Hum : 45%

| Item | Freq | Read | Antenna | Preamp | Cable | Level | Limit | Margin | Remark |
|------|--------|-------|---------|--------|------------|-------|-------|--------|--------|
| | | Level | Factor | Factor | Cable Loss | dBuV | dBuV | dBuV | |
| | MHz | dBuV | dB | dB | dB | | | | |
| 1 | 98.83 | 46.98 | 10.15 | 26.84 | 0.38 | 30.67 | 43.50 | -12.83 | QP |
| 2 | 131.76 | 46.89 | 12.79 | 26.89 | 0.57 | 33.36 | 43.50 | -10.14 | QP |
| 3 | 150.01 | 45.07 | 14.16 | 26.91 | 0.39 | 32.71 | 43.50 | -10.79 | QP |
| 4 | 299.32 | 51.26 | 12.80 | 27.19 | 0.69 | 37.56 | 46.00 | -8.44 | QP |
| 5 | 451.14 | 43.71 | 15.99 | 27.49 | 1.08 | 33.29 | 46.00 | -12.71 | QP |
| 6 | 760.70 | 42.63 | 20.38 | 27.67 | 1.45 | 36.79 | 46.00 | -9.21 | QP |


Remark: Level = Read Level + Antenna Factor - Preamp Factor + Cable Loss



Shenzhen Certification Technology Service Co., Ltd.
2F, Building B, East Area of Nanchang Second Industrial Zone,
Gushu 2nd Road, Bao'an District, Shenzhen 518126, P.R. China
Tel: 4006786199 FAX: +86-755-26736857
Website: <http://www.cessz.com> Email: Service@cessz.com


Data: 1 File: E:\REPORT DATA\WuXian\YiDong\RE 12.24.EM6 (10)

Level (dBuV/m) Date: 2014-01-08 Time: 15:37:34





Shenzhen Certification Technology Service Co., Ltd.
 2F, Building B, East Area of Nanchang Second Industrial Zone,
 Gushu 2nd Road, Bao'an District, Shenzhen 518126, P.R. China
 Tel: 4006786199 FAX: +86-755-26736857
 Website: <http://www.cessz.com> Email: Service@cessz.com



Condition : FCC PART 15_18G PEAK 3m POL: HORIZONTAL
 EUT : Flat Computer
 Model No : TS100
 Test Mode : Charging And Data Transmitting
 Power : DC 5V From Adapter AC 120V/60Hz
 Test Engineer : Store
 Remark : WRP2U-050200C
 Temp : 24.2°C
 Hum : 50%


| Item | Freq | Read | Antenna | Preamp | Cable | Level | Limit | Margin | Remark |
|------|---------|-------|---------|--------|-------|-------|-------|--------|---------|
| | | Level | Factor | Factor | Cable | dBuV | dBuV | dBuV | |
| | MHz | dBuV | dB | dB | Loss | | | | |
| 1 | 1190.00 | 56.49 | 24.32 | 34.90 | 2.31 | 48.22 | 54.00 | -5.78 | Average |
| 2 | 1190.00 | 64.49 | 24.32 | 34.90 | 2.31 | 56.22 | 74.00 | -17.78 | Peak |
| 3 | 1720.00 | 51.82 | 24.74 | 34.80 | 3.28 | 45.04 | 74.00 | -28.96 | Peak |
| 4 | 1980.00 | 54.19 | 25.80 | 34.93 | 3.60 | 48.66 | 74.00 | -25.34 | Peak |
| 5 | 2770.00 | 48.90 | 27.89 | 34.98 | 4.23 | 46.04 | 54.00 | -7.96 | Average |
| 6 | 2770.00 | 60.90 | 27.89 | 34.98 | 4.23 | 58.04 | 74.00 | -15.96 | Peak |
| 7 | 3165.00 | 50.28 | 28.28 | 34.96 | 4.56 | 48.16 | 74.00 | -25.84 | Peak |

Remark: Level = Read Level + Antenna Factor - Preamp Factor + Cable Loss



Shenzhen Certification Technology Service Co., Ltd.
 2F, Building B, East Area of Nanchang Second Industrial Zone,
 Gushu 2nd Road, Bao'an District, Shenzhen 518126, P.R. China
 Tel: 4006786199 FAX: +86-755-26736857
 Website: <http://www.cessz.com> Email: Service@cessz.com

Data: 7 File: E:\REPORT DATA\WuXian\YiDong\RE 12.24-D.EM6_(10)




Condition : FCC PART 15 B 3m POL: HORIZONTAL
 EUT : Flat Computer
 Model No : TS100
 Test Mode : Charging And Playing Video
 Power : DC 5V From Adapter AC 120V/60Hz
 Test Engineer : Store
 Remark : STC-A520B-D
 Temp : 21.2°C
 Hum : 45%

| Item | Freq | Read | Antenna | Preamp | Cable | Level | Limit | Margin | Remark |
|------|--------|-------|---------|--------|------------|-------|-------|--------|--------|
| | | Level | Factor | Factor | Cable Loss | dBuV | dBuV | dBuV | |
| | MHz | dBuV | dB | dB | dB | | | | |
| 1 | 71.83 | 38.51 | 10.51 | 26.77 | 0.19 | 22.44 | 40.00 | -17.56 | QP |
| 2 | 143.83 | 44.87 | 13.77 | 26.90 | 0.38 | 32.12 | 43.50 | -11.38 | QP |
| 3 | 216.02 | 45.75 | 10.41 | 27.05 | 0.55 | 29.66 | 46.00 | -16.34 | QP |
| 4 | 397.63 | 45.99 | 14.71 | 27.42 | 0.71 | 33.99 | 46.00 | -12.01 | QP |
| 5 | 560.69 | 45.67 | 17.56 | 27.73 | 1.05 | 36.55 | 46.00 | -9.45 | QP |
| 6 | 890.73 | 40.73 | 21.53 | 27.65 | 1.28 | 35.89 | 46.00 | -10.11 | QP |

Remark: Level = Read Level + Antenna Factor - Preamp Factor + Cable Loss



Shenzhen Certification Technology Service Co., Ltd.
2F, Building B, East Area of Nanchang Second Industrial Zone,
Gushu 2nd Road, Bao'an District, Shenzhen 518126, P.R. China
Tel: 4006786199 FAX: +86-755-26736857
Website: <http://www.cessz.com> Email: Service@cessz.com




Condition : FCC PART 15 B 3m POL: VERTICAL
 EUT : Flat Computer
 Model No : TS100
 Test Mode : Charging And Playing Video
 Power : DC 5V From Adapter AC 120V/60Hz
 Test Engineer : Store
 Remark : STC-A520B-D
 Temp : 21.2°C
 Hum : 45%

| Item | Freq | Read | Antenna | Preamp | Cable | Level | Limit | Margin | Remark |
|------|--------|-------|---------|--------|------------|-------|-------|--------|--------|
| | | Level | Factor | Factor | Cable Loss | dBuV | dBuV | dBuV | |
| | MHz | dBuV | dB | dB | dB | | | | |
| 1 | 53.88 | 43.96 | 13.22 | 27.84 | 0.21 | 29.55 | 40.00 | -10.45 | QP |
| 2 | 71.83 | 47.36 | 10.51 | 26.77 | 0.19 | 31.29 | 40.00 | -8.71 | QP |
| 3 | 143.83 | 38.40 | 13.77 | 26.90 | 0.38 | 25.65 | 43.50 | -17.85 | QP |
| 4 | 396.24 | 43.08 | 14.68 | 27.42 | 0.75 | 31.09 | 46.00 | -14.91 | QP |
| 5 | 627.27 | 45.63 | 18.82 | 27.82 | 0.98 | 37.61 | 46.00 | -8.39 | QP |
| 6 | 760.70 | 42.19 | 20.38 | 27.67 | 1.45 | 36.35 | 46.00 | -9.65 | QP |

Remark: Level = Read Level + Antenna Factor - Preamp Factor + Cable Loss



Shenzhen Certification Technology Service Co., Ltd.
 2F, Building B, East Area of Nanchang Second Industrial Zone,
 Gushu 2nd Road, Bao'an District, Shenzhen 518126, P.R. China
 Tel: 4006786199 FAX: +86-755-26736857
 Website: <http://www.cessz.com> Email: Service@cessz.com




Condition : FCC PART 15_18G PEAK 3m POL: VERTICAL
 EUT : Flat Computer
 Model No : TS100
 Test Mode : Charging And Playing Video
 Power : DC 5V From Adapter AC 120V/60Hz
 Test Engineer : Store
 Remark : STC-A520B-D
 Temp : 24.2°C
 Hum : 50%

| Item | Freq | Read | Antenna | Preamp | Cable | Level | Limit | Margin | Remark |
|------|---------|-------|---------|--------|------------|-------|-------|--------|---------|
| | | Level | Factor | Factor | Cable Loss | dBuV | dBuV | dBuV | |
| | MHz | dBuV | dB | dB | dB | | | | |
| 1 | 1185.00 | 56.46 | 24.32 | 34.90 | 2.28 | 48.16 | 54.00 | -5.84 | Average |
| 2 | 1185.00 | 65.46 | 24.32 | 34.90 | 2.28 | 57.16 | 74.00 | -16.84 | Peak |
| 3 | 1780.00 | 54.69 | 24.92 | 34.83 | 3.38 | 48.36 | 54.00 | -5.64 | Average |
| 4 | 1780.00 | 59.89 | 24.92 | 34.83 | 3.38 | 53.36 | 74.00 | -20.64 | Peak |
| 5 | 2885.00 | 55.25 | 28.00 | 34.98 | 4.34 | 52.61 | 74.00 | -21.39 | Peak |
| 6 | 3475.00 | 49.76 | 28.40 | 34.91 | 4.83 | 48.08 | 54.00 | -5.92 | Average |
| 7 | 3475.00 | 56.76 | 28.40 | 34.91 | 4.83 | 55.08 | 74.00 | -18.92 | Peak |
| 8 | 3720.00 | 50.95 | 28.93 | 34.83 | 5.00 | 50.05 | 74.00 | -23.95 | Peak |
| 9 | 4335.00 | 48.05 | 30.23 | 34.53 | 5.39 | 49.14 | 74.00 | -24.86 | Peak |

Remark: Level = Read Level + Antenna Factor - Preamp Factor + Cable Loss



Shenzhen Certification Technology Service Co., Ltd.
 2F, Building B, East Area of Nanchang Second Industrial Zone,
 Gushu 2nd Road, Bao'an District, Shenzhen 518126, P.R. China
 Tel: 4006786199 FAX: +86-755-26736857
 Website: <http://www.cessz.com> Email: Service@cessz.com




Condition : FCC PART 15_18G PEAK 3m POL: HORIZONTAL
 EUT : Flat Computer
 Model No : TS100
 Test Mode : Charging And Playing Video
 Power : DC 5V From Adapter AC 120V/60Hz
 Test Engineer : Store
 Remark : STC-A520B-D
 Temp : 24.2°C
 Hum : 50%

| Item | Freq | Read | Antenna | Preamp | Cable | Level | Limit | Margin | Remark |
|------|---------|-------|---------|--------|------------|-------|-------|--------|---------|
| | | Level | Factor | Factor | Cable Loss | dBuV | dBuV | dBuV | |
| | MHz | dBuV | dB | dB | dB | | | | |
| 1 | 1190.00 | 54.49 | 24.32 | 34.90 | 2.31 | 46.22 | 54.00 | -7.78 | Average |
| 2 | 1190.00 | 65.49 | 24.32 | 34.90 | 2.31 | 57.22 | 74.00 | -16.78 | Peak |
| 3 | 1980.00 | 58.19 | 25.80 | 34.93 | 3.60 | 52.66 | 74.00 | -21.34 | Peak |
| 4 | 2375.00 | 55.13 | 27.65 | 34.97 | 3.91 | 51.72 | 74.00 | -22.28 | Peak |
| 5 | 2770.00 | 50.90 | 27.89 | 34.98 | 4.23 | 48.04 | 54.00 | -5.96 | Average |
| 6 | 2770.00 | 57.90 | 27.89 | 34.98 | 4.23 | 55.04 | 74.00 | -16.96 | Peak |
| 7 | 3405.00 | 50.38 | 27.89 | 34.92 | 4.77 | 48.12 | 54.00 | -5.88 | Average |
| 8 | 3405.00 | 56.38 | 27.89 | 34.92 | 4.77 | 54.12 | 74.00 | -19.88 | Peak |
| 9 | 4320.00 | 49.35 | 30.20 | 34.54 | 5.39 | 50.40 | 74.00 | -23.60 | Peak |

Remark: Level = Read Level + Antenna Factor - Preamp Factor + Cable Loss



Shenzhen Certification Technology Service Co., Ltd.
 2F, Building B, East Area of Nanchang Second Industrial Zone,
 Gushu 2nd Road, Bao'an District, Shenzhen 518126, P.R. China
 Tel: 4006786199 FAX: +86-755-26736857
 Website: <http://www.cessz.com> Email: Service@cessz.com




Condition : FCC PART 15 B 3m POL: HORIZONTAL
 EUT : Flat Computer
 Model No : TS100
 Test Mode : Charging And Data Transmitting
 Power : DC 5V From Adapter AC 120V/60Hz
 Test Engineer : Store
 Remark : STC-A520B-D
 Temp : 21.2°C
 Hum : 45%

| Item | Freq | Read | Antenna | Preamp | Cable | Level | Limit | Margin | Remark |
|------|--------|-------|---------|--------|------------|-------|-------|--------|--------|
| | | Level | Factor | Factor | Cable Loss | dBuV | dBuV | dBuV | |
| | MHz | dBuV | dB | dB | dB | | | | |
| 1 | 41.71 | 36.04 | 13.93 | 27.81 | 0.19 | 22.35 | 40.00 | -17.65 | QP |
| 2 | 143.83 | 41.87 | 13.77 | 26.90 | 0.38 | 29.12 | 43.50 | -14.38 | QP |
| 3 | 287.99 | 48.92 | 12.54 | 27.17 | 0.66 | 34.95 | 46.00 | -11.05 | QP |
| 4 | 397.63 | 50.99 | 14.71 | 27.42 | 0.71 | 38.99 | 46.00 | -7.01 | QP |
| 5 | 560.69 | 47.67 | 17.56 | 27.73 | 1.05 | 38.55 | 46.00 | -7.45 | QP |
| 6 | 890.73 | 43.73 | 21.53 | 27.65 | 1.28 | 38.89 | 46.00 | -7.11 | QP |

Remark: Level = Read Level + Antenna Factor - Preamp Factor + Cable Loss



Shenzhen Certification Technology Service Co., Ltd.
 2F, Building B, East Area of Nanchang Second Industrial Zone,
 Gushu 2nd Road, Bao'an District, Shenzhen 518126, P.R. China
 Tel: 4006786199 FAX: +86-755-26736857
 Website: <http://www.cessz.com> Email: Service@cessz.com




Condition : FCC PART 15 B 3m POL: VERTICAL
 EUT : Flat Computer
 Model No : TS100
 Test Mode : Charging And Data Transmitting
 Power : DC 5V From Adapter AC 120V/60Hz
 Test Engineer : Store
 Remark : STC-A520B-D
 Temp : 21.2°C
 Hum : 45%

| Item | Freq | Read | Antenna | Preamp | Cable | Level | Limit | Margin | Remark |
|------|--------|-------|---------|--------|------------|-------|-------|--------|--------|
| | | Level | Factor | Factor | Cable Loss | dBuV | dBuV | dBuV | |
| | MHz | dBuV | dB | dB | dB | | | | |
| 1 | 32.98 | 40.10 | 13.33 | 27.58 | 0.11 | 25.96 | 40.00 | -14.04 | QP |
| 2 | 67.20 | 47.82 | 11.21 | 26.98 | 0.28 | 32.33 | 40.00 | -7.67 | QP |
| 3 | 143.83 | 48.40 | 13.77 | 26.90 | 0.38 | 35.65 | 43.50 | -7.85 | QP |
| 4 | 287.99 | 43.87 | 12.54 | 27.17 | 0.66 | 29.90 | 46.00 | -16.10 | QP |
| 5 | 396.24 | 46.08 | 14.68 | 27.42 | 0.75 | 34.09 | 46.00 | -11.91 | QP |
| 6 | 627.27 | 45.63 | 18.82 | 27.82 | 0.98 | 37.61 | 46.00 | -8.39 | QP |

Remark: Level = Read Level + Antenna Factor - Preamp Factor + Cable Loss



Shenzhen Certification Technology Service Co., Ltd.
2F, Building B, East Area of Nanchang Second Industrial Zone,
Gushu 2nd Road, Bao'an District, Shenzhen 518126, P.R. China
Tel: 4006786199 FAX: +86-755-26736857
Website: <http://www.cessz.com> Email: Service@cessz.com




Condition : FCC PART 15_18G PEAK 3m POL: VERTICAL
 EUT : Flat Computer
 Model No : TS100
 Test Mode : Charging And Data Transmitting
 Power : DC 5V From Adapter AC 120V/60Hz
 Test Engineer : Store
 Remark : STC-A520B-D
 Temp : 24.2°C
 Hum : 50%

| Item | Freq | Read | Antenna | Preamp | Cable | Level | Limit | Margin | Remark |
|------|---------|-------|---------|--------|------------|-------|-------|--------|---------|
| | | Level | Factor | Factor | Cable Loss | dBuV | dBuV | dBuV | |
| | MHz | dBuV | dB | dB | dB | | | | |
| 1 | 1185.00 | 57.46 | 24.32 | 34.90 | 2.28 | 49.16 | 54.00 | -4.84 | Average |
| 2 | 1185.00 | 65.46 | 24.32 | 34.90 | 2.28 | 57.16 | 74.00 | -16.84 | Peak |
| 3 | 1980.00 | 52.52 | 25.80 | 34.93 | 3.60 | 46.99 | 54.00 | -7.01 | Average |
| 4 | 1980.00 | 62.52 | 25.80 | 34.93 | 3.60 | 56.99 | 74.00 | -17.01 | Peak |
| 5 | 2780.00 | 50.18 | 27.90 | 34.98 | 4.25 | 47.35 | 54.00 | -6.65 | Average |
| 6 | 2780.00 | 58.18 | 27.90 | 34.98 | 4.25 | 55.35 | 74.00 | -18.65 | Peak |
| 7 | 3565.00 | 50.86 | 28.69 | 34.90 | 4.90 | 49.55 | 74.00 | -24.45 | Peak |
| 8 | 4105.00 | 47.38 | 29.86 | 34.65 | 5.25 | 47.84 | 74.00 | -26.16 | Peak |
| 9 | 4755.00 | 43.86 | 31.18 | 34.25 | 5.67 | 46.46 | 74.00 | -27.54 | Peak |

Remark: Level = Read Level + Antenna Factor - Preamp Factor + Cable Loss



Shenzhen Certification Technology Service Co., Ltd.
 2F, Building B, East Area of Nanchang Second Industrial Zone,
 Gushu 2nd Road, Bao'an District, Shenzhen 518126, P.R. China
 Tel: 4006786199 FAX: +86-755-26736857
 Website: <http://www.cessz.com> Email: Service@cessz.com



Condition : FCC PART 15_18G PEAK 3m POL: HORIZONTAL
 EUT : Flat Computer
 Model No : TS100
 Test Mode : Charging And Data Transmitting
 Power : DC 5V From Adapter AC 120V/60Hz
 Test Engineer : Store
 Remark : STC-A520B-D
 Temp : 24.2°C
 Hum : 50%

| Item | Freq | Read | Antenna | Preamp | Cable | Level | Limit | Margin | Remark |
|------|---------|-------|---------|--------|------------|-------|-------|--------|---------|
| | | Level | Factor | Factor | Cable Loss | dBuV | dBuV | dBuV | |
| | MHz | dBuV | dB | dB | dB | | | | |
| 1 | 1190.00 | 57.49 | 24.32 | 34.90 | 2.31 | 49.22 | 54.00 | -4.78 | Average |
| 2 | 1190.00 | 68.49 | 24.32 | 34.90 | 2.31 | 60.22 | 74.00 | -13.78 | Peak |
| 3 | 1585.00 | 59.44 | 24.87 | 34.75 | 3.05 | 52.61 | 74.00 | -21.39 | Peak |
| 4 | 1980.00 | 56.19 | 25.80 | 34.93 | 3.60 | 50.66 | 54.00 | -3.34 | Average |
| 5 | 1980.00 | 61.19 | 25.80 | 34.93 | 3.60 | 55.66 | 74.00 | -18.34 | Peak |
| 6 | 2375.00 | 52.13 | 27.65 | 34.97 | 3.91 | 48.72 | 54.00 | -5.28 | Average |
| 7 | 2375.00 | 59.13 | 27.65 | 34.97 | 3.91 | 55.72 | 74.00 | -18.28 | Peak |
| 8 | 2770.00 | 50.90 | 27.89 | 34.98 | 4.23 | 48.04 | 54.00 | -5.96 | Average |
| 9 | 2770.00 | 63.90 | 27.89 | 34.98 | 4.23 | 61.04 | 74.00 | -12.96 | Peak |
| 10 | 3165.00 | 55.28 | 28.28 | 34.96 | 4.56 | 53.16 | 74.00 | -20.84 | Peak |

Remark: Level = Read Level + Antenna Factor - Preamp Factor + Cable Loss

5. PHOTOGRAPH

5.1.Photos of Power Line Conducted Emission Test




Adapter 1




Adapter 2


5.2.Photos of Radiated Emission Test (In Anechoic Chamber)



Adapter 1



Adapter 1



Adapter 2



Adapter 2

6. PHOTOS OF THE EUT



**Full View
(SCT-A520B-D)**




**Full View
(WRP2U-050200C)**



Front View



Rear View



Top View



Bottom View



Left View




Right View




Inside View



Inside View




Inside View




Inside View



Inside View



Inside View



-----THE END OF REPORT-----