

---

## **USER'S MANUAL**

### **1. FRS PRODUCT DESCRIPTION**

The Family Radio Service ( FRS ) is the newest generation in personal two - way communications. FRS radios operate in a license - free band, on one of 2 license -free channels.

The FR-200 is a lightweight, palmsized two - way radio that you can carry almost anywhere - use it at shopping malls, sporting events, amusement parks, or any other activity where communications are needed for convenience or safety.

The radio provides about a 2miles range of communications - allowing you to keep in touch with family, friends or a neighborhood watch group.

The FR-200 is two channels model. You can talk to another person using any FRS radio, provided that you can on the same frequency with button.

## 2. CONTROLS AND FUNCTIONS

- > Push-To Talk button - Permits radio transmissions
- > Monitor button – Monitoring in the channel
- > Power button - Used to turn the radio on/off
- > Volume up/down button – Used to adjust the listening volume
- > Call button – Used to send a call signal in emergency condition
- > Channel select switch – Selects other channel
- > Red L.E.D – Lights in transmission
- > Green L.E.D – Lights in low-battery
- > Antenna
- > Belt Clip - Used to secure the radio to a belt, or another convenient location.
- > Battery Compartment - Houses 4 AAA size batteries which provide power to the unit.(Located on back of unit)

---

### 3. OPERATING INSTRUCTIONS

> Install 4 new AAA size batteries,

The (-) flat bottom of the battery rests on the (-) terminal of the battery compartment, and the (+) top contacts the (+) terminal. Refer to drawing below for proper battery installation.

Note: Always release batteries if product will not be used for long periods of time.

> Replace the battery compartment door.

> Push the power button.

The radio will sound a melody tone.

> To transmit,

Hold the radio 2-3 inches from your mouth, Press the Push-To-Talk button on the radio side, and speak clearly into the microphone area of the radio. For best quality, Speak slowly and to a normal tone of voice. There is no need to speak loudly.

> When your transmission is complete,

Release the PTT button and listen for a reply.

> To send a call,

Press call button to page someone in special situation, then turn red L.E.D on and has audible ring signal transmitted.

> Low battery indication

Battery voltage drop to below fixed voltage, then green L.E.D is blinking.

> Channel selection

This Radio has two channel and could be selected by slide switch.

> When not using the radio,

Conserve battery power by turning the unit off. Push the Power button.