

2.4GHz FHHS DIGITAL Transmitter/Docking

MODEL: I S- 0 8NT/NR

USA VERSION

Parts Lists

IS-08N BASE(Docking) PARTS LIST					
NO.	PART	LOCATION		Q'TY	
	ASS'Y / SET			1.0	
		작성일자 : 2007. FEB. 27			
		REV : 02			
	Transmitter Ass'Y				
BASE MAIN	Base Main PCB			1.0	
	KT24 TR antenna			2.0	
	HEAD,CONN,53014-11,11PIN,2M/M,ST,MOLEX	J5		1.0	
	CVM MODULE	U3		1.0	
	RES,CHIP,152,J,1608,1/16W	R6,R21		2.0	
	RES,CHIP,100,J,1608,1/16W	R28		1.0	
	RES,CHIP,104,J,1608,1/16W	R1,R22		2.0	
	RES,CHIP,103,J,1608,1/16W	R20,R29,R30		3.0	
	RES,CHIP,102,J,1608,1/16W	R3,R4,R23,R24		4.0	
	RES,CHIP,332,J,1608,1/16W	R7		1.0	
	RES,CHIP,331,J,1608,1/16W	R41,R42		2.0	
	ALUMINUM CAP, BLA 16 VC 47 M F60 TP (47uF/6V)	C1		1.0	
	Tantal 1uF/6.3V A TYPE	C17		1.0	
	Tantal 100uF/6.3V C TYPE	C3		1.0	
	CAP,CHIP,102K,1608,50V X7R	C4		1.0	
	CAP,CHIP,104Z,1608,16V/Y5V	C2,C5,C20,C21		4.0	
	CAP,CHIP,5R6,C,1608,50V/COG	C18,C19,C27,C28,C29,C30,C31,C32,C15,C22		10.0	
	DIODE ZENER 4.7V SMD	D8,D9		2.0	
	DIODE RF PINDIODE BAR64V-02V GS08	D10,D11		2.0	
	IC REG LM117MPX	U1		1.0	
	CPU, ATMEGA48V10AZ	U4		1.0	
BASE CAHRGER	Base charger PCB			1.0	
	CONNECTOR,MX53047-08,HEADER	J3		1.0	
	HARNESS,53014-11 11P 50mm	J4		1.0	
	JACK,MOD,1161-66(6PIN)	CN1		1.0	
	HEAT SINK			1.0	
	IC,KIA7805P,REG,TO-220,KEC	U2		1.0	
	CAP,ELEC,100uF/16V 5*11 DIP	C9		1.0	
	CAP,ELEC,470uF/16V 10*11 DIP	C23,C26		2.0	
	CAP,ELEC,1000uF/16V 10*11 DIP	C13,C24,C25		3.0	
	RES, 15 ohm 1/2W AXIAL DIP	R14		1.0	
	COIL 1mH AXIAL	L1,L4		2.0	
	RES,CHIP,000,J,1608,1/16W	R13		1.0	
	RES,CHIP,152,J,1608,1/16W	R37		1.0	
	RES,CHIP,100,J,1608,1/16W	R9		1.0	
	RES,CHIP,104,J,1608,1/16W	R10,R18		2.0	
	RES,CHIP,183,J,1608,1/16W	R19		1.0	
	RES,CHIP,102,J,1608,1/16W	R8,R11,R27,R36,R38		5.0	
	RES,CHIP,333,J,1608,1/16W	R12,R15		2.0	
	RES,CHIP,472,J,1608,1/16W	R2		1.0	
	RES,CHIP,561,J,1608,1/16W	R26		1.0	
	CAP,CHIP,102K,1608,50V X7R	C6,C8		2.0	
	CAP,CHIP,104Z,1608,16V/Y5V	C7,C10,C12,C14,C16,C33,C34		7.0	
	CAP,CHIP,5R6,C,1608,50V/COG	C11,C35		2.0	
	TR, CHIP KTA1505Y	Q2		1.0	
	TR, CHIP KTC3875SY	Q1,Q3		1.0	
	DIODE,RECTFY,S1G (400V/1A)Package:DO-214AC	D1,D2,D3,D7		4.0	

NO.	PART	LOCATION		Q'TY	
LED SUB	LED SUB PCB			1.0	
	CONN 8PIN 53047-0800 AN	J2		1.0	
	CONN A'SSY 8PIN AWG40, 30MM			1.0	
	LED GREEN BL-B2141-AAAV	D4		1.0	
	DIODE,LED,BL-B5141-AV/ RED 3MM	D5		1.0	
기구	사출 D/S FRONT		1		
	사출 D/S BACK		1		
	사출 ANT CAP		1		
	HOOK S/W		2		
	HOOK S/W TIP		2		
	FOOT RUBBER		2		
	D/S TERMINAL		4		
	SCREW T/S BH+ T2 2.6X6L FZY		4		
	SCREW T/S BH+ T2 2.6X8L FZY		4		
	LABEL SERIAL		1		
	LABEL FCC		1		
	LABEL ADAPTOR		1		