

(생산적용)

B O M L I S T

PRO NAME	CONEXANT ADSL MODEM (외장)			PCB CHANGED	DRWN	CHKD	APRD	SHEET
DOC NAME	NEOBIT 1012 CA-DQ (ETHERNET-5V)			OPTION : USB, RS 232				1/7
DOC N/O	NET-U0029-SC005-ETH only							
REV DATE	2004-02-02	Rev Code	0.3- ETH					

CHANGED HISTORY LIST

[illegible]

순번	Component Name	Item Code	SHOP	Design Name	Unit	Q'ty	Maker	NOTE
1	Chip Cap	20pF, 16V 5%, NPO, 0603	SMD	C28,C29	EA	2		
	Chip Cap	22pF, 16V 5%, NPO, 0603	SMD	C21,C22	EA	2		C
2	Chip cap	180pF, 50V 5%, NPO, 0805	SMD	C100,	EA	1		
3	Chip Cap	1nF (1000pF), 16V 5%, NPO, 0603	SMD	C140,C54,C129,C55,C68,C103,C142,C136 C132,C131,C23,C45,C50,C66,	EA	14		
4	Chip Cap	1nF (1000pF), 50V 5%, NPO, 0805	SMD	C99,	EA	1		
5	Chip Cap	1.5nF (1500pF), 16V 5%, NPO, 0805	SMD	C96,C97,	EA	2		
6	Chip Cap	4.7nF (4700pF), 16V 5%, NPO, 0603	SMD	C105,	EA	1		
7	Chip cap	0.1uF (100nF), 16V 10%, NPO, 0603	SMD	C88,C89,C1,C4,C6,C106, C101,C141,C98,C72,C52,C102,C127,C143, C70,C69,C71,C56,C53,C51,C73,C125,C128, C124,C126,C135,C82,C81,C83,C138,C139, C34,C35,C36,C37,C57,C58,C59,C40,C60, C42,C67,C41,C49,C47,C46,C48,C24,C44,C43	EA	50		
	Chip cap	0.1uF (100nF), 16V 10%, NPO, 0603	SMD	C30,C32,C33,C25	EA	4	U	U
	Chip cap	0.1uF (100nF), 16V 10%, NPO, 0603	SMD	C13,C14,C15,C16,C17,C18,C19,C20,C74,C75, C76,C77,C78	EA	13	C	C
8	Chip cap	0.1uF 16V 5%, NPO, 0805	SMD	C27,C120,	EA	2		
9	Chip cap	0.1uF 16V 10%, NPO, 1206	SMD	C94,C95,	EA	2		
10	Chip cap	1uF 16V 5%, NPO, 0805	SMD	C115	EA	1		
11	Chip Cap	2.2uF 16V 10%, X7R, 1206	SMD	C121	EA	1		
12	Chip Cap	CHIP CAP(0603)		C90,C91,C5,C104,C108,C109,C7,C84, C85,C86,C87,C130,C133,C134,C137,C12				
			SMD	C8,C122,C38,C39,C61,C62,C63,C64,C31 C3,C2,C9,C10,C11	EA	0		
13A	Film cap	0.027uF 50V 5%, PPS Film, 1206	SMD		EA	0	Panasonic	ECHU1C333JB5
13B	Polyester Capacitor	0.027uF 63V 2%, MC5mm	DIP	C92,C93	EA	2		
14A	Film Cap	0.056uF 50V 5%, PPS Film, 1206	SMD		EA	0	Panasonic	ECHU1C563GB9
14B	Polyester Capacitor	0.056uF 63V 2%, MC5mm	DIP	C116,C119	EA	2		
15A	Film Cap	0.068uF 50V 5%, PPS Film, 1206	SMD		EA	0	Panasonic	ECHU1C683GB9
15B	Polyester Capacitor	0.068uF 63V 2%, MC5mm	DIP	C117,C118	EA	2		
16	Polyester Capacitor	33nF, 450V 10%, MC10mm	DIP	C123	EA	1	ANY	
17	Polyester Capacitor	22nF, 450V 10%, MC10mm	DIP	C110	EA	1	ANY	

순번	Component Name	Item Code	SHOP		Unit	Q'ty	Maker	NOTE
18	Ceramic Cap	100pF/2KV, MC5mm	DIP	C111,C112,C113,C114	EA	4		
19	Ceramic Cap	10nF/2KV, MC7mm	DIP	C65	EA	1		
	Ceramic Cap	150pF/2KV , MC5mm	DIP	C79,C80	EA	0		C
20	전 해 Cap	1uF/50V 20%	DIP	TC2	EA	1	삼화, 삼성	
	전 해 Cap	1uF/50V 20%	DIP	TC10	EA	1	삼화, 삼성	U
21	전 해 Cap	10uF/50V 20%	DIP	TC1,TC16,TC18,TC9,TC12,TC13,TC14,TC8	EA	8	삼화, 삼성	
22	전 해 Cap	22uF/25V 20%	DIP	TC15,TC11	EA	2	삼화, 삼성	
23	전 해 Cap	47uF/25V 20%	DIP	TC17	EA	1	삼화, 삼성	
24	전 해 Cap	1000uF/ 16V, 20%	DIP	TC6	EA	1	삼화, 삼성	
25	전 해 Cap	DNE	DIP	TC4,TC5,TC7,TC3	EA	0		
26	VARISTOR	DNE	DIP	RV1,RV2	EA	0		
27	GAS Tube	SL1002A350SM	SMD	D11	EA	1	ACM	
28	Chip Resister	CR-F-T,0R, 5%, 1/16, 0603	SMD	R90,R25,R142,R19,R17,R9	EA	6	ANY	
	Chip Resister	CR-F-T,0R, 5%, 1/16, 0603	SMD	R48	EA	1	ANY	U
29	Chip Resister	CR-F-T,0R, 5%, 1/10, 0805	SMD	R15,R132,R134,R124	EA	4	ANY	
	Chip Resister	CR-F-T,0R, 5%, 1/10, 0805	SMD	R44	EA	1	ANY	U
30	Chip Resister	CR-F-T,0R, 5%, 1/8, 1206	SMD	R36,R111,R141	EA	3	ANY	
	Chip Resister	CR-F-T,0R, 5%, 1/8, 1206	SMD	R47	EA	1	ANY	U
31	Chip Resister	CR-F-T,4R7, 1%, 1/10, 0805	SMD	R138,R139	EA	2	ANY	
	Chip Resister	CR-F-T,24, 1%, 1/10, 0805	SMD	R50,51	EA	2	ANY	U
32	Chip Resister	CR-F-T,51R, 1%, 1/16, 0603	SMD	R128,R95,R96,R113,R114,R94,R60,R61,R62, R63,R117,R91	EA	12	ANY	
	Chip Resister	CR-F-T,51R, 1%, 1/16, 0603	SMD	R31,R103,R104,R107,R108	EA	4	ANY	C
33	Chip Resister	CR-F-T,61R9, 1%, 1/10, 0805	SMD	R131,R136	EA	2	ANY	
34	Chip Resister	CR-F-T,71R5, 1%, 1/10, 0805	SMD	R137,R140	EA	2	ANY	
35	Chip Resister	CR-F-T,75R, 1%, 1/16, 0603	SMD	R66,R67,R68,R69	EA	4	ANY	
36	Chip Resister	CR-F-T,130R, 1%, 1/10, 0805	SMD	R133,R135	EA	2	ANY	
37	Chip Resister	CR-F-T,221R, 1%, 1/16, 0603	SMD	R70,R74,R77,R78,R81,R83	EA	6	ANY	
38	Chip Resister	CR-F-T,274R, 1%, 1/10, 0805	SMD	R120,R121	EA	2	ANY	
39	Chip Resister	CR-F-T,784R, 1%, 1/16, 0603	SMD	R112	EA	1	ANY	
40	Chip Resister	CR-F-T,1K, 1%, 1/16, 0603	SMD	R1,R7,R115,R54,R130	EA	5	ANY	
	Chip Resister	CR-F-T,1K, 1%, 1/16, 0603	SMD	R42	EA	1	ANY	U
41	Chip Resister	CR-F-T,1K, 1%, 1/10, 0805	SMD	R122,R123	EA	2	ANY	

순번	Component Name	Item Code	SHOP	Design Name	Unit	Q'ty	Maker	NOTE
42	Chip Resister	CR-F-T,1.5K, 1%, 1/16, 0603	SMD	R65	EA	1	ANY	
	Chip Resister	CR-F-T,1.5K, 1%, 1/16, 0603	SMD	R52	EA	1	ANY	U
43	Chip Resister	CR-F-T,5.1K, 1%, 1/16, 0603	SMD	R97,R98,R99,R100,R101,R56,R57,R58	EA	8	ANY	
	Chip Resister	CR-F-T,5.1K, 1%, 1/16, 0603	SMD	R24,R30	EA	2	ANY	C
44	Chip Resister	CR-F-T,5.9K, 1%, 1/16, 0603	SMD	R64	EA	1	ANY	
45	Chip Resister	CR-F-T,6.34K, 1%, 1/16, 0603	SMD	R2	EA	1	ANY	
46	Chip Resister	CR-F-T,10KR, 2%, 1/16, 0603	SMD	R127,R4,R86,R85,R88,R93,R144,R16,	EA	8	ANY	
	Chip Resister	CR-F-T,10KR, 2%, 1/16, 0603	SMD	R43	EA	1	ANY	U
47	Chip Resister	CR-F-T,20K, 1%, 1/16, 0603	SMD	R125	EA	1	ANY	
48	Chip Resister	CR-F-T,30K, 1%, 1/16, 0603	SMD	R89	EA	1	ANY	
49	Chip Resister	CR-F-T,30.1K, 1%, 1/16, 0603	SMD	R129	EA	1	ANY	
50	Chip Resister	CR-F-T,47K, 1%, 1/16, 0603	SMD	R3	EA	1	ANY	
	Chip Resister	CR-F-T,51K, 1%, 1/16, 0603	SMD	R46	EA	1	ANY	U
51	Chip Resister	CR-F-T,75K, 1%, 1/16, 0603	SMD	R126	EA	1	ANY	
	Chip Resister	CR-F-T,75K, 1%, 1/16, 0603	SMD	R45	EA	1	ANY	U
	Chip Resister	CR-F-T,100K, 1%, 1/16, 0603	SMD	R40,R41	EA	1	ANY	U
	Chip Resister	CR-F-T,100K, 1%, 1/16, 0603	SMD	R22	EA	1	ANY	C
52	Chip Resister	CR-F-T,124K, 1%, 1/16, 0603	SMD	R119	EA	1	ANY	
	Chip Resister	CR-F-T,1M, 1%, 1/16, 0603	SMD	R32	EA	1	ANY	C
	Chip Resister	CR-F-T,5.1M, 1%, 1/16, 0603	SMD	R49	EA	1	ANY	U
53	Chip Resister	DNE (0603)	SMD	R20,R21,R28,R29,R102,R87,R92,	EA	0		Option 2, 3
				R116,R26,R27,R143,R71,R73,R72,R76,				
				R75,R79,R82,R80,R84,R8,R145,R146,				
				R53,R55,R109,R110,R18,R23,R59				
				R34,R35,R13,R14,R6,R10,R11,R12				
				R33,R5,R105,R106				
54	Chip Resister	DNE (0805)	SMD	R37	EA	0		Option
55	Chip Resister	DNE (1210)	SMD	R38,R39	EA	0		Option
56	Arry Resister	CR-F-T,51R, 1%, 1/16, 0603	SMD	RA2,RA3,RA6,RA7,RA8,RA9,RA10,RA5,RA4	EA	9	ANY	
57	Arry Resister	CR-F-T,5.1K, 1%, 1/16, 0603	SMD	RA1,	EA	1	ANY	
	Zener Diode	BAT54, SOT-23	SMD	ZD2	EA	1		U
58	Zener Diode	DNE	SMD	ZD1	EA	0		Option 1
59	Regulator DIODE	DNE	DIP	D4,D5,D7,D8,D3,D2,D6	EA	0		Option 1

순번	Component Name	Item Code	SHOP		Unit	Q'ty	Maker	NOTE
60	Small Single DIODE	MMDL914L, SOD323	SMD	D1	EA	1		Option 1
61	Dual Switching Diode	MMBD7000LT1, SOT-23A	SMD	D9,D10	EA	2	VISHAY	
62	POLYESTER SWITCH	PR-MS-075	SMD	PS1,PS2	EA	2	CERATECH	
63	Ferrite Bead	100/100MHz, 2012 (0805)	SMD	L4	EA	1		
64	Ferrite Bead	120/100MHz, 2012 (0805)	SMD	L11,L7,L8,L12,L3,	EA	5		
65	<i>Ferrite Bead</i>	<i>DNE</i>	<i>SMD</i>	<i>L9,L10</i>	<i>EA</i>	<i>0</i>		
66	Power INDUCTOR	DSC5845, 10uH	SMD	L2	EA	1		
67	<i>INDUCTOR</i>	<i>DNE</i>	<i>SMD</i>	<i>L5,L6,L1</i>	<i>EA</i>	<i>0</i>		<i>Option 1</i>
68	<i>Transistor</i>	<i>DNE</i>	<i>SMD</i>	<i>Q3,Q5,Q4</i>	<i>EA</i>	<i>0</i>		<i>Option 2</i>
	Transistor	2N7002, SOT23	SMD	Q2	EA	1		C
	MOSFET	2N7002, SOT23	SMD	Q6	EA	1		U
	MOSFET	BSS84, SOT23	SMD	Q7	EA	1		U
69	VCXO	35.328MHZ, Half	DIP	Y3	EA	1		
70	CRYSTAL	25MHZ, MCO11/ HC49S	DIP	Y2	EA	1	MicroQuartz	
72	CRYSTAL	1.8432MHz, MCO11/HC49S	DIP	Y1	EA	1	MicroQuartz	C
71	1.8V Regulator	LM1117I-1.8V, SOT223, FIX	SMD	Q8	EA	1	NATIONAL	
72	3.3V Regulator	LM1117I-3.3V, SOT223, FIX	SMD	Q1	EA	1	NATIONAL	
73	<i>Switching Regulator</i>	<i>DNE</i>	<i>SMD</i>	<i>U5</i>	<i>EA</i>	<i>0</i>	<i>ST</i>	
74	Transfomer (H/P)	HP 1302, 800uH, 1:3.3 COEV, C1571	SMD	T2	EA	1	HYPHY CoeV	
75	Transfomer(L/P)	HP1316, 5.5mH 10%	SMD	T1	EA	1	HYPHY	
76	IC (DSP)	CX82310-14, Annex.A	SMD	U11	EA	1	CONEXANT	
77	IC (SERIAL FLASH)	SST39VF160, TSOP48	SMD	U7	EA	1	SST	
78	IC (SDRAM)	HY57V651620B, TSOPii54	SMD	U8	EA	1	HYNIX	
79	IC (Ethernet Cont)	RTL8201BL QFP48	SMD	U9	EA	1	REALTEK	
	IC (RS232)	ST232CD	SMD	U12	EA	1	ST	C
80	<i>IC (Inverter)</i>	<i>DNE (74VHC14, SOIC-14)</i>	<i>SMD</i>	<i>U3</i>	<i>EA</i>	<i>0</i>	<i>ANY</i>	
81	<i>IC</i>	<i>DNE</i>	<i>SMD</i>	<i>U2</i>	<i>EA</i>	<i>0</i>	<i>ANY</i>	
	IC	74VHC74	SMD	U6	EA	1		U
	IC (UART/16Byte FIFO)	ST16C550CQ48, LQFP48	SMD	U4	EA	1		C
82	IC (Micro Power)	LMC7211, SOT23-5	SMD	U1	EA	1	NATIONAL	
83	Magnetic	HS2213	SMD	U10	EA	1	MACONICS	
84	LED	GREEN	SMD	LD1,LD2,LD3,LD4,LD5,LD6	EA	6	ROHM	

순번	Component Name	Item Code	SHOP		Unit	Q'ty	Maker	NOTE
----	----------------	-----------	------	--	------	------	-------	------

85	HEADER	PIN HEADER 4x2 Male	DIP	P1	EA	1		
86	HEADER	DNE	DIP	JP2	EA	0		
87	Tact Switch	ITA1102V-B	DIP	SW2	EA	1		
88	Tact Switch	DNE (ITA1102A)	DIP	SW1	EA	0		
89	Rocker Switch	A-12KV, SPDT	DIP	SW4	EA	1	NIKKAI	
90	Phone Connector	RJ11, 623PCB 6P4C 2PORT	DIP	RJ6	EA	1		
91	Ethernet Connector	657PU-8-SD, Half Shild,BLUE	DIP	RJ3	EA	1		
	Ethernet Connector	657PU-8-SD, Half Shild,BLACK	DIP	RJ5	EA	1		C
92	POWER JACK	DS-210, DC Power In Put, GREEN	DIP	PWR1	EA	1		
	USB CONNECTOR	USB-B, YELLOW	DIP	RJ1	EA	1		U
93	PCB	PCB		1012_CA_DQ_Ver 0.3	EA	1		

포장 관련

7/7

순번	Component Name	Item Code	SHOP	Design Name	Unit	Q'ty	Maker	NOTE
201	HOUSING- MODEM	TOP, BOTTOM			SET	1		

202	WINDOW	WINDOW			EA	1		
203	REPLATER	REPLATER			EA	1		
204	SCREW	3 x 10mm, BLACK		CHECKING the Tap	EA	4	ATTENTION	
205	BUMPON	1.6T / 12mm BLACK			EA	2		
206	LINE CORD	RJ11 to RJ11, 1.2m,		COLOR : ALL WHITE	EA	1	ATTENTION	
207	LAN CABLE	RJ45 to RJ45, 1.2m,		MOLD COLOR : Once BLUE, Other GRAY	EA	1	ATTENTION	
208	ADAPTER	+5V DC (IN PUT AC110V Only)		DC CONNECTOR MOLD COLOR : GREEN	EA	1	ATTENTION	
209	SILICAGEL	5g			EA	1		
210	AIR VINYL BAG	160mm x 430mm			EA	1		
211	MANUAL 1	USER MANUAL			EA	2		
212	MANUAL 2	USER MANUAL			EA	2		
213	CD	USER MANUAL COPY			EA	1		
214	INNER BOX	152 x 90 x 290 mm		Black LOGO on the White Paper	EA	1		
215	OUT BOX	330 x 310 x 470 mm		BROWN Inner Box 10 for 1ea Outer box		10:01		
216	Identification LABEL	38mm x 78mm		UL/FCC Marking on the Silver Color Paper	EA	1		
217	MAC/S,N LABEL	30mm x 10mm		Board, Case, Inner box, Out box	EA	4		
218	POLY TAPE	50mm			Cm	480		
219	RS 232	MODULE (Included CABLE)		Apply Require The Customer	EA	1	ATTENTION	After UART attempt It

OPTION #1 (CONSOLE)

순번	Component Name	Item Code	SHOP	Design Name	Unit	Q'ty	Maker	NOTE
1	Chip Cap	22pF, 16V 5%, NPO, 0603	SMD	C21,C22	EA	2		
2	Chip cap	0.1uF (100nF), 16V 10%, NPO, 0603	SMD	C13,C14,C15,C16,C17,C18,C19,C20,C74,C75, C76,C77,C78	EA	13		
3	Ceramic Cap	150pF/2KV , MC5mm	DIP	C79,C80	EA	0		
4	Chip Resister	CR-F-T,51R, 1%, 1/16, 0603	SMD	R31,R103,R104,R107,R108	EA	4	ANY	
5	Chip Resister	CR-F-T,5.1K, 1%, 1/16, 0603	SMD	R24,R30	EA	2	ANY	
6	Chip Resister	CR-F-T,100K, 1%, 1/16, 0603	SMD	R22	EA	1	ANY	
7	Chip Resister	CR-F-T,1M, 1%, 1/16, 0603	SMD	R32	EA	1	ANY	
8	Transistor	2N7002, SOT23	SMD	Q2	EA	1		
9	CRYSTAL	1.8432MHz, MCO11/HC49S	DIP	Y1	EA	1	MicroQuartz	
10	IC (RS232)	ST232CD	SMD	U12	EA	1	ST	
11	IC (UART/16Byte FIFO)	ST16C550CQ48, LQFP48	SMD	U4	EA	1		
12	Ethernet Connector	657PU-8-SD, Half Shild,BLACK	DIP	RJ5	EA	1		

순번	Component Name	Item Code	SHOP	Design Name	Unit	Q'ty	Maker	NOTE
201	HOUSING- MODEM	TOP, BOTTOM			SET	1		
202	WINDOW	WINDOW			EA	1		
203	REPLATER	REPLATER			EA	1		
204	SCREW	3 x 10mm, BLACK		CHECKING the Tap	EA	4	ATTENTION	
205	BUMPON	1.6T / 12mm BLACK			EA	2		
206	LINE CORD	RJ11 to RJ11, 1.2m,		COLOR : ALL WHITE	EA	1	ATTENTION	
207	LAN CABLE	RJ45 to RJ45, 1.2m,		MOLD COLOR : Once BLUE, Other GRAY	EA	1	ATTENTION	
208	ADAPTER	+5V DC (IN PUT AC110V Only)		DC CONNECTOR MOLD COLOR : GREEN	EA	1	ATTENTION	
209	SILICAGEL	5g			EA	1		
210	AIR VINYL BAG	160mm x 430mm			EA	1		
211	MANUAL 1	USER MANUAL			EA	2		
212	MANUAL 2	USER MANUAL			EA	2		
213	CD	USER MANUAL COPY			EA	1		
214	INNER BOX	152 x 90 x 290 mm		Black LOGO on the White Paper	EA	1		
215	OUT BOX	330 x 310 x 470 mm		BROWN Inner Box 10 for 1ea Outer box		10:01		
216	Identification LABEL	38mm x 78mm		UL/FCC Marking on the Silver Color Paper	EA	1		
217	MAC/S,N LABEL	30mm x 10mm		Board, Case, Inner box, Out box	EA	4		
218	POLY TAPE	50mm			Cm	480		
219	RS 232	MODULE (Included CABLE)		Apply Require The Customer	EA	1	ATTENTION	After UART attempt It

OPTION #1 (USB)

순번	Component Name	Item Code	SHOP	Design Name	Unit	Q'ty	Maker	NOTE
1	Chip cap	0.1uF (100nF), 16V 10%, NPO, 0603	SMD	C30,C32,C33,C25	EA	4	U	
2	전 해 Cap	1uF/50V 20%	DIP	TC10	EA	1	삼화, 삼성	
3	Chip Resister	CR-F-T,0R, 5%, 1/16, 0603	SMD	R48	EA	1	ANY	
4	Chip Resister	CR-F-T,0R, 5%, 1/10, 0805	SMD	R44	EA	1	ANY	
5	Chip Resister	CR-F-T,0R, 5%, 1/8, 1206	SMD	R47	EA	1	ANY	
6	Chip Resister	CR-F-T,24, 1%, 1/10, 0805	SMD	R50,51	EA	2	ANY	
7	Chip Resister	CR-F-T,1K, 1%, 1/16, 0603	SMD	R42	EA	1	ANY	
8	Chip Resister	CR-F-T,1.5K, 1%, 1/16, 0603	SMD	R52	EA	1	ANY	
9	Chip Resister	CR-F-T,10KR, 2%, 1/16, 0603	SMD	R43	EA	1	ANY	
10	Chip Resister	CR-F-T,51K, 1%, 1/16, 0603	SMD	R46	EA	1	ANY	
11	Chip Resister	CR-F-T,75K, 1%, 1/16, 0603	SMD	R45	EA	1	ANY	
12	Chip Resister	CR-F-T,100K, 1%, 1/16, 0603	SMD	R40,R41	EA	1	ANY	
13	Chip Resister	CR-F-T,5.1M, 1%, 1/16, 0603	SMD	R49	EA	1	ANY	
14	Zener Diode	BAT54, SOT-23	SMD	ZD2	EA	1		
15	MOSFET	2N7002, SOT23	SMD	Q6	EA	1		
16	MOSFET	BSS84, SOT23	SMD	Q7	EA	1		
17	IC	74VHC74	SMD	U6	EA	1		
18	USB CONNECTOR	USB-B, YELLOW	DIP	RJ1	EA	1		

포장 관련

7/7

순번	Component Name	Item Code	SHOP	Design Name	Unit	Q'ty	Maker	NOTE
201	HOUSING- MODEM	TOP, BOTTOM			SET	1		
202	WINDOW	WINDOW			EA	1		
203	REPLATER	REPLATER			EA	1		
204	SCREW	3 x 10mm, BLACK		CHECKING the Tap	EA	4	ATTENTION	
205	BUMPON	1.6T / 12mm BLACK			EA	2		
206	LINE CORD	RJ11 to RJ11, 1.2m,		COLOR : ALL WHITE	EA	1	ATTENTION	
207	LAN CABLE	RJ45 to RJ45, 1.2m,		MOLD COLOR : Once BLUE, Other GRAY	EA	1	ATTENTION	
208	ADAPTER	+5V DC (IN PUT AC110V Only)		DC CONNECTOR MOLD COLOR : GREEN	EA	1	ATTENTION	
209	SILICAGEL	5g			EA	1		
210	AIR VINYL BAG	160mm x 430mm			EA	1		
211	MANUAL 1	USER MANUAL			EA	2		
212	MANUAL 2	USER MANUAL			EA	2		
213	CD	USER MANUAL COPY			EA	1		
214	INNER BOX	152 x 90 x 290 mm		Black LOGO on the White Paper	EA	1		
215	OUT BOX	330 x 310 x 470 mm		BROWN Inner Box 10 for 1ea Outer box		10:01		
216	Identification LABEL	38mm x 78mm		UL/FCC Marking on the Silver Color Paper	EA	1		
217	MAC/S,N LABEL	30mm x 10mm		Board, Case, Inner box, Out box	EA	4		
218	POLY TAPE	50mm			Cm	480		
219	RS 232	MODULE (Included CABLE)		Apply Require The Customer	EA	1	ATTENTION	After UART attempt It

