

Thank you for choosing our product.

1 Description of Product :

Bluetooth Wireless Headset &

Telephone

Model No. : WFI100-HS-D-BS

CONTENTS

Important Safety Precautions.....	3
Included in this Kit	10
Features	11
Location of Controls.....	12
Description of Key Components.....	13
How to Use.....	15
For the Best Use	18
Specification.....	20
What to do if	21
Warranty Guideline.....	22

IMPORTANT SAFETY PRECAUTIONS

CAUTION

RISK OF ELECTRIC SHOCK
DO NOT OPEN

* **CAUTION:** TO REDUCE THE RISK OF ELECTRIC SHOCK, DO NOT REMOVE COVER(OR BACK). NO USER - SERVICEABLE PARTS INSIDE. REFER SERVICING TO QUALIFIED SERVICE PERSONNEL.

* **DANGEROUS VOLTAGE**

Uninsulated Dangerous Voltage that may be of sufficient magnitude to constitute a risk of electric shock to persons is present within this product's enclosure.

* **ATTENTION**

The Operating Instructions contains important operating and maintenance instructions.

For your safety, it is necessary to refer to the instructions.

***INSTALLATION INSTRCTION PRECAUTIONS:**

- Never install telephone wiring during a lightning storm.
- Never install telephone jacks in wet locations unless the jack is specifically designed for wet locations.
- Never touch uninsulated telephone wires or terminals unless the telephone line has been disconnected at the network interface.
- Use caution when installing or modifying telephone lines

When using your telephone equipment, basic safety precautions must always be followed to reduce the risk of fire, electric shock and injury to persons, including the following :

1. Read and understand all instructions.
2. Follow all warnings and instructions marked on this product.

3. Unplug this product from the wall outlet before cleaning. Do not use liquid cleaners or aerosol cleaners. Use a damp cloth for cleaning.
4. Do not use this product near water - for example, near a bathtub, washbowl, kitchen sink , or laundry tub, in a wet Donglement, or near a swimming pool.
5. Do not place this product on an unstable cart, stand, tripod, bracket, or table. The product may fall, causing serious damage to the product.
6. Do not allow anything to rest on the power cord. Do not locate this product where the cord will be abused by persons walking on it.
7. Do not overload wall outlets and extension cords as this can result in the risk of fire or electric shock.
8. Never push objects of any kind into this product through openings as they may touch dangerous voltage points or short out parts that could result in fire or electric shock. Never spill or spray any type of liquid on the product.
9. To reduce the risk of electric shock, do not disassemble this product, but take it to a qualified serviceman when some service or repair work is required.
10. Opening or removing covers may expose you to dangerous voltages or other risks. Incorrect re-assembly can cause electric shock when the appliance is subsequently used.
11. To reduce the risk of fire, use only No.26 AWG or larger UL Listed or CSA Certified Telecommunication Line Cord.
12. Unplug the product from the wall outlet and refer servicing to qualified service personnel under the following conditions :
 - a. When the power-supply cord or plug is damaged or frayed.
 - b. If liquid has been spilled into the product.
 - c. If the product has been exposed to rain or water.
 - d. If the product does not operate normally by following the operating instructions. Adjust only those controls that are covered by the operating and will often require extensive work by a qualified technician to restore the product to its normal operation.
 - e. If the product has been dropped or the cabinet has been damaged.
 - f. If the product exhibits a distinct change in performance.
13. Do not use the telephone to report a gas leak near the leak.

FCC NOTICE

The Headset and Dongle may cause TV or radio interference if used in close proximity

to receiving equipment. The FCC can require you to stop using the phone if such interference cannot be eliminated. Vehicles using liquefied petroleum gas (such as propane or butane) must comply with the National Fire Protection

Standard (NFPA-58). For a copy of this standard, contact the National Fire Protection Association, One Batterymarch Park, Quincy, MA 02269, Attn: Publication Sales Division.

This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) this device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

Cautions

Any changes or modifications to your phone not expressly approved in this document could void your warranty for this equipment, and void your authority to operate this equipment.

Only use approved batteries, and chargers. The use of any unauthorized accessories may be dangerous and void the Headset and Dongle warranty if said accessories cause damage or a defect to the phone.

Although your Headset and Dongle are quite sturdy, it is a complex piece of equipment and can be broken. Avoid dropping, hitting, bending or sitting on it.

Body-Worn Operation

To maintain compliance with FCC RF exposure guidelines, if you wear a headset on your body, use carrying case,

holster or other body-worn accessory supplied with this product. If you do not use a body-worn accessory, ensure that the antenna is at least one inch (or 2.5 centimeters) from your body when transmitting. Use of accessories not provided with this product may violate FCC RF exposure guidelines. For more information about FCC RF exposure, please visit the FCC Web site at www.fcc.gov.

Included in this Kit

*** Basic Set**

Item	Headset	Dongle	Charger	Adaptor
Quantity				
	1	1	1	1

Item	Clip	Metal plate	Necklace	Cigar Lighter D/C Cable
Quantity				
	1	1	1	1

Features

1. Compatible with most cellular phones (CDMA, PCS, GSM, etc.) with 2.5mm headset jack.
2. Hands free operation allows you to enjoy indoor and outdoor activities while talking on your phone.
3. Compact and lightweight design.

4. Simultaneous charging of both Headset and Dongle.

5. Auto stand-by mode for 30 seconds after a phone call is ended.

6. Low battery indicator alarm.

7. LED on Headset let's you know the On/Off status.

8. Full duplex solution to provide high audio quality for clear communication.

9. Automatic multi - channel scanning to avoid frequency entanglement with other devices.

10. Ergonomically designed for comfort and stability.

11. Volume control on Headset.

12. Rechargeable batteries.

13. Adjustable mic boom.

Location of Controls

* Headset

* Charger

.....

Description of Key components

* Headset

	<ul style="list-style-type: none"> - Hook button: ON/OFF and Redial function. - Volume up & down button : Volume control. - LED lamp : Indicates ON/OFF status - Mic boom : Adjustable for desirable position. - Earphone : Makes beep sound when a button on the Headset is pressed.
--	--

* Dongle (Audio gateway)

	<ul style="list-style-type: none"> - Insert the 2.5mm "Ear Plug" into the earphone jack of your cellular phone. - Place the Dongle into the Charger to use with regular telephone line. - LED lamp: Indicates ON/OFF status.
--	---

* Charger and Telephone

	<ul style="list-style-type: none"> - LED lamps: Indicates charging status. - Simultaneous charging for both the Headset and Dongle
--	--

* Clip

	<ul style="list-style-type: none"> - Use it to mount the Charger unit in a car or any other desired location. This clip is provided for your convenience only and may not be suitable for installing in all cars. - Place the clip into the "Clip Folder" space provided on the back side of the Charger unit. Search for a location where the Charger unit can be placed. Use a double-sided tape if necessary to secure the Charger unit in place. In some cases, the clip will not be necessary.
--	---

* Metal plate

	<ul style="list-style-type: none"> - Use the metal plate to stick the Dongle unit to your cellular phone. - Peel off the protective film and place the metal plate on the back side of your cellular phone. This metal plate may not be used in conjunction with belt clips on some cellular phones.
--	--

cellular phone, then press TALK(or CALL) button. The Hook button on the Headset can be used to dial out the number entered into the cellular phone on some models.

* Receiving a Phone Call

- Press the TALK(or CALL) button on the cellular phone or press the Hook button on the Headset.

* Ending a Phone Call

- Press the END button (or the appropriate button to end a call) on the cellular phone or press the Hook button again on the Headset.

* Redial Feature

- Some cellular phones with Redial feature can utilize the Hook button on the Headset to redial the last number dialed from the cellular phone.

- Press the Hook button once. The display on the cellular phone will show the last dialed number. Press Hook button again to dial that number.

-Note:These features may not be available on all cellular phones.

4. Using with regular telephone line

* Making a Phone Call

- Press ON/OFF button of the Dongle or Dongle for 2 to 3 seconds.
- Confirm ON status by checking that the LED lamp of the Headset and Dongle are ON.
- Connect the ear plug of the Dongle into the earphone jack of a cellular phone.
- Dial a number using the keypad of the

* Making a Phone Call

- Connect a telephone cable to the telephone jack located on the back side of the Charger unit.
- Make sure the power adaptor is also connected to the Charger unit.
- Place the Dongle in the appropriate charging cradle located on the top side of the Charger unit.
- Connect the Dongle plug to the ear phone jack located on the backside of the charger.
- Press the Hook button on the Charger unit of the Headset. Wait for a dial tone.

- Using the keypad on the Charger unit, dial the number you wish to call.

*** Receiving a Phone Call**

- Press the Hook button either on the Charger unit or Headset to receive an incoming call.

*** Ending a Phone Call**

- Press the Hook button either on the Charger or Headset.
- This will put the Headset in stand-by mode automatically.

*** Redial Feature**

- Press the Hook button either on the Charger or Headset.
- Then, press the R/P button located on the Charger keypad.

5. Registering Headset and Dongle

***Registering Headset for Cellular phones with Bluetooth headset profile.**

WTI-100 headset can be registered as a wireless headset without the use of a Dongle unit to a cellular phone with Bluetooth headset profile. To register the Headset, follow these steps:

- Turn off the Headset power by pressing the ON/OFF button for several seconds. (The green LED will stop flashing when the power is off.)
- After confirming the power off status, press and hold the ON/OFF button until the LED starts to flash slowly. During this process, the LED will turn on solid for a few seconds, but continue to press and hold the button until it starts to flash slowly.
- Using your cellular phone with Bluetooth headset profile, follow the guidelines provided with your cellular phone on registering Bluetooth headset.
(pin code :)
- Your cellular phone will search and pair with the Headset. Your cellular phone will indicate once the registration is completed.

Note : Some cellular phones require you to manually activate a wireless headset mode. If so, follow instructions provided with your cellular phone.

***Registering Headset with Dongle**

WTI-100 Headset and Dongle are paired at the factory. However, there are instances where you will need to pair the Headset and Dongle (such as using the Headset with the telephone line after pairing it with a Bluetooth cellular phone, etc.).

- Turn off the Headset and the Dongle by pressing the ON/OFF button until the LED stops flashing. .
- Once the power is off, press and hold the ON/OFF button again until the LED starts to flash slowly. During this process, the LED will turn on solid for a few seconds, but continue to press and hold the button until it starts to flash slowly.
- Release the button once the LED starts to flash. It will take several seconds for the Headset and Dongle to pair.
- When pairing is completed, the LED on both the Headset and Dongle will flash with short burst every 2 to 3 seconds, indicating the stand-by mode.

6. Using the necklace

- The necklace is comprised of two parts : long strap and short strap.
- Put the short strap on the Headset using the hole located on the lower side of the volume button.
- Take the long strap and connect the white plastic connector with that of the short strap. Insert the connector until you hear a slight click.

For the Best Use

- Charge the Headset and Dongle fully before use.
- Do not pull or twist the Mic boom by force.
- Never disassemble this product.
- Do not use benzene, paint thinner or other solvents when cleaning this product.
- Do not apply strong impact.

- Do not place this product near a fire place or any other heat source.
- The Mic boom needs to be in an upright position in order to charge the Headset.
- Avoid use with other electronics.
- For best audio quality, avoid use in areas with high radio frequency traffic or near a microwave emitting products (such as a microwave oven).
- The use of this product while driving is a sole discretion and responsibility of the user.
- Do not use this product in extreme temperatures (refer to specification for operating temperature).
- Use power adaptors provided in this kit only.

Specification

* Dongle (Audio gateway) + Headset

- Bluetooth Specification v1.1 Compatible.
- Bluetooth headset profile Compatible.
- Frequency: 2.4~2.4835GHz ISM Band.
- Size/Weight: Headset 12×30×68(23g)
- Full Digital System.
- A-Law, u-Law, 13 or 16bit PCM(8ks/s)
- Transmitter Power: 0 dBm
- Battery Voltage: 3.7V Li-Polimer (210mAh)
- Material: Plastic
- Permitted Temperature: -10 ~ +50
- Continuous Talk Time: 3Hours
- Standby time: 50Hours
- Operating range: Up to 10M

* Charger

- Input power: 12V/300mA
- Output: 4.2V
- Consumption of Electric Power: 5W
- Material: Plastic
- Permitted Temperature: -10 ~ +50

What to do if..

1. If you cannot hear any sound.

- Check the volume of the Headset as

well as that of the cellular phone.

- Make sure the Dongle ear plug is connected properly to the cellular phone or the Dongle is securely placed in the charging cradle on the Charger unit.
- Check if the Headset is ON.
- Make sure the Headset and Dongle batteries are charged.
- Check the distance between the Headset and Dongle (normal operating distance between the Headset and Dongle should not exceed 10 meters, or 30 ft.)

2. If the LED lamp on Charger unit does not light on.

- Make sure the Headset and/or Dongle is securely placed in the appropriate charging cradles on the Charger.
- Check the power adaptor connection. Make sure they are connected properly to the adaptor jack on the back of the Charger unit and the wall socket.
- Check the adaptor's specification. Make sure it has the same specification and polarity listed in this manual.

3. If you hear a beep

- If you hear a beep while other than pressing any of the buttons, it is an alarm indicating that the batteries are low. Please discontinue use and charge the Headset and/or Dongle.

Warranty Guideline

* ONE YEAR LIMITED WARRANTY

This limited, non-transferable warranty is provided to the original purchaser. This product is warranted to be free from defects in materials and craftsmanship under normal installation, use, and service for period of one(1)year from the date of purchase as shown on the purchaser's receipt.

*** WARRANTY DURATION :**

This warranty to the original user shall terminate and be of no further effect 12 months after the date of original retail sale. The warranty is invalid if the Product is (A) damaged or not maintained as reasonable or necessary, (B) modified, altered, or used as part of any conversion kits, subassemblies, or any configurations of other manufactures. (C) improperly installed, (D) serviced or repaired by someone other than our authorized service facility for a defect or malfunction covers by this warranty, (E) used in any conjunction with equipment or parts or as part of any system of other manufacture, or (F) installed or programmed by anyone other than as detailed by the Operating Instructions for this product.

*** STATEMENT OF REMEDY :**

In the event that the product does not conform to this warranty at any time while this warranty is in effect, warrantor will either, at its option, repair or replace the defective unit and return it to you without charge for parts, service, or any other cost(except shipping and handling) incurred by warrantor or its representatives in connection with the performance of this warranty, Warrantor, at its option, may replace the unit with a new or refurbished unit. THE LIMITED WARRANTY SET FORTH ABOVE IS THE SOLE AND ENTIRE WARRANTY PERTAINING TO THE PRODUCT AND IS IN LIEU OF AND EXCLUDES ALL OTHER WARRANTIES OF ANY NATURE WHATSOEVER, WHETHER EXPRESS, IMPLIED OR ARISING BY OPERATION OF LAW, INCLUDING, BUT NOT LIMITED TO ANY IMPLIED WARRANTIES OF MERCHANTABILITY OR FITNESS FOR A PARTICULAR PURPOSE. THIS WARRANTY DOES NOT COVER OR PROVIDE FOR DAMAGES. Some states do not allow this exclusion or limitation of incidental or consequential damages so the above limitation or exclusion or

exclusion may not apply to you.

*** LEGAL REMEDIES :**

This warranty gives you specific legal rights, and you may also have other rights which vary from state to state. This warranty is void outside the United States of America.

*** PROCEDURE FOR OBTAINING PERFORMANCE OF WARRANTY:**

If, after following the instructions in the Operating Instructions you are certain that the Product is defective, pack the Product carefully (Preferably in its original packaging). The Product should include all parts and accessories originally packaged with the Product. Include evidence of original purchase and a note describing the defect that has caused you to return it. The Product should be shipped freight prepaid, by traceable means, to warrantor at:

Waxess Technologies, Inc.

**C/o Unical
Enterprises, Inc**

Parts and Service Division

16960 Gale Avenue

City of Industry, CA 91745

(866)372-6668, 7 a.m. to 7 p.m. Pacific, Monday through Friday

