



1. Indicator light
2. Switch on/off
3. Audio cable
4. Back clip
5. Charging jack

BH1000-1C is a Bluetooth stereo adaptor with working frequency from 2.4GHz to 2.4835GHz. Intergraded antenna is used.

BH1000-1C can pair with Bluetooth music devices which support A2DP profile, such as Bluetooth stereo headset and Bluetooth speaker whose pin code is “0000”

BH1000-1C is powered by the build-in Li-ion DC 3.7V battery and it can be charged by the mini USB port. BH1000-1C can not operate when it is being charged and there is no data transmission via the USB port.

BH1000-1C has two indicator lights, one is red, and another color is blue. They can indicate following status:

When BH1000-1C is charging,

Indicator light	Adapter status
Red light is always bright (BH1000-1C is switched off)	Being charged
Red light is always turns off	Finish charging

When it is not charging,

Indicator light	Adapter status
Red light and Blue light blink alternately	Pairing mode
Blue light blinks once every 2s	Has connected with Headset (Bluetooth music device)
Red light blinks once every 2s	Battery capacity is not enough