

## **Introduction**

The SHIFT3 wireless plug-in car handsfree Phone-handsfree Device-MS is specially designed for in-car use. You can make and receive handsfree calls in your car, you can connect the device to a compatible phone that supports Bluetooth wireless technology.

Read this user guide carefully before using the device. Also read the user guide for your phone, which provides important safety and maintenance information. Keep the device out of reach of small children.

### **Bluetooth wireless technology**

Bluetooth wireless technology is set to revolutionize the personal connectivity by providing freedom from wired connections-enabling links and connectivity between mobile computers, mobile phones, portable handheld devices and other Bluetooth enabled devices with 10 meters(30 feet).

## **Getting started**

Before using the handsfree, you must install it in the car, and pair it with a compatible phone. The device contains the following parts shown at the start of this guide: tiltable cigarette lighter plug(1), microphone(2), indicator light(3), volume turning(4), call key(5), and speaker(6).

### **Install the device**

To function properly, the device must be connected to the cigarette lighter socket of the car, and power can be supplied by the 12 or 24 volt car battery.

Insert the device into the cigarette lighter socket. You can tilt the cigarette lighter plug to the desired angle(up to 160 degrees around). ensure that the device is properly inserted in the cigarette lighter socket, and does not interfere with the normal operation of the car.

In some car models, the cigarette lighter socket is powered by car battery might be discharged even when you remove the ignition key. In those cases, the car battery might be discharged even if the device is not used. Contact the vehicle manufacturer for more information.

### **Switch on or off the device**

To switch on, plug the device into the cigarette lighter socket. the indicator light turns on.

To switch off, pull the device out from the cigarette lighter socket, or if there is no operation, the device will automatically turn off in two minutes.

### **Pairing**

1, Switch on your phone.

2, Plug the device into the cigarette lighter socket. The device sounds a beep and the green indicator will flash slowly.

3, Place the device and a Bluetooth-enabled mobile phone no more than 1 meter apart.

4, Press and hold the call key for 6 seconds until you hear a short beep. The green and red indicators flash green and red alternatively. It's now ready for pairing.

5, Activate your Bluetooth feature on the phone, and set the phone to search for Bluetooth devices.

6, Select "Handsfree Speaker Phone" from the list of found devices.

7, Enter the pre-programmed passkey "0000" to pair and connect the device to your phone. If

the pairing is successful, the blue indicator will light and the device sounds a beep. In some phones you may need to make the connection separately after pairing.

You can set your phone to connect with the device automatically when the device is switched on.

To disconnect the device from your phone, pull the device out from the cigarette lighter socket, or disconnect the device in the Bluetooth menu of the phone.

To pair and connect the device with a new phone, first disconnect the device in the Bluetooth menu of the currently connected phone, and then pair and connect the new phone.

To pair and connect the device with the second phone, press and hold the call key 6 seconds, the green and red indicators flash green and red alternatively, and then pair and connect the second phone. If pairing is successful, the first phone can only make and receive hands-free calls.

#### **Call handling**

Once pairing is completed, you may access the following function. Some of the below-mentioned function is only accessible for handsets supported with hands-Free profile.

1, To adjust the volume during a call, use the volume turning on the device.

2, To answer a call, wait for the device to ring, then short press the call key to accept the call or answer the call via your phone in the normal way. The green indicator light.

3, To end a call, short press the call key or end the call via your phone in the normal way.

4, To reject a call, when you hear the ringing tone, short press the call key twice.

5, To redial the last number, if your phone supports last number redial with the device, short press the call key twice when no call is in progress.

6, If your phone supports voice dialing with the device, press and hold the call key 3 seconds when no call is in progress, and proceed as described in the user guide of your phone.

7, To transfer the active call between the device and your phone, press and hold the call key.

#### **Care and maintenance**

Your device is a product of superior design and craftsmanship and should be treated with care. The suggestions below will help you protect your warranty coverage.

1, Do not expose the device to liquid, moisture or humidity, as it is not waterproof.

2, Do not use abrasive cleaning solvents to clean the device.

3, Do not place the device in high temperature, as it will result in an explosion.

4, Do not expose the device to contact with sharp objects as this will cause scratching and damage.

5, Do not stick anything inside the device as this may damage internal components.

6, Do not attempt to disassemble the device, as it does not contain serviceable components.

7, If you do not use the device for long periods, be sure to store it in a dry place, free from extreme temperature, humidity and dust.

8,Keep all accessories and enhancements out of the reach of small children.

## Safety information

1,Check local laws regarding use of a phone and device while driving.If you use the device while driving,ensure your attention and focus remains on your responsibility of driving safety.

2,Never allow children to play with the device.Small parts may be a choking hazard.

3,Observe all signs that require an electrical device or RF radio product to be switched off in the designated areas,These could include hospitals,blasting areas, and potentially explosive atmospheres.

4,Turn off your device to boarding an aircraft.Do not use your device in an aircraft.

5,Never mount or store your device over any air bag deployment area serious injury may result when an air bag deploys.

## Trouble shooting

If you are unable to connect your device and phone,please try the following:

1,Ensure your device is turned on and plugged into the cigarette lighter socket.

2,Ensure the device is paired with your phone.

3,Ensure your phone's Bluetooth feature is activated.Please refer to your phone user guide for specific instruction.

4,Ensure the device is within a maximum of 10 meters of your phone and there are no obstructions,such as wall or other electronic devices in between as it may cause shorter or interference transmission.

5,If all the above steps do not resolve your problem,please remove your device from the cigarette lighter socket for a while.

The device is compliant with and adopts the Bluetooth specification 2.1.However, interoperability between the device and other Bluetooth-enabled products is not guaranteed because it depends on compatibility.for more information in the compatibility between the device with other Bluetooth-enabled products,please check with the manufacturer/importer.

## Product specifications

D.S.P.version with advanced echo cancellation and noise suppression.

Bluetooth Specifications-----:Version 2.1+EDR

Bluetooth Profile Supported----:Hands-free Profile

Transmission-----:Class 2

Operating Frequency Band-----:2.402~2.480GHz Spectrum

Input Voltage-----:12V~24V DC

Weight-----:

Dimension-----:

FCC NOTE:

This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions:(1)this device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

FCC NOTE:

The manufacturer is not responsible for any radio or TV interference caused by unauthorized modifications to this equipment. Such modifications could void the user's authority to operate the equipment.