



### Start using headset

Charging Bluetooth

Charge M1300 fully, before using it.

1. Insert adaptor into charger jack on the left side of headset.
2. Insert adaptor into an electrical outlet.
3. M1300 will be fully charged within 2 hours.

Power On

To turn on M1300, press the call button on the front for about 1–3 seconds .

Power Off

To turn off M1300, press and hold the call button for up to 4 seconds.

### How to pair

Pairing with phone

You must pair your headset with phone before you make a call.

1. Press the call button for power on.
2. Press and hold volume(+) button for about 4 seconds until the LED turns on steadily.
3. Perform Bluetooth connection with the phone.
4. When M1300 appears in the phone, press "OK"button on the phone.
5. Enter "0000" (4 zeros) and press OK
6. Once pairing is completed successfully, there will be no need for additional pairing in the next time.

### How to call

Answering a Call

When you receive a call, press call button shortly.

Ending a Call

When you finish a call, press call button shortly.

Last Number Redialing

Press call button until you hear beep sound.

Call Rejection

When you have incoming call and you hear the ring sound, press the call button for more than 1 second.

### Transfer Call/Adj.Volume

Transfer Call

1. When you transfer call from phone to headset, press call button of the headset.
2. When you transfer call from headset to phone, please refer to your phone manual.

Adjust Volume

Press volume (+/-) button.

Make a Voice Dial Call

Press call button shortly until you hear command from the phone, and then follow directions.

Your phone should support voice dial call function. Please see your phone manual for more information.

### Troubleshooting

ITEM	DESCRIPTION
No pairing with phone	–Check wheather headset is at pairing mode. –Check pairing order of phone –Check pin code "0000"
Low Volume	–Adjust volume of headset or phone.
Noise	–Stay within 30 ft from your phone.

### Specifications

ITEM	DESCRIPTION
Bluetooth Version	V 1.2
Profile	Handsfree Profile Headset Profile
Call Time Standby Time	Average 6 hrs Average 170 hrs
Call Distance	Upto 10m (30 feet)
Operating Temp.	–20 ~ 60 ‘C
Battery	120mAh , 3.7V
Size (W x L x H)	Approx. 18.4 x 45.7 x 12.8mm
Weight	Approx. 9.2 g (0.33 oz)

<<NOTICE>>

**\* Section 15.19 Labelling requirements**

This device complies with part 15 of the FCC rules

Operation is subject to the following two conditions:

- (1) This device may not cause harmful interference, and
- (2) This device must accept any interference received, including interference that may cause undesired operation.

**\* Section 15.21 Information to user**

The changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

\* IMPORTANT NOTE: To comply with the FCC RF exposure compliance requirements, no change to the antenna or the device is permitted. Any change to the antenna or the device could result in the device exceeding the RF exposure requirements and void user's authority to operate the device.

CE0197

FCC ID URMBCM110