

立体声 蓝牙耳机

Bluetooth® Stereo Headset

用户使用說明書

USER GUIDE

使用入門

■ 耳機由以下部分組成:

1. 多功能鍵 (↵)
2. 麥克風 (M)
3. 充電插孔 (- C +)
4. 聽筒 (T)
5. 耳掛 (H)
6. 指示燈 (L)
7. 上一曲/音量- (◀)
8. 下一曲/音量+ (▶)

■ 充電器和電池


使用充電器給本耳機充電前,請先檢查充電器是否為耳機配套充電器。

警告: 必須使用配套的充電器給耳機充電,使用不配套的充電器可能會損壞耳機

耳機充電

本耳機使用內置式不可拆卸充電電池。請勿嘗試從耳機中取出電池,以免損壞耳機。

1. 充電時,先將耳機關機



2. 將充電器插頭插入耳機充電接口 (- C +),另一端插到交流電源插座上(如圖)。此時耳機開始充電,充電時,紅燈 (L) 恒亮。
3. 耳機充足電,大約需要2-3個小時,充滿后藍燈 (L) 恒亮或紅燈熄滅。

1

開機或關機

開啓耳機時,請按住多功能鍵 (↵),耳機會蜂鳴且藍色指示燈 (L) 會快速閃爍或長按多功能鍵 (↵) 進入配對狀態。

關閉耳機時,請按住多功能鍵 (↵),耳機會蜂鳴且藍色指示燈 (L) 會快速閃爍兩下。

藍牙配對步驟:

1. 配對時,請將藍牙耳機和手機的距離控制在1米範圍內,越近越好。
 2. 確認藍牙耳機處於開機狀態。
 3. 按多功能鍵 (↵),到藍燈 (L) 恒亮或紅藍燈 (L) 同時(交替)亮,此時耳機進入藍牙配對狀態。
 4. 按照藍牙手機的說明書,打開"藍牙搜索"或"添加新設備"選擇耳機名稱,確認后按手機的提示輸入"0000"確認。
- 注意:藍牙耳機的配對時間是有限的,一般為60秒,如果藍燈 (L) 熄滅變為紅燈 (L) 閃爍狀態說明藍牙配對狀態已停止,如果您這時仍未配對成功,請重複步驟1~4再次配對。

斷開耳機與手機的連接

要斷開耳機與手機的連接(例如,將手機連接至其他藍牙設備),請採用以下任一方式:

- 關閉耳機
- 使用手機的"藍牙"功能表斷開耳機與手機的連接。
- 將耳機移至距離手機10米(約30英尺)以遠的位置。

將已配對耳機重新連接至手機

要連接耳機和手機,請打開耳機,使用手機的"藍牙"功能表建立連接,或按一下多功能鍵 (↵)。

2

您可以設置手機,使其在耳機啓動時自動與耳機建立連接,在手機中,要實現這一目的,請在"藍牙"功能表中更改配對設備設置。

接聽來電

來電時,耳機內發出來電提示音或鈴聲,按下耳機多功能鍵 (↵),即可接聽來電,或使用手機接聽鍵,接聽來電

挂斷通話

按下耳機多功能鍵 (↵) 或使用手機挂斷鍵即可挂斷通話。

拒絕來電

長按2秒耳機多功能鍵 (↵) 或直接用手機挂斷鍵即可拒絕來電。

暫停或保留通話

通話時,長按多功能鍵 (↵) 2秒可保留現有通話,如需恢復通話,則長按多功能鍵 (↵) 2秒。(是否支持本功能,取決于手機)

末位重撥

耳機支持末位重撥功能: 長按2秒耳機多功能鍵 (↵) 即可實現末位重撥。

音樂播放/暫停/選曲

收聽音樂時可以操作多功能鍵 (↵) 播放或暫停,上一曲、下一曲進行選曲等。(短按一次 "+" 為下一曲,短按一次 "-" 為上一曲)

音量調節

音量鍵調節音量的大小: 長按 "+" 3秒為音量增大,長按 "-" 3秒為音量減小(注:當音量達到最大或最小時會有蜂鳴聲提示)

3

Product overview


The Bluetooth Stereo Headset is composed of:

1. MF Button (↵)
2. Microphone (M)
3. Charging Jack (- C +)
4. Speaker (T)
5. Earhook (H)
6. Indicator Light (L)
7. Previous Song/Volume (-) Button (◀)
8. Next Song/Volume (+) Button (▶)

Charging the headset

Your headset uses a rechargeable battery. You must charge the battery fully before using the headset for the first time. Please make sure to turn off the headset before charging.

1. Plugging the charging cradle in the port.



2. The red indicator light remains solid when charging.
3. The fully charging takes approximately 2-3 hours.
4. The indicator light is in solid blue when charging completed.

How to turning on/off:

Turn on: Press the MF button until you hear the beep and the blue indicator light flashes.

Turn off: Press the MF button until you hear the beep and the blue indicator light flashes twice.

4

Pairing with your Bluetooth phone

1. The distance between the Bluetooth headset and your Bluetooth phone would be better within 1 meter when pairing, the closer the better.
2. Ensuring the headset is off.
3. Pressing still the Multifunctional Button until you see the blue light remains solid.
4. Set your Bluetooth phone to discover the headset by following your phone's guide. Typically, the steps involved are going to a "Setup" "Connect" or "Bluetooth" menu on your phone and then select the option to discover Bluetooth devices.
5. Your phone will find the headset and ask if you want to pair with it. Confirming this by pressing "yes" or "ok".
6. Enter passkey "0000", then press "yes" or "ok".

IMPORTANT: If pairing is successful, the indicator light will flash in blue 10 times rapidly before going to flashing every 3 seconds, if unsuccessful, the light remains on, and you will need to reattempt the pairing. While the light will go out if the pairing time takes more than 60 seconds, in that case, you need to turn off the headset and turn it on for pairing again.

Disconnect the headset from the mobile phone

If you want to disconnect the headset from the mobile phone, you can do as below:

- Turn off the headset
- Disconnect the headset from the Bluetooth list the mobile

5

phone.

- Take the headset away from the mobile phone for more than 10 meters (33ft).

Reconnect the paired headset with the mobile phone

If you want to connect the paired headset with the mobile phone, you can do as below:

- Turning on the headset and setting up the connection in the Bluetooth list of your mobile phone
- Pressing once the MF button of the headset. (You have to do the setting in your mobile phone to allow the automatic connection with the paired headset.)

Answering a call

When you hear the ring tone, press the MF button once. If you prefer answering the call by your phone, you can transfer the call from the headset on your phone.

Ending a call

Press and release the MF button once or end call on your phone's keypad.

Answering or rejecting a call when listening to music

If there is ring tone of incoming call when you are listening to music from your phone or PC or other Bluetooth enabled

6

devices, press the MF button to answer the call and press and hold the MF button for 2 seconds to reject the call.

Pause or put a call on hold

During the phone call, just press and hold the MF button for 2 seconds to put a call on hold. If you want to resume to the call, you can also press and hold the MF button for 2 seconds. (This is subject to the mobile phone's feature.)

Redialing the previous call

Press and hold the MF button for 2 seconds until you hear a long beep.

Playing music

When you are listening to the music, you can press the MF button to play music or make a pause and the volume control buttons is to select previous song and next song (Briefly press the Volume + to go to next song and Volume - to go to the previous song.).

Volume control

Press and hold the Volume Control (+) to increase volume and release when it reaches your preferred volume. Vice versa!

7

FCC STATEMENT

1. This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions:

- (1) This device may not cause harmful interference.
- (2) This device must accept any interference received, including interference that may cause undesired operation.

2. Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

NOTE: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation.

This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.

- Increase the separation between the equipment and receiver.

- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.

- Consult the dealer or an experienced radio/TV technician for help.

RF warning statement:

The device has been evaluated to meet general RF exposure requirement. The device can be used in portable exposure condition without restriction.

FCC ID: VO-I4S

This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions:

- (1) this device may not cause harmful interference,
- and (2) this device must accept any interference received, including interference that may cause undesired operation.