



FCC PART 18 MEASUREMENT AND TEST REPORT

For

WENTAI ENTERPRISE CO., LTD

6F-3, No 123, Lane235, Pao-chiao Road, Shintien city, Taipei Hsien, Taiwan

FCC ID: VY5D155D12002

This Report Concerns:		Equipment Type:		
Original Report	t	Electronic Ballast		
Test Engineer:	Amanda Wei A	manda wei		
Report Number:				
Test Date:	2008-02-19			
Report Date:	2008-02-21			
Reviewed By:	EMC Manager: Green Xu Green . Xu			
Prepared By:	Bay Area Compliance Laboratories Corp. (Shenzhen). 6/F, the 3rd Phase of WanLi Industrial Building, ShiHua Road, FuTian Free Trade Zone Shenzhen, Guangdong, China Tel: +86-755-33320018 Fax: +86-755-33320008			

Note: This test report is for the customer shown above and their specific product only. It may not be duplicated or used in part without prior written consent from Bay Area Compliance Laboratories Corp. (Shenzhen). This report **must not** be used by the customer to claim product certification, approval, or endorsement by NVLAP, NIST or any agency of the Federal Government.

TABLE OF CONTENTS

GENERAL INFORMATION	3
PRODUCT DESCRIPTION FOR EQUIPMENT UNDER TEST (EUT)	3
Objective	3
RELATED SUBMITTAL(S)/GRANT(S)	3
TEST METHODOLOGY	
TEST FACILITY	4
SYSTEM TEST CONFIGURATION	5
JUSTIFICATION	
EQUIPMENT MODIFICATIONS	5
EXTERNAL I/O CABLE	
CONFIGURATION OF TEST SETUP	
BLOCK DIAGRAM OF TEST SETUP	
CONDUCTED EMISSIONS	7
MEASUREMENT UNCERTAINTY	7
EUT SETUP	
EMI TEST RECEIVER SETUP	8
TEST EQUIPMENT LIST AND DETAILS	
TEST PROCEDURE	8
TEST RESULTS SUMMARY	
TEST DATA	9
PLOT(S) OF TEST DATA	10

GENERAL INFORMATION

Product Description for Equipment under Test (EUT)

The WENTAI ENTERPRISE CO., LTD's model: WTEB-D155D-120, or the "EUT" as referred to in this report is an Electronic Ballast which measures approximately 9.5 cm L x 9.5 cm W x 3.5 cm H, rated input voltage: AC 120V/60Hz.

* All measurement and test data in this report was gathered from production sample serial number: 0801051 (Assigned by BACL, Shenzhen). The EUT was received on 2008-01-30.

Objective

The following test report is prepared on behalf of *WENTAI ENTERPRISE CO., LTD* in accordance with Part 2, Subpart J, and Part 18, Subparts A, B and C of the Federal Communication Commissions rules and regulations.

The objective of the manufacturer is to determine compliance with FCC Part 18 limits.

Related Submittal(s)/Grant(s)

No related submittal(s).

Test Methodology

All measurements contained in this report were conducted with MP-5, FCC Methods of Measurements of Radio Noise Emissions from ISM Equipment, February 1986. All measurement was performed at Bay Area Compliance Laboratories Corp. (ShenZhen). The radiated testing was performed at an antenna-to-EUT distance of 3 meters.

Test Facility

The Test site used by Bay Area Compliance Laboratories Corp. (Shenzhen) to collect test data is located in the 6/F, the 3rd Phase of WanLi Industrial Building, ShiHua Road, FuTian Free Trade Zone, ShenZhen, Guangdong 518038, P.R. of China.

Test site at Bay Area Compliance Laboratories Corp. (Shenzhen) has been fully described in reports submitted to the Federal Communication Commission (FCC). The details of these reports have been found to be in compliance with the requirements of Section 2.948 of the FCC Rules on November 04, 2004. The facility also complies with the radiated and AC line conducted test site criteria set forth in ANSI C63.4-2003.

The Federal Communications Commission has the reports on file and is listed under FCC Registration No.: 382179 and Industrial Canada registration test site No.: 5500A. The test site has been approved by the FCC for public use and is listed in the FCC Public Access Link (PAL) database.

Additionally, Bay Area Compliance Laboratories Corp. (Shenzhen) is a National Institute of Standards and Technology (NIST) accredited laboratory, under the National Voluntary Laboratory Accredited Program (Lab Code 200707-0).



NVLAP LAB CODE 200707-0

The current scope of accreditations can be found at http://ts.nist.gov/Standards/scopes/2007070.htm .

SYSTEM TEST CONFIGURATION

Justification

The system was configured for testing in a typical fashion (as normally used by a typical user).

Equipment Modifications

No modifications were made to the unit tested.


Local Support Equipment List and Details

Manufacturer	Description	Model	Serial Number	FCC ID
Yaguang	Lamp	2D-55W	N/A	N/A


External I/O Cable

Cable Description	Length (M)	From/Port	То
Unshielded Undetachable AC Power Cable	1.0	EUT	AC Power

Configuration of Test Setup



Block Diagram of Test Setup




Measurement Uncertainty

All measurements involve certain levels of uncertainties, especially in field of EMC. The factors contributing to uncertainties are spectrum analyzer, cable loss, and LISN.

Based on NIS 81, The Treatment of Uncertainty in EMC Measurements, the best estimate of the uncertainty of any conducted emissions measurement at Bay Area Compliance Laboratories Corp. (ShenZhen) is ± 2.4 dB.

EUT Setup



Note: 1. Support units were connected to second LISN.

2. Both of LISNs (AMIN) 80 cm from EUT and at the least 80 cm from other units and other metal planes support units.

The setup of EUT is according with MP-5: 1986 measurement procedure. Specification used was with the FCC Part 18 limits.

The EUT was connected to a 120 VAC/ 60Hz power source.

EMI Test Receiver Setup

The EMI test receiver was set to investigate the spectrum from 450 kHz to 30 MHz.

During the conducted emission test, the EMI test receiver was set with the following configurations:

Test Equipment List and Details

Manufacturer	Description	Model	Serial Number	Calibration Date	Calibration Due Date
Com-Power	L.I.S.N.	LI-200	12005	N/A	N/A
Com-Power	L.I.S.N.	LI-200	12208	N/A	N/A
Rohde & Schwarz	EMI Test Receiver	ESCS30	DE25330	2007-03-26	2008-03-26
Rohde & Schwarz	L.I.S.N.	ESH2-Z5	892107/021	2007-03-26	2008-03-26

^{*} Com-Power's LISN were used as the supporting equipment.

Test Procedure

During the conducted emission test, the EUT power cord was connected to the outlet of the LISN.

Maximizing procedure were performed on the six (6) highest emissions of the EUT.

All data was recorded in the peak detection mode.

Test Results Summary

According to the recorded data in following table, the EUT complied with the FCC Part 18, with the worst margin reading of:

1.80 dB at **1.640 MHz** in the **Hot** conductor mode. (*High Power*) **4.10 dB** at **24.920 MHz** in the **Neutral** conductor mode. (*Low Power*)

^{*} Statement of Traceability: Bay Area Compliance Laboratories Corp. (Shenzhen) attests that all calibrations have been performed in accordance to NVLAP requirements, traceable to the NIST.

Test Data

Environmental Conditions

Temperature:	25 °C
Relative Humidity:	56 %
ATM Pressure:	100.0 kPa

The testing was performed by Amanda Wei on 2008-02-19.

Test Mode: ON (High Power)

Line Conducted Emissions				FCC Part 18.307	
Frequency (MHz)	Amplitude (dBμV)	Detector (PK)	Conductor (Hot/Neutral)	Limit (dBµV)	Margin (dB)
1.640	46.20	PK	Hot	48.00	1.80*
0.465	45.50	PK	Hot	48.00	2.50*
0.630	45.20	PK	Hot	48.00	2.80*
1.725	44.90	PK	Hot	48.00	3.10*
1.810	44.90	PK	Hot	48.00	3.10*
20.475	44.30	PK	Hot	48.00	3.70*
22.945	43.10	PK	Neutral	48.00	4.90
0.465	38.00	PK	Neutral	48.00	10.00
0.630	35.90	PK	Neutral	48.00	12.10
17.615	35.20	PK	Neutral	48.00	12.80
12.335	33.60	PK	Neutral	48.00	14.40
0.800	33.10	PK	Neutral	48.00	14.90

Test Mode: ON (Low Power)

Line Conducted Emissions				FCC Part 18.307	
Frequency (MHz)	Amplitude (dBμV)	Detector (PK)	Conductor (Hot/Neutral)	Limit (dBµV)	Margin (dB)
24.920	43.90	PK	Neutral	48.00	4.10
27.120	43.50	PK	Neutral	48.00	4.50
24.030	41.50	PK	Hot	48.00	6.50
24.710	41.50	PK	Hot	48.00	6.50
27.120	39.80	PK	Hot	48.00	8.20
21.560	39.00	PK	Hot	48.00	9.00
0.530	38.70	PK	Neutral	48.00	9.30
0.680	36.60	PK	Neutral	48.00	11.40
0.830	35.30	PK	Neutral	48.00	12.70
0.450	35.00	PK	Hot	48.00	13.00
0.980	33.10	PK	Neutral	48.00	14.90
0.600	32.00	PK	Hot	48.00	16.00

^{*} Within measurement uncertainty.

Plot(s) of Test Data

Plot(s) of Test Data is presented hereinafter as reference.

19. Feb 08 12:30


FCC 18

EUT: Electronic Ballast M/N: WTEB-D155D-120

Manuf: WENTAI

On(high power)

Operator: On (high power)
Operator: Amanda
Test Spec: AC120V/60HZ H
Comment: Temp: OF The Temp: 25 Humi: 56% Comment:



19. Feb 08 11:10

FCC 18


EUT: Electronic Ballast M/N: WTEB-D155D-120

Manuf: WENTAI

Op Cond: On (high power)

Operator: Amanda

Test Spec: AC120V/60HZ N Comment: Temp: 25 Humi: 56%



19. Feb 08 17:15

FCC 18


EUT: Blectronic Ballast M/N: WTEB-D155D-120

Manuf: WENTAI

Op Cond: On (low power)

Operator: Amanda

Test Spec: AC120V/60HZ H Comment: Temp: 25 Humi: 56%




19. Feb 08 16:35

FCC 18

EUT: Blectronic Ballast M/N: WTEB-D155D-120

Manuf: WENTAI
Op Cond: On (low power)

Operator: Amanda
Test Spec: AC120V/60HZ N
Comment: Temp: 25 Humi: 56%



***** END OF REPORT *****