

H508

- ★ Bluetooth 1.1/1.2/2.0 Compatible
- ★ Support HEADSET and HEANSFREE profile
- ★ One-button operation:Main function Button
- ★ Support:Voice Dial/Redial etc.
- ★ Transmission Range:10m
- ★ Talking Time:4Hours
- ★ Standby Time:110Hours
- ★ Mini Size(L:W:H):33*16*9mm

Bluetooth Headset Using Instruction

● Charge the Headset

Charge H508 for 2Hours

1. Insert the charger to the bottom of Headset,the red indicator which need take one minute at most will be on as charging.After finishing charging which will take about 2hours the red indicator will turn off.
2. Disconnect the charger with headset

● Activate Bluetooth function in Mobile

The bluetooth function in mobile presets as “Shut Off”.Before using headset,please activate the function in your mobile.

Generally the steps as following:

1. Selecting(Menu)>>Setting>>Connecting>>Bluetooth Link>>Setting
2. Roll on to Bluetooth On/Off
3. Press “Change”
4. Press “Select”.If bluetooth on it'll keep working till you turn it off.

● Pair your Mobile with Bluetooth headset

Step A – Put headset under Pairing Status,before using headset,please pair it with your mobile:Hold the answer key for 3seconds till the blue LED on.The bluetooth will be found by other bluetooth devices.

Step B – Set in mobile making it find headset

1. For mostly mobile:Selecting(Menu)>>Setting>>Connect>>Bluetooth Link>>Handsfree>>Searching devices,mobile will list all the bluetooth devices it found.
2. Choosing H508
3. Press for confirmation to pair handsfree mobile.
4. Input passkey:0000
5. Press “ok” to confirm.

Once the pair is successful,the blue LED will flash.

● Test/Use

Now,mobile and headset complete pairing,you can use it to dial or answer any call.

1. Wear bluetooth headset
2. Dial the number in your mobile and press”Send”
3. If the pair is successful,you will hear the ringing.After this successful pairing,no

need repeat the above steps of setting if you use again in future.

● Direction for Functions

Power on and Power off

Turn on the headset,press red “answer”key till LED flash,then release it.

Turn off the headset,Press and hold “answer”key till LED flash rapidly.

For saving power,lease turn off your headset if not using for a long time.

Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

This device complies with Part 15 of the FCC Rules.

Operation is subject to the following two conditions:

- (1) this device may not cause harmful interference, and
- (2) this device must accept any interference received, including interference that may cause undesired operation.

Volume adjust

1. The headset is preset at the highest volume.
2. Please adjust it in your mobile to reach a ideal effect.

Making a conversation

Function	Operation
End a call	Tap “answer”key
Answer a call	Tap “answer”key
Redial last call	double tap “answer”key

Indicator (offer the information for headset status)

Insert charger	
Indicator	Status
Red LED on	Charging
Red LED off	complete charging
Without charger	
Indicator	Status
Off	Off
On(Blue LED)	Pairing

Indicator (Offering information for headset status)

Blue LED flash	Pairing successfully
Blue LED flash every 3seconds (0.1second on,2.9second off)	Connected (In conversation)
Blue LED flash every 3seconds (0.1second on,2.9second off)	Standby (No conversation)

Red LED flash	Low power

Tones reminder

Tones	Status
Audio Tone	Last call redial
Audio Tone	Low power
Ringing	Incoming call
Single high tone	Pair successfully
Audio Tone	On/Off