


front side
正面

 <p>HAVIT SK889BT MULTI-COLOR AMBIENT LIGHT BLUETOOTH SPEAKER PRODUCT MANUAL</p>	<p>Packing list:</p> 	<p>Product structure:</p> 	<p>Power ON/OFF 1.Long press the power button for three seconds to turn on; 2.Long press the power switch for three seconds to turn off.</p> <p>Bluetooth connection 1.Turn on the Bluetooth speaker, the breathing light flashes slowly. 2.Then active the Bluetooth of your phone and search for "HAVIT SK889BT". Click manually to connect. 3. Since the speaker can automatically reconnect to the last paired device. When the Bluetooth of your device turns on. (Just turn on the speaker), it will automatically reconnect.</p> <p>Answer incoming calls Press the power button to answer incoming calls. Tip: Since some mobile phones default to answer calls via their own receiver, please refer to the instructions of your phone and set on your phone.</p>	<p>End the call Press the power button once to end the current call.</p> <p>Refuse incoming calls Long press the power button for 2s to reject when there comes a call.</p> <p>Last number redial Dual press the power button to redial the last calling number.</p> <p>Mode switching Long press play/pause button to select mode. (Bluetooth /TF card /FM)</p> <p>light effect switching Short press the power button to switch the light effect of the speaker. There are four lighting modes.</p> <p>Micro TF card mode Insert a TF card, the speaker will automatically recognize and automatically broadcasts MP3 format music in it.</p>
<p>FM mode 1. Insert the provided Type-C cable to the speaker micro USB slot as an antenna. Long press the play pause button to enter FM mode 2. Dual press the play/pause button to activate automatic channel search. 3. Dual press the play/pause again for 2 seconds to stop the search 4. Long press the "+" / "-" to select channel.</p> <p>Clearing pairing Records Press the play/pause button three times to clear the pairing records</p> <p>Music playing 1. Short press the play/pause button to pause/play; 2. Long press the "-" for PREV; 3. Long press the "+" for NEXT; 4. Short press the "-" for VOL-; 5. Short press the "+" for VOL+ .</p>	<p>True Wireless Stereo (TWS) Fit for two SK889BT speakers You can connect two SK889BT speakers as a pair for stronger stereo and surrounding effect. 1. Make sure the Bluetooth function is OFF on your Bluetooth player; 2. Turn on two speakers; 3. Double-click the play/pause button of a speaker at will (the double-click is the host), there will be a "dong" sound when double-clicking, wait for about 1 minute after the prompt sound appears, and a "di" sound will appear when the pairing is completed, indicating that the pairing has been successful. 4. Then active the Bluetooth of your phone and search for "HAVIT SK889BT". Click manually to connect. 5. Double click the play pause button again TWS to disconnect.</p> <p>Charging 1. As product has built-in non-removable and rechargeable battery, please use the provided Type-C cable to charge. 2. Please choose the charger that is certified by</p>	<p>the regular manufacturer. 3. The battery performance may decrease as repeating charging and using the speaker. It's a normal phenomenon for all rechargeable batteries. 4. The power LED lights up red when charging and goes off when charging is complete.</p> <p>Specification: Bluetooth version: V5.3 Rated power: 7W Peak power: 8W Speaker size: 57MM Battery: 3.7V/1500mAh Play time: 6H(Medium volume) Charging time: 4H Support: BT, TWS, TF, hands-free calls, FM Wireless working range: 10M (without obstacles) Input voltage: DC5V/1A Charging method: Type-C Product size: 100*138mm Material: ABS+PC</p>	<p>Warnings: 1. Please follow the instruction to operate. 2. Please charge the product with input power below 5V/1A, in order to protect the battery; 3. Please do not use this product in the near water. Do not immerse this product in any liquid or splash any liquid on this product. 4. Please store or use the product in a normal temperature environment. 5. Please keep the product from heat source, such as radiators, hot air regulators, stoves, or other heat generating instruments. As it is not anti-high temperature. 6. Don't jam the ports of the product, such as charger port, LED port and microphone etc. 7. In order to protect your hearing and extend the speaker service life, it is not recommended to adjust the volume to the maximum level for a long time. 8. Whatever reasons damage the product, please feel free to contact our after-sales staff in time rather than repair by yourself. Otherwise, you will accept without after-sales service.</p>	<p>Any Changes expressly or modifications not approved by the party responsible for compliance could void the user's authority to operate the equipment. This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation. Note: This equipment has been tested and found to comply with the limits of a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures: —Reorient or relocate the receiving antenna. —Increase the separation between the equipment and receiver. —Connect the equipment into an outlet on a circuit different from that to which the receiver is connected. —Consult the dealer or an experienced radio/TV technician for help. FCC Radiation Exposure Statement: The device has been evaluated to meet general RF exposure requirement. The device can be used in portable exposure condition without restriction.</p>

材质: 128g双铜纸 双面印刷, 风琴折

印刷色号(Printing color number): C:0 M:0 Y:0 K:70

尺寸(Size): 55 X 77 mm